Electronic Conduction in Disordered Carbon Materials

by

Chun Yee Cheah

A thesis
submitted to the Victoria University of Wellington
in fulfilment of the requirements for the degree of
Doctor of Philosophy
in Physics

Victoria University of Wellington

2015

Abstract

Graphene, consisting of a single layer of carbon atoms, is being widely studied for its interesting fundamental physics and potential applications. The presence and extent of disorder play important roles in determining the electronic conduction mechanism of a conducting material. This thesis presents work on data analysis and modelling of electronic transport mechanisms in disordered carbon materials such as graphene. Based on experimental data of conductance of partially disordered graphene as measured by Gómez-Navarro et al., we propose a model of variable-range hopping (VRH) – defined as quantum tunnelling of charge carriers between localized states – consisting of a crossover from the two-dimensional (2D) electric field-assisted, temperature-driven (Pollak-Riess) VRH to 2D electric field-driven (Shklovskii) VRH.

The novelty of our model is that the temperature-dependent and field-dependent regimes of VRH are unified by a smooth crossover where the slopes of the curves equal at a given temperature. We then derive an analytical expression which allows exact numerical calculation of the crossover fields or voltages. We further extend our crossover model to apply to disordered carbon materials of dimensionalities other than two, namely to the 3D self-assembled carbon networks by Govor et al. and quasi-1D highly-doped conducting polymers by Wang et al. Thus we illustrate the wide applicability of our crossover model to disordered carbon materials of various dimensionalities.

We further predict, in analogy to the work of Pollak and Riess, a temperature-assisted, field-driven VRH which aims to extend the field-driven expression of Shklovskii to cases wherein the temperatures are increased. We discover that such an expression gives a good fit to the data until certain limits wherein the temperatures are too high or the applied field too low. In such cases the electronic transport mechanism

crosses over to Mott VRH, as expected and analogous to our crossover model described in the previous paragraph.

The second part of this thesis details a systematic data analysis and modelling of experimental data of conductance of single-wall carbon nanotube (SWNT) networks prepared by several different chemical-vapour deposition (CVD) methods by Ansaldo et al. and Lima et al. Based on our analysis, we identify and categorize the SWNT networks based on their electronic conduction mechanisms, using various theoretical models which are temperature-dependent and field-dependent. The electronic transport mechanisms of the SWNT networks can be classed into either VRH in one- and two-dimensions or fluctuation-assisted tunnelling (FAT, i.e. interrupted metallic conduction), some with additional resistance from scattering by lattice vibrations.

Most notably, for a selected network, we find further evidence for our novel VRH crossover model previously described. We further correlate the electronic transport mechanisms with the morphology of each network based on scanning electron microscopy (SEM) images. We find that SWNT networks which consist of very dense tubes show conduction behaviour consistent with the FAT model, in that they retain a finite and significant fraction of room-temperature conductance as temperatures tend toward absolute zero. On the other hand, SWNT networks which are relatively sparser show conduction behaviour consistent with the VRH model, in that conductance tends to zero as temperatures tend toward absolute zero. We complete our analysis by estimating the average hopping distance for SWNT networks exhibiting VRH conduction, and estimate an indication of the strength of barrier energies and quantum tunnelling for SWNT networks exhibiting FAT conduction.

Dedicated to the memory of my mother

Guat Lay Tan

Acknowledgments

I thank Emeritus Prof Alan Kaiser for excellent supervision, and our experimental collaborators Assoc Prof Cristina Gómez-Navarro and Dr Viera Skákalová for sharing their data with us for analysis and modelling. I acknowledge Prof Uli Zülicke for support as Head of School and second supervisor, and the Theme 2 group of the MacDiarmid Institute for Advanced Materials and Nanotechnology – in particular Dr Simon Granville and Prof Roger Reeves – for helpful discussions.

Financial support for this thesis is furnished by a three-year doctoral scholarship from the MacDiarmid Institute for Advanced Materials and Nanotechnology; a three-month Victoria PhD Submission Scholarship from Victoria University of Wellington; as well as Prof Alan Kaiser's research funding from the Royal Society of New Zealand and the School of Chemical and Physical Sciences, Victoria University of Wellington. My postgraduate experience has been enriched by being Sessional Assistant to Prof Gillian Turner, Dr Natalie Plank, Dr Howard Lukefahr and Mr John Hannah.

I would additionally like to thank the members of my examination committee, namely Prof Paul Morris (chair), Dr Simon Granville, Assoc Prof Martin Allen (University of Canterbury) and Prof Oleg Sushkov (University of New South Wales, Australia).

Contents

Abstract	ii
Acknowledgments	v
CHAPTER 1. Introduction to carbon materials	1
1.1 Graphite intercalation compounds	2
1.2 Graphene	4
1.2.1 Discovery of graphene	
1.2.2 Crystal structure and electronic properties of pure graphene	
1.2.3 Potential applications of graphene-based materials	
1.2.4 Reduced graphene oxide: chemically produced graphene	
1.2.4.1 Recent advances in the synthesis of reduced graphene oxide	
1.3 Carbon nanotubes	15
1.3.1 Discovery of carbon nanotubes	
1.3.2 Commercial and emerging technologies based on carbon nanotubes	
1.3.3 CVD-grown single-wall carbon nanotubes	
CHAPTER 2. Theory of electronic transport in disordered conductors	19
2.1 Variable-range hopping	20
2.1.1 Variable-range hopping and Anderson localization	
2.1.2 Temperature-dependent (Mott) variable-range hopping; its derivation	

2.1.3	Electric-field assisted, temperature-driven (Pollak-Riess) variable-range hopping	
2.1.4	Electric-field driven (Shklovskii) variable-range hopping	
2.1.5	Topical literature review	
2.1.5.1	Differing values of the Mott coefficient	
2.1.5.2	Temperature (in-)dependence of the Mott pre-exponential factor	
2.1.5.3	Existing variable-range hopping crossover models	
2.1.5.4	Comments on competing model by Pipinys and Kiveris	
2.2	Fluctuation-assisted tunnelling	35
2.2.1	Temperature-driven (Sheng) fluctuation-assisted tunnelling	
2.2.2	Electric field-driven (Kaiser-Park) fluctuation-assisted tunnelling	
2.2.3	Graphical comparison of fluctuation assisted tunnelling and variable-range hopping	

CHAPTER 3. Experimental background: synthesis methods of materials under study **39**

3.1	Reduced graphene oxide – Gómez-Navarro et al.	39
3.2	3D self-assembled carbon networks – Govor et al.	41
3.3	Quasi-1D highly conducting polymers – Wang et al.	42
3.4	Single-wall carbon nanotube networks by various synthesis methods	42
3.4.1	Direct grown carbon nanotube networks via spray-coated catalysts – Ansaldo et al.	
3.4.2	Direct grown carbon nanotube networks via patterned catalysts – Lima et al.	
3.4.3	Post-grown carbon nanotube networks – Andrade et al.	

CHAPTER 4. Methodology for data analysis and modelling **46**

4.1	Data digitization – Grafula	46
4.2	Data analysis	48
4.2.1	Curve fitting and modelling – Origin	
4.2.1.1	Chi-square and adjusted R^2 as indicators of quality of fit	

4.2.1.2	Coding in C language	
4.2.2	Numerical calculations – MATLAB	
CHAPTER 5. Results and discussion: variable-range hopping transport in disordered carbon materials		58
5.1	A model of crossover from temperature-dependent to field-dependent variable-range hopping transport	59
5.1.1	Partially disordered graphene	
5.1.2	3D carbon networks	
5.1.3	Quasi-1D highly-doped conducting polymers	
5.2	Investigation into theoretically predicted equivalence of temperature and field scaling parameters	84
5.3	A proposal for a temperature-assisted, field-driven VRH expression	87
CHAPTER 6. Exploratory work		92
6.1	A model consisting of the Pollak-Riess term, and its inverse	92
6.2	A ‘field-dependent fluctuation assisted tunnelling’ model	94
CHAPTER 7. Results and discussion: electronic transport mechanisms in single-wall carbon nanotube networks		97
7.1	Overview of the electrical data of the nanotube networks	98
7.2	Electronic transport mechanisms of the nanotube networks	102
7.2.1	Direct grown carbon nanotube networks via spray-coated catalysts prepared by Ansaldo et al.	
7.2.1.1	Correlation between electronic transport and morphology	
7.2.2	Direct grown carbon nanotube networks via patterned catalysts prepared by Lima et al.	
7.2.3	Post-grown carbon nanotube networks prepared by Andrade et al.	
7.3	Further analysis	120
7.3.1	Mean hopping distances in VRH networks	
7.3.2	Barrier heights in FAT networks	

CHAPTER 8. Conclusions	124
8.1 Crossover from temperature-dependent to field-dependent variable-range hopping conduction in partially disordered graphene	124
8.2 Conduction in single-wall carbon nanotube networks: further evidence for our crossover model	130
8.3 Outlook	133
References	134
APPENDIX. Publications, presentations and publicity	146

CHAPTER 1. Introduction to carbon materials

The overarching idea of this thesis is the physics of the electronic transport of disordered carbon materials, including graphene and carbon nanotubes. Why model electronic transport? It allows us not only to *identify* the transport mechanism, but also to *compare* between different mechanisms. In addition, it also affords us the power to *predict*, within reasonable limits, the conduction behaviour of similar samples; similarly for example, in terms of their fabrication method, morphology, or chemistry. (The author acknowledges the talk by V. P. Ting of the University of Bath, UK at VUW, Feb 2014 in which the motivations for modelling were presented in the concise manner adapted here.) The presence and severity of disorder in a material plays an important influence in its electronic conduction mechanism. In a quote attributed to materials scientists Sir Charles Frank or Prof Sir Colin Humphreys, “Crystals are like people: it is the defects in them that make them interesting”.

Sir Nevill Mott's humble and practical nature is evident in his Nobel Lecture of 1977, in which he said, “I myself am neither an experimentalist nor a real mathematician; my theory stops at Schrödinger equation. What I’ve done in this subject is to look at all the evidence, do calculations on the back of an envelope and say to the theoretician, ‘if you apply your techniques to this problem, this is how it will come out’ and to the experimentalists just the same thing. This is what I did for $T^{1/4}$ [i.e. 3D variable-range] hopping...” [Mott 1977, p.10].

In a large manner, the approach of this thesis is the same, i.e. as an interface between established theories and experimental data. The validity or otherwise of the

theories is reflected by the experimental data, and vice versa through systematic data analysis and modelling. Among the theoretical models of electronic conduction that will be used in this thesis is Mott's variable-range hopping, in later years extended by other scientists to account for the influence of sufficiently high applied electric field. There is also a complementary theoretical model of fluctuation assisted tunneling first introduced by Ping Sheng, and these two models will be compared and contrasted in this thesis.

To quote Prof. Olga Botner, member of the Nobel Committee for Physics, who was interviewed after the announcement of 2013 Nobel Prize in Physics (video: <http://www.nobelprize.org/mediaplayer/index.php?id=1955>, from time 1 minute, 10 seconds onward), “There are a lot of theories out there, [and] there are a lot of theorists out there, but in the end it's the interplay between experiment and theory which decides what nature has chosen...”

In this chapter I will introduce and review the recent progress of carbon materials. In the next chapter, the theory of electronic conduction in disordered conducting materials will be reviewed and discussed. This will be followed by the experimental background of the analyzed samples in this thesis in Chapter 3. Data analysis methodology is presented in Chapter 4, followed by results and discussion in Chapters 5 and 6 for the electronic transport mechanisms in disordered carbon materials and Chapter 7 for carbon nanotube networks. Chapter 8 recapitulates the main results from this work.

1.1 Graphite intercalation compounds

A popularly researched material in the late 1970s until the late 1990s is graphite intercalation compounds (GICs). A ‘predecessor’ carbon material that was to foreshadow the excitement to come with graphene, a GIC is a material wherein a graphite host is combined with a “properly selected” [Inagaki 1989, p. 1560] intercalate material in order to achieve a high electrical conductivity.

“Insertion” is a general term to mean the introduction of atoms, ions or molecules into a host lattice. “Intercalation” is a more specific term wherein the host lattice consists of two-dimensional (2D) layers [Özmen-Monkul 2010, p.1]. Expansion occurs wherein the layered host increases in inter-layer distance to incorporate the intercalates [Özmen-Monkul 2010, p.1].

A notable example of GICs is the pentafluoride compound, AsF_5 , exhibiting electrical conductivity nearing $1 \times 10^8 \text{ S/m}$ [see Inagaki 1989, Fig. 1], which is higher than the electrical conductivity of copper which is $6 \times 10^7 \text{ S/m}$ [Giancoli 2009, p. 658]. Graphite intercalated with metal chlorides result in electrical conductivity comparable to that of copper [Inagaki 1989]. Work on transport properties of GICs usually report the in-plane electrical conductivity normalized to that of pure graphite [see Dresselhaus et al. 1977, Fig. 1].

A review of the possible applications of GICs is contained in [Inagaki 1989]. These applications can be divided broadly into five categories [Inagaki 1989, Table 1]: highly conductive materials, battery electrodes, organic synthesis catalysts, materials for storage and isotope-separation of hydrogen and “others”.

A short history on the research of GICs is presented in [Inagaki 1989, Table 2]. Prior to 1974, research focused on synthesis of new compounds. From then onward, the focus turned to new physics and engineering; the former spurred by the unexpected high conductivity of the pentafluorides (also known as a fluoro-metalate intercalated GIC first reported by Vogel et al. [Vogel et al. 1977; Özmen-Monkul 2010, p. 29]), and the latter motivated by the commercialization of the lithium battery with graphite fluoride (i.e. $\text{Li}/(\text{CF})_n$) [Inagaki 1989, p. 1561]. [Vogel et al. 1977] found that electrical conductivity of C_xAsF_y at room temperature exceeded that of copper [Özmen-Monkul 2010, p.29].

At the time of writing of Inagaki’s 1989 review, GICs started losing their allure for scientists, who were then switching en masse to research on superconductors instead, due to the discovery of high-temperature superconductive ceramics in 1987 [Inagaki 1989, p. 1561 and Table 2]. However in the materials science and chemistry community, the synthesis of new GICs still holds interest to the present day, e.g. the doctoral dissertation of [Özmen-Monkul 2010].

It is notable that intercalation has very recently attracted renewed interest as an alternative method to synthesize graphene. It has been found [Kovtyukhova et al. 2014] that graphite can be reversibly intercalated by certain non-oxidizing acids. Once the graphite is intercalated, graphene can be exfoliated. This synthesis method does not involve oxidation or reduction [Kovtyukhova et al. 2014] of graphene, in contrast to the reduced graphene oxide material under study in this thesis (see Chapter 3.1).

1.2 Graphene

1.2.1 Discovery of graphene

As a pencil is used to write on paper, graphite, a 3D allotrope of carbon consisting of stacks of graphene layers weakly coupled by van der Waals forces [e.g. Castro Neto et al. 2009], is transferred onto the surface material. Despite the pencil being invented in 1565 [Petroski 1992], graphene was only isolated in 2004 [Novoselov et al. 2004]. The main reason for the long time between the invention of the pencil and the isolation of graphene was that the latter was not expected to exist in a free state [Novoselov et al. 2005a] until then.

In a strict sense, two-dimensional crystals cannot exist at finite temperatures because they are extremely soft and flexible and, in fact, on the verge of structural instability [Katsnelson and Geim 2008]. However, this apparent contradiction is resolved by recognizing that freely suspended graphene is in fact, at room temperature, not strictly a plane sheet but corrugated, with ripples in the out-of-plane direction, which seem to stabilize the system [Paufler 2013]. Rajput and colleagues have reported that ripples intrinsically form in a graphene-semiconductor Schottky junction field [Rajput et al. 2013] (more details on Rajput's work will be presented in a later section, Chapter 1.2.3).

The effect of ripples on large graphene nanoflakes have also been studied theoretically by [Barnard and Snook 2012]. Barnard and Snook via DFT studies, found that mechanical, thermodynamic and electronic properties are unaltered by ripples; however only fundamental differences in wavefunctions occur between a flat and

rippled structure. Further to this, [Lanza et al. 2013] report methods to tune the wrinkles in CVD-grown graphene flakes on copper. They do this by optimizing the transfer process and tuning the morphology of the substrate, namely by improving the graphene-substrate adhesion to minimize compressive strain in the graphene [Lanza et al. 2013].

It is interesting though, that already in 1947 a paper on the band structure of graphene has been published [Wallace 1947]. At that time however, the study of the individual layers served as a starting point to study graphite. This approximation was justified by the spacing of lattice planes of graphite which are large compared to the hexagonal spacing in each layer [Wallace 1947].

Novoselov et al. [2004] mechanically exfoliated graphene (alternatively mentioned in the paper as “repeated peeling”, this method of mechanical exfoliation is colloquially referred to as the “Scotch-tape method”) and deposited it on top of an SiO_2 substrate. It was then observed that different layers of graphene showed up differently coloured under an optical microscope. As examples, a SEM image of different layers of graphene on SiO_2 is reported here [Hill et al. 2006, Fig. 2], while an AFM image of different layers of graphene on SiO_2 can be found here [Gomez-Navarro et al. 2007, Figs. 1(a) and (b)].

This first isolation of graphene in 2004 [Novoselov et al. 2004] was rapidly followed-up by back-to-back articles in *Nature* the following year [Novoselov et al. 2005b; Zhang et al. 2005] by Geim and Novoselov’s group in the UK and Kim’s group in the US. Reviews of the properties of graphene soon followed [Geim and Novoselov 2007; Castro Neto et al. 2009] and Geim and Novoselov were awarded the Nobel Prize in Physics in 2010.

1.2.2 Crystal structure and electronic properties of pristine graphene

An excellent pedagogical description of graphene is the following excerpt from the press release for the 2010 Nobel Prize in physics (*emphasis mine*): “As a material it is completely new – not only the thinnest ever but also the strongest. As a *conductor of*

electricity it performs as well as copper. As a conductor of heat it outperforms all other known materials. It is almost completely transparent, yet so dense that not even helium, the smallest gas atom, can pass through it.” (http://www.nobelprize.org/nobel_prizes/physics/laureates/2010/press.html)

Graphene consists of a single layer of carbon atoms, with each carbon atom connected via covalent bonds to three other carbon atoms, at 120° angles between each bonded pair and with bond lengths $1.42 \text{ \AA}$ [see e.g. Geim and MacDonald 2007, Box 1; Terrones et al. 2012, p. 3], see Fig. 1-1. This configuration of covalent bonds is termed as sp^2 hybridization. The energy required to displace one carbon atom with sp^2 hybridization arrangement of graphitic lattice is between 15 and 20 eV [Banhart 1997; Terrones et al. 2012, p. 10].

Fig. 1-1. Atomic model of pristine graphene showing its hexagonal crystal structure. Each carbon atom is connected via covalent bonds to three other carbon atoms at 120° angles and with bond lengths $1.42 \text{ \AA}$. Image by AlexanderAIUS reproduced under the Creative Commons license BY-SA.

The lattice structure of graphene can be considered as consisting of two triangular sublattices in which electronic states form two energy bands, connected by inversion symmetry, which intersect at K and K' points in the Brillouin zone. The connected nature of the energy bands means an absence of an electronic bandgap, which can be understood as a “gapless semiconductor” [Geim and MacDonald 2007], see Fig. 1-2. Close to these crossing points, the electron energy $E(k)$ has a linear dependence on the wave vector k [e.g. Peres 2010, p. 2675; Das Sarma et al. 2011, Fig. 2(c)]:

$$E(k) = \pm \hbar v_F k \quad (1.1)$$

This linear dependence on the wave vector is described by the relativistic Dirac equation [e.g. Peres 2010, p. 2675]:

$$H_K = v_F \boldsymbol{\sigma} \cdot \mathbf{p} \quad (1.2)$$

and thus electrons and holes in monolayer graphene are called Dirac fermions. Large mean free paths with carrier mobilities exceeding $10^5 \text{ cm}^2/\text{V.s}$ have been reported [e.g. Terrones et al. 2012]. The 2D character and Dirac fermion behaviour can be lost if additional layers are added to the graphene [e.g. Terrones et al. 2012, p. 3].

Fig. 1-2. Sketch shows the connected energy bands of graphene. The conduction and valence bands intersect at K and K' points in the Brillouin zone.

For practical samples, disorder is present in many forms. Electronic properties of graphene in the presence of disorder are discussed in Chapter 2. In terms of crystal structure, realistic graphene cannot be infinite but rather contain edges. These edges could be of either two types: zigzag or armchair. Molecular models of these different edge morphologies can be found in [Terrones et al. 2012, Fig. 2].

The study of electronic transport in graphene, notably monolayer and bilayer graphene, has been of such great interest that in recent years an updated review is published every year [Das Sarma et al. 2011; Peres 2010; Castro Neto et al. 2009]. A review on electronic transport with emphasis on disorder in graphene is also available [Mucciolo et al. 2010].

The most interesting property of graphene is that its majority carrier concentration, be it holes or electrons, can be controlled by a gate voltage [see e.g. Geim and Novoselov 2007, Fig. 3; also Novoselov et al. 2004, Fig. 2(c)]. A positive gate voltage induces electrons as the majority charge carriers, while a negative gate voltage induces holes as the majority charge carriers.

Very recently, three research groups independently reported that cadmium(II) arsenide, Cd_3As_2 , has the same characteristic electronic structure as that found in graphene [Borisenko et al. 2013; Liu et al. 2014; Neupane et al. 2014]. Specifically, the material exhibits the characteristic electronic structure wherein conduction and valence band energies touch each other at certain points in momentum space, so-called the Dirac points. Thus, in terms of electronic structure, this material can be regarded as the bulk, or 3D, analog of graphene.

It is interesting to mention that besides graphene, topological insulators have a similar Dirac-point electronic structure giving rise to similar physics between graphene and topological insulators. Unlike graphene however which has spin degeneracy, topological insulators do not [see e.g. Avdoshenko et al. 2013]. Further comments are beyond the scope of this thesis.

1.2.3 Potential applications of graphene-based materials

This section must be prefaced with the caveat that possible applications of graphene change very rapidly compared to the advance in knowledge of its fundamental properties [Paufler 2013]. A research group has issued an early caveat that the ability of graphene oxide to float around in water (as used in the Hummers method to produce reduced graphene oxide, see Chapter 3.1) might pose a toxicity risk to humans and animals [Bourzac 2014; Lanphere et al. 2014].

A large motivating factor in the early days of graphene studies is that since silicon-based semiconductor electronic devices are approaching their (fundamental) performance limitations, there is hence a demand for a new electric field-controllable

material to replace silicon. This is pointed out by the Geim group in their seminal paper on graphene [Novoselov et al. 2004]. Until 2007, most efforts have been focused in the direction of graphene-based electronics funded by companies such as Intel and IBM [Geim and Novoselov, 2007]. In the same paper, the authors offered the catchphrase ‘Graphenium Inside’ in analogy to Intel’s popular marketing slogan ‘Intel Inside’ [Geim and Novoselov, 2007].

However, a revised and more cautious assessment is given in Geim’s later review: “It is premature to predict whether graphene will indeed emerge as the replacement to today’s Si circuit” [Geim and MacDonald, 2007]. In the meantime, graphene could find new applications which are unique from silicon, but closely related to carbon nanotubes, such as in composite materials and as solid-state gas sensors [Geim and Novoselov 2007].

As the so-called Kroemer's Lemma of New Technology says, “The principal applications of any sufficiently new and innovative technology always have been – and will continue to be – applications *created* by that technology” [Kroemer 2003; 2001]. The emphasis on ‘created’ is by Kroemer, to highlight that rather than replacing existing technologies, graphene would create niche applications of its own. A review by Morozov et al. mentioned “the first prototypes of future graphene-based devices” including “room-temperature field transistors with ballistic transport, extremely sensitive gas sensors, one-electron graphene transistors, liquid-crystal displays and solar batteries (in which graphene is used as a transparent conducting electrode), spin transistors” etc. [Morozov et al. 2008].

In fact, graphene finds most promise for the first commercial applications in optics devices, according to [Grigorenko et al. 2012]. Graphene can fulfil multiple functions in photovoltaic devices: as the transparent conductor window, photoactive material, channel for charge transport, and catalyst [Bonaccorso et al. 2010].

Even more recently, instead of utilizing graphene’s excellent in-plane conductivity, it has been found to be useful also as a thin electrically insulating barrier, taking advantage of the fact that although very conductive in plane, graphene exhibits poor conductivity perpendicular to the plane [van ’t Erve et al. 2012]. Also recently, a one-dimensional metallic-semiconducting-metallic junction made entirely from

graphene achieving a level of precision beyond modern lithographic limits has been reported [Hicks et al. 2012].

However, integration of graphene into an established semiconductor fabrication might not be so straight-forward. It has been recently found that intrinsic ripples form in a graphene-semiconductor Schottky junction, which influences the homogeneity of the electric field [Rajput et al. 2013]. Rajput and colleagues [2013] performed STM studies and first-principles (DFT) calculations on CVD-grown graphene transferred on semiconductor surfaces of opposite polarization.

It has been argued by Kelly [Kelly 2013] that graphene "will struggle to ever achieve competitive commercial applications". Kelly calculated – using semiconductor device theory – that the frequency and power parameters of graphene compare unfavourably to silicon. The calculations however are complicated by the fact that intrinsically graphene does not have a bandgap. Kelly repeats this claim in a later paper [Kelly 2014]: "while [graphene] has some attractive properties, it does not outpace any incumbent electronic or optical technologies with which it has been compared."

Of course, Kelly had assumed first and foremost that graphene will be directly replacing silicon technology and showed that this is not viable as acknowledged in the end of the article [Kelly 2013] itself, that commercially successful applications "will have to come from outside mainstream electronics and optoelectronics" [Kelly 2013]. This view is shared by [Novoselov et al. 2012]: "It is unlikely that graphene will make it into high-performance integrated logic circuits as a planar channel material within the next decade because of the absence of a bandgap. However, many other, less stringent, graphene electronic applications are being developed, using the available (probably not ideal in terms of quality) material." More viably, graphene has been shown to be incorporable with silicon technology by Vaziri, Mehr, Lippert et al. (see next paragraphs).

Mehr et al. performed atomistic, ab-initio simulations of a graphene base transistor [Mehr et al. 2012]. The main advantage of using graphene as a base in a hot-carrier transistor in a bipolar junction transistor configuration is that a transport barrier exists akin to a bandgap, compared to other works which use graphene as the channel in a field-effect transistor wherein such a transport barrier does not exist. Due to the transport barrier, Mehr et al. show that such a device is suitable for logic operations.

Another advantage of using graphene is that being monatomic thin, ballistic transport is achieved traversing the material. In addition, graphene is chemically inert and unreactive to interface materials.

These ab-initio simulations of [Mehr et al. 2012] are experimentally realized by their collaborators [Vaziri et al. 2013] and this device concept has earned Mehr et al. a very recent U.S. patent for the so-called ‘graphene base transistor’ [Mehr et al. 2014]. The demonstration of this device is remarkable because it is compatible with current established silicon fabrication technology.

Another recent development from the same group, in line with their goal of incorporating graphene into established silicon fabrication methods, is the growth of graphene on germanium substrates deposited on silicon wafers [Lippert et al. 2014]. Germanium acted as a buffer layer between the graphene and silicon. It was found that graphene deposited on germanium had much higher quality than if deposited on SiO_2 at a temperature of 900 deg. C [Lippert et al. 2014, Fig. 1]. Despite the higher quality, the resulting graphene film still contains a high density of defects based on electrical measurements [Lippert et al. 2014, Fig. 6], and due to these disorders, the transport mechanism across the disordered graphene is explained by variable-range hopping (see Chapter 2.1) and in fact the authors have cited our paper [Cheah et al. 2013] in support of their observed electronic conduction.

Very recently, a new method has emerged to grow graphene on the side walls of silicon carbide (SiC), which is then heated to evaporate silicon atoms leaving behind the graphene. This means there are no dangling bonds or rough edges to scatter electrons, which result when sheets of graphene are cut into narrow ribbons to form wires of a nanocircuit. In the epitaxial graphene nanoribbons produced via the former method, the scientists claim single-channel ballistic charge transport [Baringhaus et al. 2014].

Graphene-based devices are fabricated by supporting the graphene on a substrate e.g. glass. This results in the suppression of graphene's high thermal conductivity. Recent advances have found multilayered graphene can recover some of the high thermal conductivity that is otherwise lost [Sadeghi et al. 2013]. Other methods are using new dielectric supports e.g. boron nitride, which has a comparable crystal structure to graphene. The similar crystal structure might lead to better thermal conductivity and less phonon scattering when boron nitride is used to support graphene,

but more work is needed to improve the BN/graphene interface quality to increase conductance across the interface [Chen et al. 2014].

The scattering of charge carriers at grain boundaries (GBs) could degrade electrical conduction. [Tsen et al. 2012] categorize GBs into two types: well-stitched GB which results from a fast growth rate, and overlapped GB resulting from a slow growth rate. It is found that small-overlapped GBs hinder transport as electrons scatter off them. On the other hand, large-overlapped GBs exhibit improved conductance due to the graphene being bilayer instead of monolayer graphene; however the film is much weaker in this configuration. The most promising of all are well-stitched GBs which are found to not be the dominant scattering mechanism to affect large-scale device transport [Tsen et al. 2012].

[Cruz-Silva et al. 2014] recently reported strong, stretchable fibers made from graphene oxide that can be knotted into a yarn. The graphene oxide fibers show high robustness to elongation and knotability, and is claimed to be stronger than other carbon fibers. Cruz-Silva et al. propose that removing the oxide (i.e. reducing the graphene oxide into graphene) and doping with silver nanorods would improve the conductivity of the yarn for power transfer applications as a light-weight candidate to replace traditional copper lines.

1.2.4 Reduced graphene oxide: chemically produced graphene

It is known that in a pristine graphene sample, electrons are delocalized and move as in a metal. In a small scale lab production, graphene can be produced by mechanical exfoliation [Lee et al. 2008] which exhibits intrinsic strength and elastic properties.

Despite the vast potential of electronic applications of graphene, progress is hampered by the limited availability of large graphene sheets of high quality. To quote [Lee et al. 2008]: “The intrinsic strength reported here [for mechanically exfoliated monolayer graphene] serves as a benchmark for structural and mechanical applications,

although the strength of macroscopic graphitic materials is still limited by the presence of defects and grain boundaries.”

A promising solution to this problem comprises chemical conversion of readily accessible graphene oxide into graphene; these materials are called reduced graphene oxide (rGO) [Hummers et al. 1958; Marcano et al. 2010; Sun and Fugetsu 2013; Pei and Cheng 2012]. It is however also well-documented that graphene derived in this manner contains a significant amount of crystalline defects [e.g. Gomez-Navarro et al. 2007]. Bagri and colleagues illustrate the inherent disorders in rGO in an atomic model (reproduced as Fig. 5-1(b) in this thesis) showing remnant oxygen groups and vacancies in the resulting rGO [Loh et al. 2010; Bagri et al. 2010]. See [Terrones et al. 2012, Fig. 22] for a diagrammatic illustration of rGO synthesis.

A recent study [Botas et al. 2013] compared the two most widely used chemical synthesis methods of graphene oxide. These synthesis methods were the Hummers and Brodie methods. Both methods differed in terms of the acid medium (nitric or sulfuric acid) and the type of salt used (potassium chlorate or potassium permanganate) [Botas et al. 2013]. Botas et al. concluded that the Hummers oxidation method resulted in “a larger restoration of the pristine graphite 2D structure” [Botas et al. 2013].

Besides rGO synthesis, there are alternative ways of producing graphene, albeit of varying quality and not yet reaching the purity achieved from mechanical exfoliation. These synthesis methods include CVD and various chemical methods [see e.g. Bonaccorso et al. 2010, p. 613ff].

1.2.4.1 Recent advances in the synthesis of reduced graphene oxide

The method used to synthesize rGO in this thesis is the standard Hummers method (see Chapter 3.1). However, it must be noted there have been recent advances of rGO synthesis utilizing modified versions of the Hummers method [Marcano et al. 2010; Sun and Fugetsu 2013].

Marcano et al. modified the ratio of chemicals of the Hummers' method to achieve an improved efficiency of the graphite oxidation process. This results in GO that is more oxidized than that prepared by Hummers' method but result in comparable electrical conductivity when the GO is reduced into rGO by using hydrazine as reducing agent. Also the improved method of Marcano et al. claims to not generate toxic gas and allow easy control of temperature [Marcano et al. 2010].

Sun and Fugetsu suggest a different modification to the Hummers method. They proposed as starting material, graphite intercalated with H_2SO_4 , so-called "expanded graphite" before proceeding with the traditional Hummers method. This modification is claimed to improve the reproducibility and safety of the synthesis of graphene oxide [Sun and Fugetsu 2013], which is not reduced into rGO in the paper.

Another very recent development uses ascorbic acid – commonly known as vitamin C – as a natural antioxidant to reduce GO into rGO [Muchhala et al. 2014]. The use of ascorbic acid as reducing agent in the synthesis of rGO is claimed by the authors to be more environmentally friendly in contrast with Gómez-Navarro's method which used hydrazine, a "harsh chemical treatment" [Muchhala et al. 2014], for that purpose.

(As an aside, we note that in the literature review of [Muchhala et al. 2014], their sentence, "They reported two possible conduction processes: 2D-VRH conduction mechanism at higher temperatures with low bias and at lowest temperatures with high biases, a temperature-independent field-driven tunneling process" attributed to [Kaiser et al. 2009] should have been rightly attributed instead to [Cheah et al. 2013] as it is one of the main results of this thesis (see Chapter 5) i.e. that of a crossover between two VRH conduction regimes, and was not discussed in the older paper.)

Besides improvements on the synthesis method, post-synthesis procedures can also be performed on the rGO to improve its properties. Compton et al. propose a post-synthesis modification to rGO to improve its electrical conductivity. This results in their so-called "alkylated" graphene paper [Compton et al., 2010; Compton and Nguyen, 2010].

1.3 Carbon nanotubes

1.3.1 Discovery of carbon nanotubes

Carbon nanotubes (CNTs) are rolled-up sheets of graphene ([Lehman et al. 2011, Appendix A] lists the technical definitions of the various forms of CNTs). Two main types of CNTs with high structural perfection are single-walled (SWNT) and multi-walled carbon nanotubes (MWNT), the latter consisting of nanotubes concentrically placed inside another “like rings of a tree trunk” [Rafique and Iqbal 2011].

The discovery of carbon nanotubes is widely credited to Iijima [Iijima 1991], but it has in recent years been pointed out that Radushkevich and Lukyanovich had published a figure showing hollow carbon filaments, now known as MWNT, in a Russian-language publication back in 1952 [Monthieux and Kuznetsov 2006; Grobert 2007]. Other reviews attribute the discovery of MWNT to Wiles and Abrahamson in the late 1970s [Ball 2001; Liu et al. 2009]. All the cited reviews emphasize, however, that it was Iijima’s report in 1991 [Iijima 1991] that attracted global attention to MWNT research.

[Iijima 1991] reported the structural morphology of MWNT by use of a high-resolution transmission electron microscope (HRTEM) and electron diffraction [Lehman et al. 2011]. The discovery of SWNT came two years after Iijima's 1991 paper [Iijima and Ichihashi 1993; Monthieux and Kuznetsov 2006].

1.3.2 Commercial and emerging technologies based on carbon nanotubes

The main advantage of carbon nanotube (CNT) networks is that they are flexible, compared to rigid silicon in the electronics industry. Being flexible opens up potential applications in for example, flexible display and thin film transistors [Sun et al. 2013]. In a review, [De Volder et al. 2013] state that “continued CNT research and development will be complementary to the rise of graphene”. This means that the rapid

growth in the synthesis and characterization of graphene – e.g. CVD methods and Raman spectroscopy techniques – both leverage from and in turn contribute to CNT research [De Volder et al. 2013].

In the review of [Rutherglen et al. 2009], they state that “electronic devices based on carbon nanotubes are among the candidates to eventually replace silicon-based devices for logic applications.” Single-wall CNTs, owing to their near-ballistic electron transport and high cut-off frequencies, are promising for radiofrequency transistors. However, the challenge is to realize techniques to synthesize dense, well-aligned arrays of semiconducting nanotubes in a cost-effective manner for use in such transistor applications [Rutherglen et al. 2009].

The main challenge of using CNTs in electronic devices, usually field-effect transistors (FET), is that conventional as-grown CNTs consist of a mixture of semiconducting and metallic CNTs [Sun et al. 2013]. As metallic CNTs have little or no bandgap, this results in high leakage currents [Shulaker et al. 2013]. An additional obstacle in realizing robust and complex CNT FETs is substantial inherent imperfections in CNT technology, including mis-positioned and metallic CNTs [Shulaker et al. 2013].

Electrical transport in SWNT can be tuned by inherent or created disorder, viz. by localized lattice defects (whether unintentional or intentional damage), electric potential fluctuations and mechanical deformations [Biercuk et al. 2008]. However, the coexistence of multiple sources of disorder in nanotubes as well as the large variability in their properties “makes it hard to make wide generalizations on the effects of disorder”, according to [Biercuk et al. 2008, p. 463].

Researchers from Stanford University have demonstrated a CNT computer fabricated entirely from CNT FETs (or CNFET), demonstrating CNT-based circuits as “a feasible and plausible emerging technology” [Shulaker et al. 2013]. The researchers reported a simple but functional computer made entirely from carbon nanotube transistors comprising 178 transistors each containing between 10 and 200 CNTs, which is able to fetch and write data as well as perform arithmetic operations with the ability to multi-task [Shulaker et al. 2013].

CNTs have been used as transparent conductive coatings or films [Ansaldo et al. 2008], and as active material for transparent and flexible transistors [Ansaldo et al. 2009]. According to Ansaldo et al., SWCNT films are “one of the most promising” candidates to replace indium tin oxide (ITO) as transparent electrodes in solar cells and flat displays [Ansaldo et al. 2009].

1.3.3 CVD-grown single-wall carbon nanotubes

The ability to produce CNTs of the length of several millimetres via the CVD method is well established [Chakrabarti et al. 2006; Jayasinghe et al. 2011; Lan et al. 2011]. In fact, a recent advance in which aligned carbon nanotube (CNT) arrays over 150 μm long have been grown by catalytic chemical vapour deposition on the walls of bare cordierite (i.e. a type of ceramic) monoliths (i.e. support structures with mm-order diameter uniform channels) in a single step [Minett et al. 2013].

The main advantage of the directly grown chemical vapour deposition (CVD) method over post-growth techniques is that the networks typically consist of several millimetre-long tubes, and hence a very low concentration of tubes is needed to reach the percolation threshold to establish an electrical circuit. This low concentration to achieve percolation is optimal as the intertube contacts in CNT networks contribute significantly to their sheet resistance [Lima et al. 2007].

In addition, single-walled CNTs (SWCNT) produced via CVD hold much promise in producing transparent, conductive samples with fewer defects [Ansaldo et al. 2009] compared to post-growth production methods. The main drawback of post-growth techniques is that they require CNTs to be dispersed in a liquid medium, thus damaging and shortening the tubes considerably, see e.g. [Andrade et al. 2007].

Ansaldo et al. advocate for CVD-grown SWCNTs rather than by spraying or filtration. The latter methods have a main limitation wherein CNTs are deposited in the form of thick bundles and are mixed with insulating molecules to try to unbundle the CNTs. Ultrasonification which is used to help dispersion, introduce defects in the tubes. The optimization of the CVD method is reported in [Ansaldo et al. 2009].

Skákalová et al. recently studied composites of CNTs with graphite oxide to tune the electronic transport properties. They found that compositing SWCNTs with electrically insulating graphite oxide enhances the electrical conductivity. This counterintuitive result is explained by 'indirect' electronic doping from the oxide groups into the SWCNTs, thereby leading to more efficient tunnelling of electronic charges between tubes [Skákalová et al. 2014].

CHAPTER 2. Theory of electronic transport in disordered conductors

Defects or imperfections in materials are usually regarded as being disadvantageous with regard to the physical and electronic properties of the materials. Particularly for microelectronic devices in mass fabrication in the semiconductor industry, defects are known to cause issues such as reverse leakage current and are widely studied in order to eliminate the occurrence of such defects [see e.g. Cheah et al. 2009]. However, at the nanoscale, defects are now recognized to be useful as the nature and degree of defects can be exploited to generate novel, innovative and useful material properties and devices [Terrones et al. 2012].

Two possible mechanisms for electronic transport in materials containing disorder are variable range hopping (VRH) and fluctuation-assisted tunnelling (FAT). The main similarity between the two mechanisms is that both are quantum tunnelling processes. The main difference between the two is that for VRH, electrons are trapped in localized energy states and tunnelling can be driven by temperature and/or applied electric field whereas for FAT, electrons are delocalized and tunnelling is driven by the applied electric field. This is illustrated in Fig. 2-1. The sketch shows a comparison between the electronic transport mechanisms of VRH and FAT. The effect of temperature T and applied voltage source V are exaggerated to illustrate the tunnelling between electronic states shaded in gray and indicated by the direction of dotted arrows. Notably the distinction between VRH and FAT is in the scale of the localization of the charge carriers. In the FAT mechanism, resistance is dominated by a barrier separating delocalized carrier states. On the other hand, for VRH, significant resistance is contributed by barriers separating localized carrier states.

Fig. 2-1. Sketch shows a comparison between the electronic transport mechanisms of (a) fluctuation assisted tunnelling (FAT) and (b) variable-range hopping (VRH). The effect of temperature T and applied voltage source V are exaggerated to illustrate the tunnelling of electronic states shaded in gray across potential barriers in the direction indicated by dotted arrows. Both conduction mechanisms consist of quantum tunnelling, with the main difference being that in VRH, quantum tunnelling occurs between localized electronic states whereas for FAT, quantum tunnelling occurs across a thin barrier separating metallic states.

2.1 Variable-range hopping

2.1.1 Variable-range hopping and Anderson localization

Semiconductors which are lightly doped can have electrons in localized states due to intentional doping or unintended impurities. A possible mechanism for electronic conduction is the transition of these electrons between localized states, which are tunnelling assisted by phonons. (*Phonons* are periodic potentials induced by atoms

vibrating about their equilibrium lattice positions [e.g. Ridley 1982]. *Acoustic* phonons, i.e. fast moving quanta of crystal lattice vibrations, are the main heat carriers in graphene near room temperature [Nika and Balandin 2012].) These transitions are known as “hopping”. This transition is the dominant conduction mechanism if the temperature is so low that the number of conduction band electrons is very much smaller than the number of localized electrons [Shegelski 1986, p. 1].

VRH can describe conduction in disordered semiconductors in terms of hopping i.e. the phonon-assisted quantum tunnelling between electronic localized states centred at different positions in the bandgap. Mott’s law for VRH conductivity [Kaiser 2001, p. 11-12; Mott 1993, pp. 32-34]:

$$\sigma(T) = \sigma_0 \exp \left[- \left(\frac{T_0}{T} \right)^p \right] \quad (2.1)$$

Factors	VRH Conductivity behaviour
3D	$p = 1/4$
2D	$p = 1/3$
1D (or 3D with electron-electron interactions)	$p = 1/2$

The pre-factor σ_0 is temperature-dependent but often neglected due to the stronger temperature-dependence of exponential term [Kaiser 2001, p. 11-12]; this assumption of temperature-independence has been shown to be experimentally valid [Sarachik and Dai 2002] but there is some disagreement in the literature (see discussion in Chapter 2.1.5.2). At sufficiently high temperatures, the value of $\gamma = 1$ would indicate hopping to nearest neighbours [Kaiser 2001, p. 11-12]. Note that this is when VRH no longer applies as VRH by definition requires hopping of variable distances between electronic states.

For a system in which the electrons are majority delocalized, e.g. a near perfect metallic crystal or graphene, the presence of phonons (i.e. lattice vibrations) decreases electronic mobility. Thus the increase of temperature, which causes a corresponding increase in phonons, results in decrease in mobility. In other words, in concept,

maximum electronic mobility is achieved at temperatures low enough when the phonons are frozen out.

On the other hand, for a system wherein electrons are dominantly localized (according to the localization theory of Anderson, localization can be due to impurities and random lattice interactions; localization occurs when the density of energy levels are sufficiently low [Anderson 1958]), e.g. in a conducting material containing disorder, phonons are a major contributing factor to increasing electronic mobility. As such, as temperature increases causing phonons to increase, the mobility increases.

This theory of Anderson localization is an important assumption in the derivation of Mott's theory. As said by Mott himself [Mott 1972, p. 1], "...in amorphous theory [i.e. the theory of disordered, or non-crystalline materials], as in theology, one must declare one's faith and I will begin by saying that I believe this theorem [Anderson localization theorem] to be true, and that one can get nowhere in understanding the experiments without it. All the attempts of our Cambridge group to provide a theoretical framework for experimental work are based on it."

In [Shklovskii 1973], a sketch reproduced below as Fig. 2-2, illustrates electron hopping accompanied by phonon emission, also known as phonon-assisted tunnelling, which is essentially VRH. The sketch shows an electron occupying one of the localized states tunnelling to an unoccupied state. Because the new state is lower in energy compared to the initial state, a phonon is emitted.

Fig. 2-2. Hopping conduction accompanied by phonon emission. The inclined line represents the position of the quasi-equilibrium Fermi level in a strong electric field. Reproduced from [Shklovskii 1973]. Copyright 1973 American Institute of Physics.

2.1.2 Temperature-dependent (Mott) variable-range hopping; its derivation

Conduction due to VRH can be described by the expression [Mott 1993, pp. 31-32]

$$\sigma(T) = \sigma_0 \exp \left[- \left(\frac{T_0}{T} \right)^p \right]; \quad p = \frac{1}{d+1} \quad (2.2)$$

where σ is conductivity and d is the dimensionality of the system. The derivation of this expression is detailed below, adapted from [Mott 1993, pp. 31-32]. The first publication of this expression was in [Mott 1968, p. 8].

Mott starts by modelling the system as a “Fermi glass”, i.e. an electron gas in a highly disordered medium. The presence of disorder causes a finite, Anderson-localized density of states to exist near the Fermi energy in the electron gas. (We must note that by modelling the system as an idealized electron gas, there is the assumption that the electric field is distributed uniformly throughout the sample material. This results in discrepancies when calculating physical values from fitting parameters, as we shall see in Chapter 5.) At sufficiently low temperatures, Mott points out that hopping would be majority by variable range hopping and not by nearest neighbour hopping. The density of states per unit energy range near the Fermi energy is:

$$\frac{4\pi r_{ij}^3 g_F}{3}, \quad (2.3)$$

which consists of the volume of sphere with radius r_{ij} , multiplied by density of localized states at the Fermi energy g_F . For an electron to hop a distance r_{ij} say from site i to site j , the lowest activation energy needed is the reciprocal:

$$\Delta E_{ij} = \frac{1}{\left(\frac{4\pi r_{ij}^3 g_F}{3} \right)}, \quad (2.4)$$

and we note that the further the electron hops, the smaller would be the activation energy (or energy difference) needed (as $\Delta E_{ij} \propto \frac{1}{r_{ij}^3}$).

The hopping rate is then proportional to the quantity:

$$P_{ij} = \exp \left[- \left(\frac{2r_{ij}}{a} + \frac{\Delta E_{ij}}{k_B T} \right) \right], \quad (2.5)$$

where a is the localization radius of the electronic wavefunction, ΔE_{ij} is a particular energy difference associated with the hop, k_B is the Boltzmann constant and T is the temperature. Substituting ΔE_{ij} from above into P_{ij} we get:

$$P_{ij} = \exp \left[- \left(\frac{2r_{ij}}{a} + \frac{1}{\left(\frac{4\pi r_{ij}^3 g_F k_B T}{3} \right)} \right) \right]. \quad (2.6)$$

Maximizing P_{ij} with respect to r_{ij} gives the typical hopping distance r_{ij} ,

$$\frac{dP_{ij}}{dr_{ij}} = P_{ij} \left[- \left(\frac{2}{a} - \frac{1}{4\pi r_{ij}^4 g_F k_B T} \right) \right] = 0; \quad (2.7)$$

$$r_{ij} = \left(\frac{a}{2\pi g_F k_B T} \right)^{\frac{1}{4}}. \quad (2.8)$$

We can observe that as the temperature decreases, the range in position space of typical hops increases, hence the term “variable range” in variable-range hopping (VRH). The physical reason for this is that at low temperatures, fewer energy states are accessible. An electron tends to tunnel farther to a site that requires less change in energy than to a nearby site with a difference in energy that is large compared with the available phonons. This is the basic idea of the VRH theory [see e.g. Mott 1993, pp. 31-32; Shengelski 1986; Kaiser RPP 2001, pp. 11-12; Mansfield 1991].

In other words, at sufficiently low temperatures, and provided there is a non-vanishing density of states at the Fermi level, the typical resistances between neighbouring impurities become larger than those connecting some remote impurities whose energy levels happen to be very close to the Fermi level [Shklovskii and Efros, 1984, p. 202].

The hop distance expression above implies a conductivity of the form

$$\sigma(T) = \sigma_0 \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{4}} \right] \quad (2.9)$$

where σ_0 is a temperature- and field-dependent pre-factor but it is usually considered as a constant because the temperature dependence in the exponential is much larger than that of the pre-factor. T_0 is called the Mott coefficient, and is given by [Shklovskii 1973]

$$T_0 \approx \frac{16}{g_F L^3}. \quad (2.10)$$

Or alternatively [Mott and Davis 1979, Eq. (2.64)],

$$T_0 = \frac{3}{k_B g_F L^3} \quad (2.11)$$

which involves the density of states $g_F a^3$ near the Fermi level and their localization length L . By noting that Shklovskii sets the value of k_B to be unity, both values of T_0 are equivalent except for the numerator. Note that the Mott coefficient T_0 can be approximately understood as having a roughly inverse behaviour with the localization length of the electronic wavefunctions. More rigorously, assuming a constant density of states, then $T_0 \propto L^{-3}$. (See Chapter 2.1.5.1 where I comment on the different values of T_0 in the literature.)

The above theory of VRH conductivity was first derived for three dimensional materials [Mott 1968, p.8]. It was later found that in two dimensions, this index becomes 1/3 instead of 1/4, and thus the general form of conductivity due to VRH is [Mott 1993, pp. 31-32],

$$\sigma(T) = \sigma_0 \exp \left[- \left(\frac{T_0}{T} \right)^p \right]; \quad p = \frac{1}{d+1} \quad (2.12)$$

with d the dimensionality of the system.

2.1.3 Electric-field assisted, temperature-driven (Pollak-Riess) variable-range hopping

The full form of the pre-factor σ_0 , showing its temperature- and field-dependence, is [Pollak and Riess 1976]:

$$\sigma_0 = \sigma_L \exp\left(\frac{aE}{T}\right); a = \frac{0.18r_{ij}(T)e}{k_B}. \quad (2.13)$$

(The notation here for the electric field E is not to be confused with the notation for energy difference ΔE_{ij} introduced earlier.) The value 0.18 which is valid for surface transport (i.e. 2D) would be replaced by 0.17 if bulk transport (i.e. 3D) is considered instead [Pollak and Riess 1976, Eq. 31(b)]. Pollak and Riess obtained the values of the factor 0.17 and 0.18 by calculating via percolation theory and building on from Mott's original derivation [Mott 1968, p.8]. The factor 0.17 was found to be comparable with experimental results with a factor of 0.20 [Pollak and Riess 1976].

Mott and Davis [1979, p. 356, Eq. (7.2)] further refined this expression by introducing the condition $E \ll 2k_B T \alpha / e$, where α^{-1} is radius of wavefunction. The pre-factor σ_L can be experimentally interpreted as the conductivity at zero field limit. The factor $\exp\left(\frac{aE}{T}\right)$ manifests itself as the slope of the plot of $\ln G$ versus V_{ds} , as previously reported [Kaiser et al. 2009]. By using a as a fitting parameter to experimental data of field and temperature, we can thus obtain the hop length r_{ij} .

The full form of Mott's VRH law can be written [Pollak and Riess 1976; Mott 1993]:

$$\sigma_{LOW \text{ FIELD}}(T, E) = \sigma_L \exp\left[-\left(\frac{T_0}{T}\right)^{\frac{1}{d+1}}\right] \exp\left(\frac{aE}{T}\right) \quad (2.14)$$

The above expression is only valid for zero and low applied fields. Specifically, low field refers to electric fields $E \ll 2k_B T \alpha / e$ as introduced in the previous page.

2.1.4 Electric-field driven (Shklovskii) variable-range hopping

Shklovskii extended the VRH theory to higher fields and obtained the expression [Shklovskii 1973, Eq. (3a); see also recent review by Arkhipov et al. 2003],

$$\sigma_{HIGH\ FIELD}(E) = \sigma_H \exp \left[- \left(\frac{E_0}{E} \right)^{\frac{1}{d+1}} \right] \quad (2.15)$$

where

$$E_0 \approx \frac{T_0}{ea} \quad (2.16)$$

where T_0 is the Mott coefficient defined earlier and e is the electronic charge. It is observed that in the high field regime, VRH depends on the field instead of temperature. Parameter σ_H can be experimentally understood as the saturation conductance at the limit of very high fields. Pollak and Riess [Pollak, p.2351] claimed to have theoretically obtained results which “agree functionally” with Shklovskii’s high-field theory.

Shklovskii proposed that when subject to strong electric fields, the temperature factor in the Mott VRH be replaced by the electric field [Shklovskii 1973, Eq. (3a)]. This can be seen in another way that the temperature factor in the Mott VRH is replaced by an effective temperature term which relies solely on field [Arkhipov, Eq. (3)],

$$kT_F = \frac{eE}{2\gamma}. \quad (2.17)$$

This can be interpreted as thermal energy gain being replaced by electrostatic energy gain over the distance $\frac{1}{2\gamma}$.

2.1.5 Topical literature review

2.1.5.1 Differing values of the Mott coefficient

It is of note that there is some disagreement concerning the value of the Mott coefficient in the literature and this discussion serves as a review of the literature focussing on this coefficient. The Mott coefficient (see its definition toward the end of Chapter 2.1.2) is denoted either B, B_0, β or T_0 in the literature. In this discussion, these notations will be used interchangeably to unambiguously denote the Mott coefficient. A qualitative discussion will be presented first followed by the mathematical details.

Mott and Davis [1979] and Mott [1993] obtained B by a relatively simple method of writing out the expression for the lowest activation energy and then calculating for the highest hopping probability (refer derivation in Chapter 2.1.2). However, Mott acknowledges that different methods might give different values of B . In [Mott and Davis 1979], it is stated that percolation theory gives a more rigorous treatment, “with a value of B_0 differing little from that in (2.63). By different methods, they range from 1.78 to 2.48.”

Percolation theory is used by Shklovskii and Efros [1984] to calculate the Mott coefficient (denoted β in their work). Percolation theory determines the critical total concentration at which percolation first occurs. This is solved using a Monte Carlo (i.e. random walk) method which is then extrapolated to an array of infinite sites. Mott and Davis explain the percolation theory concisely thus: “The essence of [percolation] approach is that the spheres of radius R on sites along a most favoured path must join up to form a percolation channel through the material. R must be chosen so that it does, and a value of R comes out from the analysis varying as $T^{-\frac{1}{4}}$ [in the 3D case].” [Mott and Davis 1979, p.35]. Shklovskii and Efros explain the Monte Carlo method used in solving the percolation theory: “Another productive numerical method in percolation theory is the random trial method, known as the Monte Carlo method. It includes practically all computer calculations in which a random number generator is used to any extent.” [Shklovskii and Efros 1984, p. 106])

It is interesting to note that Shklovskii and Efros dismiss completely Mott’s proposed values for B . According to [Shklovskii and Efros 1984]: “Mott gave only a

qualitative derivation of (9.1.1), from which the exact value of the coefficient β could not be determined.”

Based on Mott’s own admission that percolation theory is more rigorous, we believe the coefficient value of Shklovskii and Efros to be more accurate and we shall use the latter value over Mott’s. (We were also strongly encouraged in this direction by an anonymous reviewer to our paper, [Cheah et al. 2013].) To give fair credit to both groups, the advantage of Mott’s derivation is in its simplicity and physical intuitiveness; this is excellent for pedagogical reasons. On the other hand, Shklovskii and Efros’ method gives a more accurate value of the coefficient based on its rigorousness.

We end this section with the mathematical details excerpted from the relevant sources. According to [Mott and Davis 1979, Eq. (2.64)], in the 2D case, conductivity follows

$$\sigma = A \exp\left(-\frac{B}{T^{\frac{1}{3}}}\right); \quad B = \left(\frac{3\alpha^2}{g_F k_B}\right)^{\frac{1}{3}} \quad (2.18)$$

where $1/\alpha$ is the decay length of the localized wave function [Mott 1993, pp. 31-35]. In the 3D case, [Mott and Davis 1979, Eq. (2.63)], hopping probability follows

$$v_{ph} = \exp\left(-\frac{B}{T^{\frac{1}{4}}}\right); \quad B = B_0 \left(\frac{\alpha^3}{kN(E_F)}\right)^{\frac{1}{4}}; \quad B_0 = 2 \left(\frac{3}{2\pi}\right)^{\frac{1}{4}} = 1.66 \quad (2.19)$$

and the conductivity is obtained by then multiplying the above expression by $e^2 N(E_F) \bar{R}^2$.

According to [Pope and Swenberg 1999, p. 993], conductivity is calculated as

$$\sigma = 2e^2 N(E_F) \bar{R}^2 v_{ph}. \quad (2.20)$$

If the density of states $N(E_F)$ is assumed to be constant and equal to N_0 , VRH predicts a conductivity of the form

$$\sigma = 2 \left(\frac{9\zeta N_0}{8\pi k_B T}\right)^{\frac{1}{2}} v_{ph} \exp\left[-\left(\frac{T_0}{T}\right)^{\frac{1}{4}}\right] \quad (2.21)$$

where the characteristic temperature $T_0 = 16/k_B N_0 \zeta^3$ (this form of the coefficient is used by Granville and colleagues [Sharma et al. 2010, Eq. (2)]), with $\zeta = \alpha^{-1}$, the inverse localization length.

In comparison, [Shklovskii and Efros 1984, Eqs. (9.1.19) and (9.1.21)] give in the 2D case, resistivity follows

$$\rho = \rho_0 \exp\left(\frac{T_0}{T}\right)^{\frac{1}{3}}; \quad T_0 = \frac{\beta}{kN(E_F)a^2}; \quad \beta = 13.8 \pm 0.8. \quad (2.22)$$

Note that this value contradicts with the number of 1.66 of Mott and Efros, and we shall use the latter value for the Mott coefficient for the work in this thesis for reasons stated above. For the 3D case, [Shklovskii and Efros 1984, Eqs. (9.1.1) and (9.1.18)], resistivity follows

$$\rho(T) = \rho_0 \exp\left(\frac{T_0}{T}\right)^{\frac{1}{4}}; \quad T_0 = \frac{\beta}{kN(E_F)a^3}; \quad \beta = 21.2 \pm 1.2 \quad (2.23)$$

where a is the localization radius of states near the Fermi level.

2.1.5.2 Temperature (in-)dependence of the Mott pre-exponential factor

As with the value of the Mott coefficient, there is also no general consensus in the literature as to whether the pre-exponential factor in the Mott VRH expression is, or should be, dependent on temperature. For the work in this thesis, we assume the pre-exponential factor to be temperature independent (see Chapter 2.1.1). The main support for this assumption comes from the experimental work of [Sarachik and Dai 2002].

The work of Sarachik and Dai [2002] reports experimentally measured conductivity data of boron-doped silicon (Si:B) in which the VRH pre-factor is shown to be temperature independent in the 3D bulk system. The interpretation of this temperature independent pre-factor (i.e. σ_0 in $\sigma = \sigma_0 \exp\left(\frac{-T_0}{T}\right)^p$) is that it “implies

hopping that is not mediated by phonons” [Sarachik and Dai 2002], meaning it is distinguishable from the exponential temperature term (i.e. the $\exp T^{-p}$ term) of the VRH expression.

On the other hand, [Paasch et al. 2002, Eq. (18)] employ a temperature-dependent pre-exponential factor for data in organic semiconductors, in which the pre-factor depends on temperature. The form of the temperature-dependent pre-factor follows $\sigma_0 \propto T^{-\frac{1}{2}}$. The work of [Sharma et al. 2010, Eq. (2)], which cites Paasch et al. [2002], report low-temperature VRH in cobalt-doped ZnO, in which the pre-factor depends on temperature following, similarly, $\sigma_0 \propto T^{-\frac{1}{2}}$.

From the textbook of [Shklovskii and Efros 1984, p. 224], for lightly-doped amorphous semiconductors, in which the localized states near the Fermi level are probably due to short-range structural defects, the temperature dependence of the pre-exponential factor (if we write Mott’s law as resistivity $\rho = \rho_0 \exp \left[- \left(\frac{T_0}{T} \right)^p \right]$) is given as:

$$\rho_0 \approx \bar{\rho}_0 \left(\frac{T_0}{T} \right)^{\frac{\nu+2}{4}} \quad (2.24)$$

where ν is the correlation radius obtained from numerical calculations, and tabulated in [Shklovskii and Efros 1984, Table 5.2, p. 105]. In 2D space, $\nu \sim 1.4$ and thus $\rho_0 \propto T^{-0.9}$ or approximately $\rho_0 \propto T^{-1}$. For 3D, $\nu \sim 0.9$ thus giving $\rho_0 \propto T^{-0.7}$ or approximately $\rho_0 \propto T^{-\frac{3}{4}}$. However, to complicate things, different values of this index appear in the literature. From the textbook of [Mott and Davis 1979, p. 35], the pre-exponential factor in 3D depends on temperature is suggested to be

$$\sigma_0 = 0.022C\alpha \left(\frac{T_0}{T} \right)^{0.35} \quad (2.25)$$

where C is a constant and α is the inverse decay length of the localized wave function.

To try to shed light on this conundrum, we tried to fit our experimental data with a modified model $G = G_0(T^{-n}) \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{d+1}} \right]$, by introducing a factor T^{-n} and leaving the value of fitting parameter n open to scaling, to see if it matches any of the

predictions above, i.e. that G_0 is temperature dependent. Unfortunately, this effort is inconclusive as we use G_0 as a fitting parameter, and do not have sufficient data to conclude whether it taken over a temperature range, it would scale with respect to temperature.

Alternatively, we looked into [Sharma et al. 2010, Eq. (2)],

$$G_0 = 3e^2 \nu_{ph} \sqrt{\frac{N(E_F)}{8\pi\alpha k_B T}}. \quad (2.26)$$

If one can assume that the phonon frequency at Debye temperature ν_{ph} , the density of localized electronic states at the Fermi level $N(E_F)$, and the inverse localization length α all stay constant as temperature T is varied, then $G_0 \propto \frac{1}{\sqrt{T}}$. If these assumptions can hold, we would then see G_0 decrease as temperature T is increased.

Based on the values of our fitting parameters (see Chapter 5, Table 5.1), for our rGO samples at $V_g = 0$ at a temperature of 40 K, the mean value of G_0 is $2.3 \times 10^{-10} S$, while at a temperature of 220 K, the value of $G_0 = 2.2 \times 10^{-7} S$. We see that instead of decreasing, the value of G_0 instead increased as the temperature increased, which means that the assumptions cannot hold. Hence the most possible explanation is that other factors also play influencing parts to the value of G_0 . Specifically, that either, with increasing temperature, $N(E_F)$ or ν_{ph} increases, or α decreases (the latter could be related to the average hopping length decreasing as temperature increases, as predicted by the VRH theory). As such, based on our fitting parameters, we cannot give a conclusive statement on whether the G_0 scales with $T^{-\frac{1}{2}}$ (or any other index).

2.1.5.3 Existing variable-range hopping crossover models

The main novel result in this thesis (see Chapter 5) is our proposed transport model incorporating a crossover in electrical conductance from low-field VRH, $\ln G \propto T^{-\frac{1}{3}}$, to

high-field VRH, $\ln G \propto E^{-\frac{1}{3}}$ in disordered graphene [Cheah et al. 2013]. We further extend this model to apply to other carbon materials of different conduction dimensionalities [Cheah and Kaiser 2014]. In Chapter 6, we present further evidence in data for SWNT supporting our crossover VRH model. To the best of our knowledge, such a crossover VRH model is novel at least for 2D materials such as graphene.

In this section, we review the literature focussing on existing VRH crossover models. VRH is a common transport mechanism in disordered materials [e.g. Pichon and Rogel 2011; Okada and Taniguchi 1997; Yosida and Oguro 1996; Hauser and Rodgers 1982] that have a substantial density of localized states close to the Fermi level, with spatially overlapping wavefunctions.

For materials in which the density of states at the Fermi level is suppressed by Coulombic electron-electron interactions, VRH is expected to follow the Efros-Shklovskii [Huang et al. 2010; Efros and Shklovskii 1975] model – i.e. with the conductance $\ln G \propto T^{-\frac{1}{2}}$ at low applied fields E for both 2D and 3D materials, and with the conductance $\ln G \propto E^{-\frac{1}{2}}$ at high fields – rather than the standard Mott model. Efros-Shklovskii crossovers have been observed in 3D CdSe thin films [Yu et al. 2004], disordered carbon nanotubes [Wang et al. 2007] and very recently for disordered graphene [Lo et al. 2013].

We note that our reduced graphene oxide (rGO) differs to those of [Lo et al. 2013] in that our sample is only partially disordered with highly conducting crystalline regions making up a large fraction of the sample. While [Lo et al. 2013] found in their highly disordered graphene that VRH followed Efros-Shklovskii behaviour (i.e. crossover from $\ln G \propto T^{-\frac{1}{2}}$ to $\ln G \propto E^{-\frac{1}{2}}$), as also found by [Yu et al. 2004], our partially disordered graphene sample follow the standard non-interacting 2D VRH behaviour where crossover occurs from $\ln G \propto T^{-\frac{1}{3}}$ to $\ln G \propto E^{-\frac{1}{3}}$.

A slightly different conduction mechanism is reported in 3D GeAu thin films wherein a crossover occurs from $\exp(T^{-\frac{1}{2}})$ to $\exp(E)$ as the field is increased [Wang et al. 1995]. That is, the field dependence appears to follow the Pollak-Riess intermediate-field behaviour rather than reaching the high-field limit. In 3D carbon networks, a crossover from $\exp(T^{-\frac{1}{4}})$ to $\exp(E^n)$ behaviour, wherein n scales from zero to one as

the field is increased, has been reported [Govor et al. 2000]. In Chapter 5, we show that our model can very well describe the data of [Govor et al. 2000] while maintaining the power index determined by the system dimensionality and without need for arbitrary scaling of the power index.

2.1.5.4 Comments on competing model by Pipinys and Kiveris

Pipinys and Kiveris, in several papers [e.g. Pipinys and Kiveris 2008; 2010; 2012], introduced a field- and temperature-dependent “phonon-assisted tunnelling rate” empirical expression to “compare” with the VRH model. Those authors claim that the VRH model does not work because of the “discrepancy” between reports of different dimensionality powers in the exponent [Pipinys and Kiveris 2008]. However, a completely physical explanation exists for why, for example, a CNT might exhibit differing conduction dimensionalities; this could be due to the different resulting morphology or fabrication conditions of the samples and is no sign of weakness of the VRH model.

The “phonon-assisted tunnelling rate” empirical expression of Pipinys and Kiveris proposes a tunnelling rate W , which is proportional to all of these terms: the electrical field E , $1/E$, $\exp(T^{\frac{1}{2}})$, $\exp(T^{-\frac{1}{4}})$, $\exp(1/E)$, $\exp(\exp(T))$, $\exp(\exp(T^{\frac{1}{2}}))$, and $\exp(\exp(T))$ where T denotes temperature [Pipinys and Kiveris 2012, Eq. (7)]. In fact, the tunnelling rate concept has already been employed in a more elegant manner by Mott in deriving his VRH expression in 1968, see Mott’s derivation summarized in Chapter 2.1.2. In some cases, Pipinys and Kiveris required a duplication of the expression terms into a composite to fit a set of temperature-dependent data, see e.g. [Pipinys and Kiveris 2012, Fig. 5].

Pipinys et al. claim that electric field-dependent data of Wang et al. [Pipinys and Kiveris 2012, Fig. 7 and p. 278] does not fit to Kaiser et al.’s expression for field-dependent FAT, and use that as justification for using their “phonon-assisted tunneling

rate” expression. Unfortunately, Pipinys et al. seem to be confusing the two distinctly different mechanisms of VRH and FAT. In fact, [Wang et al. 2007] had explicitly showed the good fit of their field-dependent data to Efros-Shklovskii (Coulomb-gap dominated) VRH, i.e. conductance proportional to $\exp(T^{-1/2})$ at low fields and proportional to $\exp(E^{-1/2})$ at high fields.

Pipinys and Kiveris again attempted to use their complicated expression to explain data of other scientists [Pipinys and Kiveris 2010]. Again, in this case, the original group who published the data [Khan et al. 2008] already sufficiently described their experimental conductance in a multi-wall CNT using a crossover model from 2D to 3D Mott VRH model. (For more on conduction mechanisms in CNT, see Chapter 6.)

The model used by Pipinys and Kiveris originates from their paper from 1976 [Kiveris et al. 1976, eq. (10)]. The main concept behind the theoretical derivation of electron tunnelling probability is the assumption that such tunnelling occurs from a filled deep electron level (a ‘trap’ or a ‘center’) of the valence band to the conduction band, aided by the absorption and emission of *one* longitudinal *optical* phonon, in the presence of a strong applied electric field.

The paper of Kiveris et al. [1976] derived this theory to describe data of thermoluminescence experiments, “generalizing ... the single-phonon-assisted band-to-band tunnelling theory to trap-to-band transitions” [Herrmann and Schenk 1995]. Hence we can conclude that this is not a competing model (not least for the reason that this thesis considers thermally-driven phonons and not optical phonons), but which in recent years seems to have been misappropriated to explain unrelated experimental data.

2.2 Fluctuation assisted tunnelling

2.2.1 Temperature-driven (Sheng) fluctuation-assisted tunnelling

Other than VRH, another possible transport mechanism in disordered conductors is via fluctuated assisted tunnelling (FAT). The main difference between VRH and FAT is

that VRH involves tunnelling between localized electronic states whereas FAT involves tunnelling through thin barriers interrupting otherwise metallic states.

FAT occurs in a material wherein delocalized electrons in crystalline regions are trapped within thin barriers consisting of disordered regions. As the temperature and/or applied electric field of the sample are increased, the electrons gain sufficient energy to tunnel across the barrier. This tunnelling through thin barriers between metallic regions with delocalized charge carriers is the FAT mechanism, and the tunnelling rate is enhanced by thermal fluctuations [see e.g. Kaiser and Skákalová 2011, Fig. 12].

Conduction via FAT can be described with the Sheng equation [Sheng 1980, Eq. 36(a)]:

$$\sigma^{-1}(T) = \sigma_0^{-1} \exp\left(\frac{T_b}{T + T_s}\right) \quad (2.27)$$

where σ is conductivity and T_s is so-called Sheng's parameter. The order of magnitude of barrier energy is indicated by the value of $k_B T_b$, where k_B is Boltzmann's constant. The extent of quantum tunnelling in the low-temperature limit is indicated by the ratio T_s/T_b [Kaiser et al. 2008].

FAT is usually considered together with metallic conduction contributed by phonon backscattering [e.g. Kaiser 2001; Skákalová et al. 2006]. It has been reported that for thick single-wall carbon nanotube (SWNT) networks, conduction follows mainly a quasi-1D metallic conduction (the first term) plus a minor contribution from FAT (the second term) [Skákalová et al. 2006, Eq. (4)] as follows:

$$\frac{1}{G(T)} = A \exp\left(-\frac{T_m}{T}\right) + B \exp\left(\frac{T_b}{T_s + T}\right). \quad (2.28)$$

The quasi-1D metallic-like behaviour arises from zone boundary in-plane phonon scattering [Pietronero 1983]. The parameter T_m in the metallic term is fixed at 1830 K to correspond to 160 meV or 1230 cm⁻¹, the band of energies expected for in-plane zone boundary phonons in SWNT [Skákalová et al. 2006, p.7].

On the other hand for thin SWNT networks, the temperature dependence of electronic conduction is generally dominated by VRH.

2.2.2 Electric field-driven (Kaiser-Park) fluctuation-assisted tunnelling

Kaiser and colleagues have extended the temperature-dependent FAT theory of Sheng in the previous section, to cases where an applied voltage is increased and the electrical contribution becomes significant. The empirical field-dependent FAT expression [Kaiser et al. 2004, Eq. (2); Kaiser and Park, 2005] is as follows:

$$G = \frac{I}{V} = \frac{G_0 \exp\left(\frac{V}{V_0}\right)}{1 + h \left[\exp\left(\frac{V}{V_0}\right) - 1 \right]} \quad (2.29)$$

where G_0 is the Ohmic behaviour at low field. As applied voltage or field increases, conductance increases exponentially on scale determined by V_0 . At higher field values, this exponential increase slows to an extent determined by parameter h . This model extended Sheng's FAT model to cases of higher conductivity wherein tunnelling up until the top of the barrier and thermal activation over the barrier are both represented.

2.2.3 Graphical comparison of fluctuation assisted tunnelling and variable-range hopping

It is possible to distinguish at a glance the different trends of FAT and VRH mechanisms by a graphical method of the conductance data, Fig. 2-3. Samples showing VRH would show a conductance tending to zero as the temperature approaches absolute zero. On the other hand, samples showing FAT would exhibit conductance tending to a finite, non-zero value as the temperature approaches absolute zero. The latter means that a finite value of the room temperature conductance remains near absolute zero temperature, which is characteristic of FAT being interrupted metallic conduction.

Mathematically, we can look into the analytical expressions for FAT and VRH. In the VRH expression, as temperature $T \rightarrow 0$, conductance $\sigma \rightarrow \exp\left(-\frac{T_0}{0}\right) \rightarrow \exp(-\infty) = 0$. Meanwhile, in the FAT expression, as temperature $T \rightarrow 0$, conductance $\sigma \rightarrow \exp\left(\frac{0+T_s}{T_b}\right)$ which gives a finite, non-zero value of conductivity near absolute zero due to the finite values of T_s and T_b (the meanings of T_s, T_b and the ratio T_s/T_b are explained in Chapter 2.2.1).

Experimentally, a general trend can be observed: as metallic conduction is increasingly interrupted in single-wall carbon nanotube (SWNT) networks – i.e. the electrons become increasingly localized – the transport mechanism switches from FAT to VRH. In other words, the thicker the film containing the nanotube networks gets, the conduction behaviour tends toward FAT [Kaiser et al. 2008; Skákalová et al. 2006].

Fig. 2-3. General trend of conductivity versus temperature for materials exhibiting fluctuation assisted tunnelling (FAT) and variable-range hopping (VRH) transport, based on the experimental data on SWNT networks reported in [Kaiser et al. 2008, Fig. 2; Skákalová et al. 2006, Fig. 10].

CHAPTER 3. Experimental

background: synthesis methods of

materials under study

This chapter details the experimental procedures resulting in the materials analyzed in this thesis to establish the background of the data under study. The work has been undertaken by other research groups either directly collaborating with us or groups whose materials data were used in our analysis work. These materials are disordered graphene in the form of reduced graphene oxide prepared by Gómez-Navarro and colleagues [Gómez-Navarro et al. 2007], self-assembled carbon networks by Govor and team members [Govor et al. 2000; 2001; 2002], highly conducting polymers by [Wang et al. 1992] (see results and discussion in Chapter 5) and single-wall carbon nanotube networks by Skákalová and colleagues [Ansaldo et al. 2007; 2008; 2009; Lima et al. 2007; Andrade et al. 2007] (see results and discussion in Chapter 6).

3.1 Reduced graphene oxide – Gómez-Navarro et al.

Reduced graphene oxide (rGO), an inherently disordered form of graphene produced via a chemical synthesis method has been introduced in Chapter 1.2.4. For the data under study in this thesis, the rGO samples are prepared by Gómez-Navarro and colleagues [Gómez-Navarro et al. 2007] via the procedures detailed in the following paragraph.

First, graphitic oxide is prepared by oxidizing graphite flakes via treatment with KMnO_4 and NaNO_3 in concentrated H_2SO_4 . This method of preparing graphitic oxide is known as the Hummers method [Hummers et al. 1958] (see Chapter 1.2.4.1 on advances to the Hummers method). The graphitic oxide is then floated on water wherein it disperses into single layers (viz. graphene oxide, GO), due to weak van der Waals interactions [e.g. Castro Neto et al. 2009] between the graphene layers.

The resulting graphene oxide is then deposited on a Si substrate with a 300-nm thick thermally grown SiO_2 layer whose surface has been modified by aminosilination, i.e. by use of the chemical 3-aminopropyltriethoxysilane (APTES). APTES is a surface treatment procedure to increase its receptivity to the subsequent chemicals [e.g. Vandenberg et al. 1991; Sarkar and Daniels-Race 2013].

The graphene oxide is then chemically reduced using hydrogen plasma treatment, which includes the chemical hydrazine as a precursor, thus forming rGO. The hydrogen plasma treatment procedure has been optimized to obtain the maximum electrical conductivity. This conductivity is subsequently confirmed to be intrinsic to the graphene oxide, rather than a contribution from contacts, by measuring the resistance at various electrode separations.

The principle is that if resistance varies proportionally with sample length, then this resistance is intrinsic to the sample, whereas if the resistance stays independent of the sample length, then this resistance is due to an extrinsic factor. In experiments, the varying sample length can in effect be varied by the separations between electrodes, and it has been shown in [Kaiser et al. 2009] that the resistance between electrodes of varying separations d is proportional to d . This shows that the measured resistance is essentially the intrinsic resistance of the rGO sample.

It is also important to determine that the contacts are of a non-invasive nature. Gold is used as contact material for the samples studied in this thesis. In similar samples and configurations to that studied in this thesis, [Sundaram et al. 2009] have found that there is a negligible potential barrier at the gold/graphene interface. This shows that the effect of contacts can be neglected.

Each graphene sample, with height ~ 1 nm from atomic force microscopy, is then patterned with top contacts consisting of 0.3/25 nm Ti/AuPd [Kaiser et al. 2009]

via e-beam lithography. The samples are then placed in an Oxford Instrument cryostat under low-pressure helium (^4He) for electrical transport measurements, which are sensitive to temperature. The devices are fabricated in the field-effect transistor (FET) configuration to enable electrical transport measurements. The silicon substrate is electrically separated from the graphene layer by the SiO_2 layer; the substrate acts as the back gate. The FET configuration is well-known from e.g. papers by Geim and Novoselov [Lopez et al. 2009, Fig. 2(c); Novoselov et al. 2004, Fig. 1(e)].

Electrical conduction data is sometimes reported in the literature as resistance, resistivity, or more commonly as their inverses, conductance $G \equiv I/V \equiv 1/R$ or conductivity $\sigma \equiv 1/\rho$. We remind ourselves of the relationship between resistance R and resistivity ρ , i.e. $R = \rho L/A$ where the length of the material L is determined by the distance between the test electrodes and the cross-sectional area A of the material can be considered constant. If the resistance is intrinsic, i.e. R scales proportionally to L , then the resistivity $\rho = RA/L$ would stay constant, provided the cross-sectional area of sample A stays fixed. Hence we can see the straightforward conversions between the different parameters as required.

3.2 3D self-assembled carbon networks – Govor et al.

We have used the electrical data of these carbon networks to demonstrate the applicability of our VRH crossover model of graphene to also 3D disordered carbon materials. These self-assembled carbon networks were prepared by Govor and colleagues [Govor et al. 2000; 2002]. These networks consist of disordered carbon connections with width and height about 100 nm, arranged in a planar pattern of micron-sized hexagons. The carbon networks consist of “hexagonal basic cells with diameters of about $1 - 1.5 \mu\text{m}$ ” [Govor et al. 2001] and sample thickness of ~ 100 nm [Govor et al. 2000] fabricated using a three-step self-assembly process.

3.3 Quasi-1D highly conducting polymers – Wang et al.

Besides graphene and 3D carbon networks, we also use the electrical data of quasi-1D highly conducting polymers to illustrate the wide applicability of our VRH crossover model. The polymer is the HCl-doped emeraldine salt form of polyaniline (PAN-ES, see Fig. 3-1) prepared by Wang and colleagues. The sample is 1:4 stretched PAN-ES at doping ratio $[Cl]/[N] = 0.50$. Electrical measurements are performed by Wang et al. following the two-probe technique, with the field perpendicular to the plane in a sandwich configuration; the PAN-ES is contained in a film of thickness $20\text{ }\mu\text{m}$ [Wang et al. 1992].

Wang and colleagues report that more than 50 % of their sample is amorphous, indicating the high level of disorder in the polymer and consistent with the expectation of the presence of localized electronic states dominating the conduction mechanism. The quasi-1D VRH electrical transport of the PAN-ES is suggested to be dominated by the amorphous regions or between the bundles of the polymers [Wang et al. 1992].

Fig. 3-1. Schematic chemical structure of the HCl-doped emeraldine salt form of polyaniline (PAN-ES) [Wang et al. 1992].

3.4 Single-wall carbon nanotube networks by various synthesis methods

In Chapter 6, we perform a systematic analysis of single-wall carbon nanotube (SWNT) networks grown by various synthesis methods. CNT networks can be grown via

chemical vapour deposition (CVD) – also known as the in-situ, as-grown or direct growth method – or via post-growth techniques. Chemical vapour deposition (CVD) is commonly used in the semiconductor industry to produce high-purity, high-performance thin films. Post-growth technique involves the deposition of suspensions of CNTs on a substrate; the possible deposition methods are various, i.e. spray-coating, vacuum filtration, spin-coating, dip-coating, and electrophoretic deposition [Andrade et al. 2007].

The direct growth or CVD method is the focus of the study in this thesis. The main advantage of CVD growth is that the resulting networks consist of several mm-long tubes, and so a very low concentration of tubes is needed to reach the percolation threshold (i.e. to establish an electrical connection). In contrast, the main drawback of all post-growth techniques is that they require CNTs to be dispersed in a liquid medium, via sonication (i.e. the act of applying sound energy to agitate particles in a sample) or chemical treatment, in thus manner damaging or cutting the tubes. As a result, higher concentrations of post-growth CNTs are needed to reach the percolation threshold. This is not optimal because the increased number of inter-tube contacts significantly increases the resistance of CNT networks [Lima et al. 2007].

However, a drawback of CVD method is that by-products end up deposited on the substrate surface. These by-products do not contribute to electrical conductivity and degrade optical transmittance. Thus, in terms of optical transmittance, CVD-grown CNTs are comparable to post-growth deposited CNTs [Andrade et al. 2007].

3.4.1 Direct grown carbon nanotube networks via spray-coated catalysts – Ansaldo et al.

The SWNT samples are grown by direct growth from spin-coated catalyst by Ansaldo and colleagues. Specifically, the direct (or in-situ) growth of the SWNT is performed via alcohol-based CVD, with ethanol as the alcohol. The spin-coated catalyst is also known as a pre-cursor, and consists of cobalt acetate or a mixture of cobalt and nickel acetate [Ansaldo et al. 2009; 2007].

The SWNT was grown on a thermally-grown silicon dioxide on silicon substrate. Different catalysts (i.e. Co, Fe, Mo, Ni acetate and bimetallic mixtures) were spin-coated onto the SiO₂ on Si chips for electrical testing in the temperature range between 500 and 900 deg. C [Ansaldo et al. 2007].

It was found that Co as catalyst results in a dense, “continuous carpet-like network”. On the other hand, when Fe, Mo, Co-Fe mixtures, Ni are used as catalysts, the single-wall carbon nanotubes are hard to find and of poor quality (i.e. described as either “short multi-wall nanotubes and other bent fibres” or “isolated tubes or very sparse networks” [Ansaldo et al. 2007]). Co-Ni compounds are most promising as catalysts, with relatively long and high-quality nanotubes, with the possibility to tune the production from carpet-like to isolated nanotubes [Ansaldo et al. 2007].

Ansaldo et al. have developed a novel method to transfer SWCNT networks grown on SiO₂ onto polymeric films at room temperature. Their networks show very high transparency in the infrared region. The networks, being able to be transferred onto a polycarbonate film, hold promise for a transparent, flexible and highly conductive material [Ansaldo et al. 2008].

Ansaldo et al. advocate for CVD-grown SWCNTs rather than by spraying or filtration. The latter methods have a main limitation wherein CNTs are deposited in the form of thick bundles and are mixed with insulating molecules to try to unbundle the CNTs. Ultrasonification which is used to help dispersion introduce defects in the tubes. The optimization of the CVD method is reported in [Ansaldo et al. 2009].

In the Raman spectrum of a carbon nanotube, the peaks of the graphite structure-derived *G*-band and the defect-derived *D*-band appear in the vicinities of 1590 cm⁻¹ and 1350 cm⁻¹, respectively. The ratio of the *G*/*D* band peaks can be used to evaluate both the crystal purity and defect concentration of the nanotube. Specifically, the higher this *G*/*D* ratio, the less amorphous components and defects present.

For the SWNTs analyzed in this thesis, we note that in the Raman data reported for the best catalyst ratio [see Ansaldo et al. 2007, Fig. 5], the *G* peaks are prominent while the *D* peaks are hardly visible. This high Raman *G*/*D* peak ratio indicates the high quality of the SWNT samples grown by Ansaldo and colleagues.

3.4.2 Direct grown carbon nanotube networks via patterned catalysts – Lima et al.

SWNT sample # 933-1, 933-2 (the same sample but at different drain current) by Lima et al. is grown by the direct (or in-situ) growth from patterned catalyst. That is, the growth of the SWNT via CVD is from specific catalyst regions patterned via photolithography. These specific patterned regions are in contrast to the global area growth of Ansaldo et al. in the previous section. The catalyst is a solid solution of $\text{MgO-Fe}_2\text{O}_3\text{-MO}_3$ in powder form [Lima et al. 2007].

The procedure to synthesize a CNT network is as follows: a quartz (SiO_2) surface is covered with a photoresist layer and subsequently patterned by photolithography. The catalyst is then applied over the patterned photoresist layer. CNTs are then synthesized in a CVD furnace [see Lima et al. 2007, Fig. 1 for an illustration].

3.4.3 Post-grown carbon nanotube networks – Andrade et al.

For comparison to the direct grown SWNT networks and as supporting information, we also analyze a post-grown SWNT network prepared by Andrade and colleagues. The method used is post-growth deposition via spray-coating method. That is, a suspension of already grown CNTs is deposited via spray-coating on a substrate [Andrade et al. 2007].

CHAPTER 4. Methodology for data analysis and modelling

The main work in this thesis is the modelling and fitting of experimental data. The sources of the experimental data have been detailed in the previous chapter. In this chapter, we shall present an overview of the mathematical concepts and coding involved in data analysis and modelling. Several software packages are used to facilitate this process. Data digitization is performed with Grafula II 2.32 (Wesik, Russia, 2000). Processing and analysis of data are accomplished via Origin 8.5 (OriginLab, USA, 2010) and MATLAB 7.13 (Mathworks, USA, 2011).

4.1 Data digitization – Grafula

Digitization in the context of this thesis can be defined as the representation of an image in the form of a graph as a set of discrete points. While raw data furnished to us by collaborator groups would not necessitate such a procedure, to analyze published data from the wider literature it is necessary to convert the published graphs into a tabulated form in order to enable analysis and modelling of data.

For this purpose, we utilize the digitization capability of the software Grafula II 2.32 (Wesik, Russia, 2000). In brief, the operation of the software is as follows. The user calls up an image in bitmap format of a graph of interest on Grafula, and informs the software of the locations of the zero origin, the maximum and minimum points of both axes alongside their scale values by manual input.

With the axes and zero origin points set up, the user then informs the software of the location of each data point of interest by manual input and each input is recorded as a value in the tabulated window of data points. A magnifying window assists the user in the input of the locations of the data points.

Fig. 4-1. Screenshot of the Grafula software in action.

Fig. 4.1 shows a representative screenshot of the Grafula software in action. The axes have been defined as shown by the green lines. We have added red lines as guides to the locations of the axes. The numerical scales of the axes are defined at the top-right window. As an example, several consecutive data points from two data sets have been digitized; this is seen as green and red circles in the graph (near the top-left region of the graphical image) which are translated into the tabulated data of the bottom-right window. The tabulated data are then transferred to other data analysis software, e.g. Origin, for modelling.

Another method for data digitization for graphs already in the Origin format is by using the Screen Reader tool in Origin. Fig. 4-2 shows this procedure. The representative screenshot demonstrates how a single data point can be obtained from the graph. In this example, our aim is to replot the data according to given values of the x-axis (blue lines in the figure). By thus digitizing, we obtain a tabulated set of data with respect to the given values of the x-axis for further analysis.

Fig. 4-2. An alternative way to digitize graphs is to use the Screen Reader tool in the Origin software.

4.2 Data analysis

4.2.1 Curve fitting and modelling – Origin

4.2.1.1 Chi-square and adjusted R^2 as indicators of quality of fit

Data analysis in modelling the experimental data is performed via the Origin 8.5 software (OriginLab, USA, 2010). In this section we shall overview the curve fitting principles behind the Origin software. Curve fitting is performed via a nonlinear regression model:

$$Y = f(X, \theta) + \epsilon \quad (4.1)$$

where the dependent variable (i.e. output, e.g. electrical conductance) Y is written as a function of independent variables (i.e. input, e.g. applied voltage) X and fitting parameters (e.g. the Mott coefficient) θ . The error term ϵ represents the unexplained variation in the dependent variable and is usually assumed to have a mean of zero.

Due to the nonlinear relationship between the dependent and independent variables, no explicit solutions exist for the equation parameters. Therefore, the parameter values need to be estimated using an iterative (i.e. computational) process.

To estimate the parameters, the chi-square minimization or “weighted least-square” method is used. The goal is to minimize the sum of the squares of the deviations between the theoretical curve and the experimental points for a range of independent variables. The chi-square value χ^2 is defined as follows:

$$\chi^2 = \sum_{i=1}^n \omega_i (y_{exp,i} - y_{theor,i})^2 \quad (4.2)$$

where ω_i is the weighting coefficient, $y_{exp,i}$ are the experimental data points, $y_{theor,i}$ are the theoretical points. The best quality fit is obtained for the parameter values that correspond to the minimum value of χ^2 , and this is done iteratively by the Origin software. (The maximum number of iterations n performed by Origin per run is 400.)

Another common measure of the quality of the fit is the coefficient of determination. The coefficient of determination R^2 is the square of Pearson’s correlation coefficient R , the latter defined as [Sheskin 2004, p. 950]:

$$R = \frac{\sum y_{exp,i} y_{theor,i} - \frac{(\sum y_{exp,i})(\sum y_{theor,i})}{n_i}}{\sqrt{\left[\sum y_{exp,i}^2 - \frac{(\sum y_{exp,i})^2}{n_i} \right] \left[\sum y_{theor,i}^2 - \frac{(\sum y_{theor,i})^2}{n_i} \right]}} \quad (4.3)$$

where the notations are consistent with earlier introduced symbols. In the case where the sampling value (i.e. number of data points) n_i is large, the correlation coefficient simplifies to

$$R \approx \frac{\sum y_{exp,i} y_{theor,i}}{\sqrt{(\sum y_{exp,i}^2)(\sum y_{theor,i}^2)}} \quad (4.4)$$

It is noted that the numerator $\sum y_{exp,i} y_{theor,i}$, being a sum of products, could possibly have a negative value. To avoid this issue, the coefficient is usually squared to keep the numerator always positive, thus:

$$R^2 = \frac{(\sum y_{exp,i} y_{theor,i})^2}{(\sum y_{exp,i}^2)(\sum y_{theor,i}^2)}. \quad (4.5)$$

The closer to 1 this coefficient is, the better the quality of the fitting curve.

There is however still a weakness associated with this coefficient. Note that R^2 is essentially the “fitting sum of squares” divided by the total sum of squares. The numerator can be artificially increased by adding the number of fitting parameters. On the other hand, the denominator remains fixed. Hence in theory, adding arbitrary fitting parameters could artificially increase the numerator thus giving the illusion that the correlation improves.

An “adjusted R^2 ” coefficient overcomes this weakness by adding to the denominator of R^2 the number of fitting parameters k :

$$adjusted\ R^2 = 1 - (1 - R^2) \left(\frac{n_i - 1}{n_i - k - 1} \right). \quad (4.6)$$

Both the adjusted R^2 and the minimum χ^2 coefficient values are used as a measure of the quality of fit in this work. For example, for two different fitting functions or models, the one with the lowest minimum χ^2 , and adjusted R^2 closest to 1, would be the best fit. The fit curves shown in this work generally have adjusted R^2 values exceeding 0.9000. The choice of weighting is found to influence the quality of fit; it is found that a ‘statistical’ weighting usually gives the best fit.

We note that the latest versions of the Origin software, including the one used in this work, calculates the adjusted R^2 coefficient in contrast to solely R^2 in its earlier versions. We emphasize that that means that the number of fitting parameters is taken into account in assessing the quality of fit.

4.2.1.2 Coding in C language

As a representative example, we demonstrate how our VRH crossover model (see Chapter 5) is implemented in the Origin fitting procedure. In brief, the crossover

consists of two theoretical regimes of VRH transport, namely the low-field VRH wherein conductance G follows:

$$G_{LOW\ FIELD}(T, |E|) = G_L \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{d+1}} \right] \exp \left(\frac{a|E|}{T} \right) \quad (4.7)$$

and the high-field VRH regime wherein G follows:

$$G_{HIGH\ FIELD}(|E|) = G_H \exp \left[- \left(\frac{E_0}{|E|} \right)^{\frac{1}{d+1}} \right]. \quad (4.8)$$

The meanings of the symbols are as introduced in Chapter 2. The modulus around the field parameter E introduced here is to account for the symmetrical behaviour of the conductance G across the positive and negative field values E .

In the C language syntax, this crossover model is implemented as follows:

```
#include <origin.h>

//-----
-

//

void _nlsfNEWonlyGhigh(
// Fit Parameter(s):
double G_H, double E_0,
// Independent Variable(s):
double E,
// Dependent Variable(s):
double& G)
{
    // Beginning of editable part
    if(E>0) {
        G=G_H*exp(-E_0/E^(0.3333333333));
    } else {
        E=-E;
    }
}
```

```

G=G_H*exp (-E_0/E^(0.3333333333)) ;
}

// End of editable part
}

```

Note that the expressions as coded above use the exponential form $\exp\left(-\frac{T'_0}{T^{\frac{1}{d+1}}}\right)$ instead of $\exp\left[-\left(\frac{T_0}{T}\right)^{\frac{1}{d+1}}\right]$ (and similarly, $\exp\left(-\frac{E'_0}{E^{\frac{1}{d+1}}}\right)$ instead of $\exp\left[-\left(\frac{E_0}{E}\right)^{\frac{1}{d+1}}\right]$). The Mott coefficient T_0 and Shklovskii coefficient E_0 are easily converted by a power change from T'_0 and E'_0 to be consistent with the notations in the rest of this thesis.

The most important feature of the code above is the use of the if-else condition to achieve mirror-image symmetry around the y-axis of conductance across both positive and negative applied voltages. This symmetry was not utilized in previous fittings by the group and is hence novel in this thesis. The use of the if-else code has two main advantages as follows.

Firstly, it considers all the data points over the whole measured range for a particular dataset instead of splitting the dataset according to positive and negative applied voltages. This increase in the number of data points certainly improves the fitting quality of the model to the data. Secondly, it achieves in a single fitting step, a fit to the whole dataset in half the effort compared to previous efforts when the data points were separated into the positive and negative applied voltages.

We proposed our crossover model incorporating two theoretical regimes motivated by the discovery that at certain intermediate temperatures, a single fitting expression was not sufficient to describe the data over the range of applied drain-source voltages. The fitting procedure employed in these cases is to mask off a certain range of data while the other is fitted with one expression first, and the process is inverted for the other expression.

This “double-fitting-and-masking” procedure requires discretion on the part of the observer, for example, in deciding how much of the data set to mask off and also in ensuring the two fit lines meet each other at the crossover point. Attempts were made to fully automate this process, i.e. to let the software simultaneously fit both functions at

once, with the crossover point by user input. However, this was not successful as ‘kinks’ resulted in the crossover region. The following paragraphs will describe this less successful attempt at full automation.

The code for the program is as follows:

```
#include <origin.h>

// Crossover point, X and temperature T will be manually
input

void _nlsfTryComposite(
// Fit Parameter(s):
double G_L, double T, double a, double T_0, double G_H,
double E_0, double X,
// Independent Variable(s):
double E,
// Dependent Variable(s):
double& G)
{
    // Beginning of editable part
    if(E>0){
        if (E>X){
            G=G_H*exp(-E_0/E^(1/3.0));
        } else {
            G=G_L*exp(a*E/T)*exp(-T_0/T^(1/3.0));
        }
    } else {
        E=-E;
        if (E>X){
            G=G_H*exp(-E_0/E^(1/3.0));
        } else {
            G=G_L*exp(a*E/T)*exp(-T_0/T^(1/3.0));
        }
    }
}
```

```

}
// End of editable part
}

```

Fig. 4-3. Representative output of attempted full automation of the fitting program showing kinks in the crossover regions.

A representative output of a graph fitted using this code is as shown in Fig. 4-3. We observe that fitting using the above program results in kinks at the crossover points, rather than perfectly smooth transitions. Looking into the program code, this is due to our usage of the if-else condition. To simplify, the pseudo-code is as follows:

```

If (voltage > crossover)
    [fit to high-field function]
else [fit to low-field function]

```

It would be better if some continuity can be forced at the crossover point. For example, before transitioning from one fitting function to the other, the value of conductance could be saved in the system and used as the starting value for the next fitting function. This would result in a smooth transition. A pseudo-code for this concept is as follows:

```

While (voltage < crossover)
    [fit to low-field function]
else [take note of the conductance value as  $G_1$ ;
    then starting with  $G_1$ , continue to fit to low-field
    function]

```

However, attempts to implement this code into Origin have not been successful, as this would necessitate the do-while condition instead of if-else. The problem with the do-while condition is it operates in an infinite loop, and no output could be obtained. It most probably is beyond the capability of the Origin software to implement this fully automated concept.

4.2.2 Numerical calculations – MATLAB

Early attempts were made in MATLAB to model the experimental data by fitting them to physical functions; this was eventually found easier done with the Origin software. However, the MATLAB 7.13 software (Mathworks, USA, 2011) is found to be helpful in performing analytical calculations. Coding is performed in the C language syntax similar to Origin.

An example of the MATLAB program used to calculate the crossover point, i.e. the field value when crossover occurs between the two VRH regimes in our crossover model, is as follows:

```

d=2; %dimension
T=40; %temperature
% enter these values from table
a_min=1.4e2;
a_max=1.5e2;
E_0_min=8.3;
E_0_max=9;

```



```

% calculate crossover point range
X_min=((d+1)*a_min/(T*E_0_min))^-((d+1)/(d+2));
X_max=((d+1)*a_max/(T*E_0_max))^-((d+1)/(d+2));
X=(X_min+X_max)/2
plusminus=(X_max-X_min)/2

```

The crossover field expressions, denoted by symbol X in the code, refer to expressions for $E_{crossover}(T)$ derived in Chapter 5.1.1, i.e. $E_{crossover}(T) = \left(\frac{a(d+1)}{TE_0^{\frac{1}{d+1}}} \right)^{-\frac{d+1}{d+2}}$. We note that the expressions as coded above writes the Shklovskii coefficient in the exponential term as $\exp\left(-\frac{E'_0}{E^{\frac{1}{d+1}}}\right)$ instead of $\exp\left[-\left(\frac{E_0}{E}\right)^{\frac{1}{d+1}}\right]$. The Shklovskii coefficient E_0 is easily converted by a power change from E'_0 as coded, to be consistent with the notations in the rest of this thesis.

What the above program does is it calculates the crossover field value based on the range of fitting parameters input into the system. These fitting parameters are obtained from Origin's curve fitting program from the previous section. At a certain system dimensionality d and temperature T , the user inputs the range of values (minimum and maximum values) of the fitting parameters a and E_0 .

The program then calculates the maximum and minimum values of the crossover field point E_C , shown in the above program as X , and displays as output the average value of the crossover point. As an example, for disordered graphene at a temperature of 40 K and with zero applied gate voltage, the corresponding fitting parameters (see Chapter 5, Table 5.1) when input into the program results in an output of a calculated crossover point as follows:

```

>> Program_calculate_Crossover
X =
    0.8421
plusminus =
    0.0038

```

In this example, we obtain a crossover voltage of 0.8421 ± 0.0038 V. To two significant figures, the crossover voltage E_C is 0.84 V, as reported in our paper [Cheah et al. 2013, p. 4] and shown in Chapter 5, Table 5.1(b). The crossover voltages at other non-zero gate voltages are obtained in a similar manner as described above.

CHAPTER 5. Results and discussion: variable-range hopping transport in disordered carbon materials

In this chapter, we will present results and discussions of a proposed crossover variable-range hopping (VRH) model involving established theoretical framework of two distinct regimes of VRH. Specifically, this model consists of a crossover between temperature-dependent hopping to field-dependent hopping, with the crossover field given by our analytical expression.

This model is shown to give a very good explanation for the experimentally measured conductance of not only partially disordered graphene [Cheah et al. 2013], but also disordered carbon materials of other dimensionalities, namely 3D self-assembled carbon networks and quasi-1D highly-doped conducting polymers [Cheah and Kaiser 2014]. We estimate the average hopping distance based on fitting parameters, and investigate the theoretical prediction of the order equivalence of the temperature- and field-scaling parameters.

We also present exploratory, unpublished work which details the attempts at further improving this model. Specifically, two phenomenological models are presented wherein a single fitting function can apply to describe the experimental data instead of two fitting functions that crossover between each other.

5.1 A model of crossover from temperature-dependent to field-dependent variable-range hopping transport

5.1.1 Reduced graphene oxide

Due to the chemical processes involved in the preparation of reduced graphene oxide (rGO), see Chapter 3.1, the resulting graphene inherently contains disorder. We emphasize that our rGO samples are only partially disordered in contrast to the highly disordered graphene of [Lo et al. 2013] which exhibits different electronic transport behaviour from our samples.

Scanning tunnelling microscopy (STM) measures the electron charge density distribution on the sample surface, thereby serving as a good indicator of the surface morphology at the atomic level of the sample. Fig. 5-1(a) shows a representative STM image on our rGO samples prepared by Gómez-Navarro and colleagues which reveal disordered regions interspersed between highly crystalline regions.

The disordered regions in rGO are attributed to oxygenated functional groups [Gómez-Navarro et al. 2007; Loh et al. 2010], cf. atomic model in Fig. 5-1(b). We observe formerly oxidized regions (areas indicated within green lines) that remain disordered after reduction while outside the green lines, a significantly more crystalline structure of the graphene is observed. The size of the disordered regions obtained from the STM image is around 6 nm [Gómez-Navarro et al. 2007].

We shall now focus on the electrical conductance data. The electrical conductance data of rGO at temperatures of 40 and 220 K have been previously published by Kaiser and colleagues. The electronic transport mechanism at temperature of 220 K has been suggested to be a combination of variable-range hopping (VRH) plus

a temperature-independent residual metallic conduction term [Kaiser et al. 2009]. The 40 K data were shown in the paper [Kaiser et al. 2009] but no analysis was made.

Fig. 5-1. (a) Scanning tunnelling microscopy (STM) by Gómez-Navarro et al. reveals formerly oxidized regions (inside green lines) on the rGO that remain disordered after reduction. Meanwhile, a significantly more crystalline structure of the graphene is observed outside the areas marked in green. Reproduced with permission from [Gómez-Navarro et al. 2007]. Copyright 2007 American Chemical Society. (b) Atomic model by Bagri et al. of typical rGO showing remnant oxygen atoms (in red) and vacancies amongst the carbon atoms (in grey). Reproduced with permission from [Bagri et al. 2010]. Copyright 2010 Macmillan Publishers. (c) This bulk carbon network observed via scanning electron microscopy (SEM) by Govor et al. appears to resemble a 3D, micron-scale analogue (with ring diameters $\sim 1 \mu\text{m}$ and sample thickness $\sim 10 \mu\text{m}$) to the hexagonal atomic arrangement of carbon in graphene. Electrical data of these bulk carbon networks are discussed later in Chapter 5.1.2. Reproduced with permission from [Govor et al. 2000]. Copyright 2000 American Physical Society.

In this thesis, we analyze these electrical conductance data at temperatures of 40 and 220 K and in addition also unpublished data at a temperature of 2 K and present a conduction model for all three temperatures wherein a complete physical model emerges to describe the whole temperature range from absolute zero to near room temperature and across the measured range of applied voltages.

Before we proceed, it is important to note that the experimental data of electrical conductance at a temperature of 2 K has been corrected for leakage current at low source-drain voltage biases wherein significant scattering of the data points are observed at this low temperature. This work was done by Jaurigue, Kaiser and Gómez-Navarro and is shown in Fig. 5-2.

Fig. 5-2. Electrical conductance data of the reduced graphene oxide by Gómez-Navarro et al. at a temperature of 2 K are corrected for leakage current effects significant at this low temperature, shown representatively at gate voltage $V_g = -20$ V. Parts (c) and (d) show the raw data of current I versus drain-source bias voltage V_{ds} before correction, while parts (a) and (b) show the same data after correction for leakage current wherein $I = 0$ when $V_{ds} = 0$. In (b), there still remains some residual scattering of conductance data around the range $|V_{ds}| \leq 0.1$; these outliers are eliminated from further analysis, cf. Fig. 5-10 (a). Reproduced from an unpublished report by Jaurigue, Kaiser and Gómez-Navarro.

Owing to the characteristic conical electronic band structure in graphene (see Fig. 1-2), a positive V_g applied to the gate produces a substantial density of electron carriers in the graphene layer. On the other hand a negative V_g produces hole carriers. At $V_g = 0$ i.e. near the charge neutrality point, conductivity is at a minimum as charge carriers exist in sparse puddles of electrons and holes [Martin et al. 2008; Adam et al. 2011]. The terminology “electron-hole puddles” is used in graphene literature to refer to spatial charge density fluctuations in the charge neutrality point [see e.g. Martin et al. 2008, Fig. 3].

Fig. 5-3 shows an overview of the electronic conductance G behaviour at temperatures of 220, 40 and 2 K at zero applied gate voltage V_g . The semi-logarithmic plot shows experimentally measured conductance versus the drain-source voltage V_{ds} at the three temperatures T as indicated. We find that the experimental data (of Gómez-Navarro and colleagues, shown as symbols) can be well described by our crossover model (shown as red and green curves) incorporating two distinct regimes of VRH introduced in Chapter 2.1.

Fig. 5-3. Semi-logarithmic plot of conductance G versus drain-source voltage V_{ds} of rGO at three temperatures T as indicated, at zero gate voltage V_g . Experimental data of Gómez-Navarro et al. are shown as symbols while fits to our 2D VRH crossover model are shown as red and green curves, with the crossover points indicated by red arrows.

Published in [Cheah et al. 2013]. Copyright 2013 IOP Publishing.

Our VRH crossover model, shown as red and green curves, consists of the following theoretical framework. The red curves are fits to field-assisted, temperature-driven 2D VRH, according to the theory of Pollak and Riess, as defined in Chapter 2.1.3:

$$G_{LOW\ FIELD}(T, E) = G_L \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{d+1}} \right] \exp \left(\frac{aE}{T} \right), \quad (5.1)$$

but with conductance G replacing the conductivity σ terms with a trivial unit conversion. The green curves are fits to field-driven 2D VRH, according to the theory of Shklovskii, as defined in Chapter 2.1.4:

$$G_{HIGH\ FIELD}(E) = G_H \exp \left[- \left(\frac{E_0}{E} \right)^{\frac{1}{d+1}} \right], \quad (5.2)$$

again with conductance G replacing the conductivity σ terms.

We observe that at a temperature of 220 K (Fig. 5-3), the conduction can be fully explained via the 2D Pollak-Riess theory of field-assisted, temperature-driven VRH. On the other hand, near absolute zero at a temperature of 2 K, the conduction can be fully explained via the 2D Shklovskii theory of field-driven VRH. It is most interesting at the intermediate temperature of 40 K that a crossover or transition occurs between these two Pollak-Riess and Shklovskii VRH regimes; this is shown in Fig. 5-4.

Fig. 5-4. A close-up of the conductance crossover region at 40 K showing the construction of our crossover model. Symbols and colours are as defined in Fig. 5-3.

Fig. 5-3 gave a first idea on the electrical transport behaviour at the charge neutrality point, i.e. zero applied gate voltage $V_g = 0$ wherein conductivity is at a minimum and contributed by the presence of puddles of electrons and holes. It is of interest to see whether similar trends develop at the same intermediate temperature of 40 K at other applied gate voltages.

Fig. 5-5 shows that as the applied gate voltage is positive and negative, corresponding to the majority charge carriers being electrons and holes respectively, the same conduction trends are observed in a qualitative manner. Quantitatively, we observe that electronic conduction (corresponding to $V_g = -20$ V) gives a higher conductance than hole conduction ($V_g = 20$ V) and both of these conductances are in turn higher than that of the charge neutrality region where applied gate voltage is zero. The larger magnitudes of conductance for hole and electronic conduction are expected due to the much larger carrier densities available for conduction.

Fig. 5-5. Semi-logarithmic plot as in Fig. 5-1 showing the different magnitudes of conductance at a temperature of 40 K for different gate voltages corresponding to hole conduction and electron conduction as well as near the charge neutrality point. Dashed lines, as in Fig. 5-4, are representative extrapolations of the fits beyond their appropriate limits, demonstrating the VRH crossover behaviour. Published in [Cheah et al. 2013].

Copyright 2013 IOP Publishing.

Fig. 5-6 presents an alternative visualization of the data in Fig. 5-3, wherein a linear-linear plot of conductance versus drain-source voltage is used instead of a semi-logarithmic plot of the latter figure. We see that in this configuration, the data near room temperature, at temperature of 220 K is emphasized but the data at lower temperatures collapse into too low conductance magnitudes for satisfactory display. However it is still helpful to note that our model shows a decent fit to the experimental data.

Fig. 5-6. Alternative visualization of Fig. 5-3 as a linear-linear plot of conductance G versus drain-source voltage V_{ds} of rGO at three temperatures T as indicated, at zero gate voltage V_g . Fig. 5-3 used a semi-logarithmic plot of conductance versus the drain-source voltage.

In Fig. 5-7 we present the data in Fig. 5-3 plotted as logarithmic conductance versus the inverse one third of the drain-source voltage. In this configuration, we emphasize the high-field behaviour of the conduction. Also, as can be observed by the green lines, the linearity of the logarithm of conductance versus the inverse one third of the voltage shows the characteristic 2D field dependence of the VRH model.

The parts of the experimental data (shown as symbols) in Fig. 5-7 that do not exhibit such linearity of conductance with respect to the inverse one third of the drain-source voltage, indicate that the field dependent regime of Shklovskii no longer holds. As shown by the fits in red, this second regime is the temperature-driven regime of

Pollak and Riess. This highlights the need for our crossover VRH model to explain the complete range of data at various temperatures and voltages.

Fig. 5-7. Logarithmic conductance G plotted versus the inverse one third drain-source voltage $V_{ds}^{-1/3}$ of rGO at three temperatures T as indicated, at zero gate voltage V_g .

As the data for temperatures of 2 and 40 K have not been previously analyzed, we focus further on the data at these two temperatures. In Fig. 5-7 we observe that near charge neutrality at zero applied gate voltage, the data at a temperature of 2 K can be described by the field-driven Shklovskii VRH regime.

Fig. 5-8 presents further data at the same temperature but at different gate voltages, corresponding to dominant hole and electronic conduction, to convince the reader of the similar applicability of the field-driven regime theory. We restrict the x -axis to only values of $0 \leq |V_{ds}| \leq 8$ V and cut off the axis at higher values to avoid too much extrapolation of the experimental data.

The semi-logarithmic, inverse one third plot configuration of the previous two figures can also be helpful in providing an alternative representation of the data in Fig. 5-5. We present the conductance data at a temperature of 40 K in Fig. 5-9. The green lines are fits to the field-driven regime of Shklovskii, crossing over to the red curves which are fits to the temperature-driven regime of Pollak and Riess.

Fig. 5-8. Logarithmic conductance G plotted versus the inverse one third drain-source voltage $V_{ds}^{-1/3}$ of rGO at a temperature of 2 K, for zero and non-zero gate voltages V_g in rGO. Published in [Cheah et al. 2013]. Copyright 2013 IOP Publishing.

Fig. 5-9. Semi-logarithmic plot of conductance G versus the inverse one third drain-source voltage $V_{ds}^{-1/3}$ at a temperature of 40 K, for zero and non-zero gate voltages V_g in rGO. Published in [Cheah and Kaiser 2014]. Copyright 2014 Inderscience.

In the following set of figures, Fig. 5-10, we present the complete data at the three temperatures of 2, 40 and 220 K at zero and non-zero gate voltages. Note that the crossover of the regime can be observed to occur as the temperature is increased from graph (a) to (c). We observe a very slight asymmetry of the conductance with respect to

the applied drain-source voltage V_{ds} . The magnitude of conductance is slightly higher at negative V_{ds} values compared to positive ones. This could be due to the presence of small Schottky barriers at the interface between the sample and electrodes which behave differently depending on the direction of charge carrier flow.

Note that as mentioned in Chapter 4.2.1.2, we employ in this thesis a mirror-symmetry method in our fitting model; a condition not imposed in previous analysis of the group. This is to ensure that the complete range of data is taken into account in one go without having to split the data set into positive and negative applied drain-source voltages. We believe that the increased sample size in the data set allows for an improved quality of fit, and that the slight deviation of the experimental data from the modelling fits due to the slight asymmetry of conductance is negligible.

Fig. 5-10 (continued at next page). Semi-logarithmic plot of conductance G versus drain-source voltage V_{ds} of rGO at temperatures of (a) 2; (b) 40; and (c) 220 K, at zero and non-zero gate voltages V_g . Experimental data of Gómez-Navarro et al. are shown as symbols while fits to our 2D VRH crossover model are shown as red and green curves.

Fig. 5-10 (continued). Semi-logarithmic plot of conductance G versus drain-source voltage V_{ds} of rGO at temperatures of (a) 2; (b) 40; and (c) 220 K, at zero and non-zero gate voltages V_g . Experimental data of Gómez-Navarro et al. are shown as symbols while fits to our 2D VRH crossover model are shown as red and green curves.

Table 5.1. Fitting parameters for our model based on experimental conductance of rGO at temperatures of (a) 2; (b) 40; and (c) 220 K, with fitting expressions as stated in the text (see p. 58). Spatial dimensionality $d = 2$ for graphene. Where a range of parameters are applicable, the values are given in brackets. The calculated crossover voltages for the intermediate temperature of 40 K are also listed in (b).

(a)			
Parameters at $T = 2 \text{ K}, V_g (V) =$	-20	0	20
$G_H (S)$	3.5×10^{-4}	$(3.4 - 3.7) \times 10^{-4}$	1.1×10^{-3}
$(E_0)^{\frac{1}{3}} (V^{\frac{1}{3}})$	9.3	12 - 13	13

(b)			
Parameters at $T = 40 \text{ K}, V_g (V) =$	-20	0	20
$G_L (S)$	$(6.0 - 7.5) \times 10^{-9}$	$(1.8 - 2.8) \times 10^{-10}$	$(1.4 - 1.6) \times 10^{-9}$
$a (K.m/V)$	102	120	103
$T_0 (K)$	91232	40548	57811
$G_H (S)$	$(1.6 - 2.7) \times 10^{-5}$	$(1.8 - 3.3) \times 10^{-5}$	2.0×10^{-5}
$(E_0)^{\frac{1}{3}} (V^{\frac{1}{3}})$	(5.3 - 5.9)	(8.3 - 9.0)	7.2
$V_{crossover} (V)$	0.66 ± 0.03	0.84	0.87 ± 0.03

(c)			
Parameters at $T =$ $220 \text{ K}, V_g (V) =$	-20	0	20
$G_L (S)$	8.5×10^{-7}	2.2×10^{-7}	3.8×10^{-7}
$a (K.m/V)$	27.2	52.0	29.4
$T_0 (K)$	91232	40548	57811

The values of the fitting parameters used for the data of rGO at various temperatures and voltage conditions are summarized in Table 5.1. Fitting functions are as introduced early in this section with spatial dimensionality $d = 2$ for graphene. We can understand the parameter G_H as the saturation conductance in the limit of high applied electric field. On the other hand, we can understand the parameter G_L as the conductance as the applied electric field tends to zero.

To obtain the values of the Mott coefficients T_0 , we use the idea of plotting the low-field limit conductance magnitudes G_L , which serve as the zero intercepts on the y-axis at $V_{ds} = 0$, versus temperature T . This effectively fixes the electric field while only

varying the temperature. Thus one T_0 value holds for all temperatures instead of being varied with temperature as in Table 5.1. The graph is then fitted to the 2D Mott VRH model:

$$G_L = G_0 \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{3}} \right], \quad (5.3)$$

to obtain the values of T_0 , as shown in Fig. 5-11.

We obtain from the graph values of $T_0^{\frac{1}{3}} = 45$ ($V_g = -20$ V); 39 (+20); 34 (0) $K^{\frac{1}{3}}$ equivalent to $T_0 = 91232$ ($V_g = -20$ V); 57811 (+20); 40548 (0) K. Note that these values are at $V_{ds} = 0$. As a check for our values, we refer to T_0 values reported previously for similar rGO samples but from a different batch and at $V_{ds} = 0.1$ V [Kaiser et al. 2009], and these are $T_0^{\frac{1}{3}} \sim 36$ ($V_g = -20$ V); 53 (+20); 53 (0). These values are read from the graph of [Kaiser et al. 2009, Fig. 4(a)]. We see that our T_0 values are in satisfactory agreement with the reported values in the literature for a different batch of rGO samples.

Fig. 5-11. Obtaining the Mott coefficient from the rGO conductance data of Gómez-Navarro et al. by plotting low-field limit conductance G_L (symbols) versus temperature T and fitted to 2D Mott VRH model (lines).

Based on the fitting parameters, we can calculate the mean hopping distances in the disordered regions in rGO, from the low-field VRH fits (red curves in Figs. 5-3 to 5-10). From the value of the fitting parameter a of Table 5.1, we can calculate the hopping distance r at a given temperature T and applied gate voltage V_g via the formula

$$r(T, V_g) = \frac{ak_B L}{0.18e} \quad (5.4)$$

where k_B is the Boltzmann constant and e is the electronic charge. The hopping distance is multiplied with the distance between electrodes $L = 1.1 \mu m$ to convert electric field E to its corresponding voltage V , following the relation $V = EL$. The latter conversion is necessary because the fits are performed on voltage values on the x -axis rather than the field.

At a temperature of 40 K, the mean hopping distance at zero applied gate voltage is:

$$r(T = 40, V_g = 0) = 7.8 \times 10^{-8} m$$

Meanwhile, at non-zero gate voltages at the same temperature, mean hopping distances are:

$$r(T = 40, V_g = 20) = 6.3 \times 10^{-8} m$$

$$r(T = 40, V_g = -20) = 6.9 \times 10^{-8} m$$

Therefore we obtain, to two significant figures, mean hopping distances of 78 nm (at zero V_g), 63 nm (positive V_g) and 69 nm (negative V_g). Averaging the three cases, which correspond to near charge neutrality, majority electron and hole transports respectively, we obtain an estimate of the mean hopping distance of 70 nm at temperature 40 K.

This mean hopping distance of 70 nm is considerably larger than the 6 nm disordered regions inferred from STM data on the graphene samples [Gómez-Navarro et al. 2007], see Chapter 5.1.1. We attribute this large magnitude of the mean hopping distance to the assumption that the electric field is distributed uniformly throughout the graphene sample. Specifically, in our calculations, the electric field is averaged over the whole graphene sample, using $E_{ave} = V_{ds}/L$. It is thus argued that the electric field magnitude is not equal for the disordered and crystalline regions in the rGO. Instead, in

the disordered regions where hopping occurs and contributes to the dominant resistance of the rGO, the electric field is one order of magnitude larger [Kaiser et al. 2009] in the disordered regions compared to the average value of the applied field.

An elaboration of the physical justification of the non-uniformity of electric field distribution within the rGO comprised of disordered regions amongst more crystalline regions is in order. We emphasize that the mean hopping distances $r(T)$ calculated from theory are averages over the whole sample. In reality, the rGO sample is probably on the order of 10 % disordered – as first proposed by [Kaiser et al. 2009] – where most of the resistance contribution comes from, thus resulting in the VRH conduction mechanism observed. Based on the STM image of Fig. 5-1(a), we can model the resistance contributions from the disordered and more crystalline regions of the rGO as series resistors thus:

$$R_{total} = R_{disordered} + R_{crystalline}. \quad (5.5)$$

As the resistance in the crystalline regions is negligible (near ballistic transport) compared to resistance from the disordered regions, the total resistance contribution is thus:

$$R_{crystalline} \ll R_{disordered}; \quad (5.6)$$

$$R_{total} \approx R_{disordered}. \quad (5.7)$$

As the current flowing through the sample is equal, i.e. $I_{disordered} = I_{crystalline} = I$, it follows that the applied drain-source voltage would be mainly concentrated in the disordered region:

$$V_{total} \equiv V_{ds,applied} \approx V_{disordered}. \quad (5.8)$$

Due to our assertion that *in the order of* 10 % of our rGO sample is disordered [Kaiser et al. 2009], it follows that the electric fields (according to the definition $E = V/L$) in

the disordered regions is thus *in the order of* 10 higher than the field in the more crystalline regions:

$$E_{disordered} \approx 10 \times E_{crystalline}; \quad L_{disordered} = \frac{1}{10} \times sample. \quad (5.9)$$

Thus, in correcting for the non-uniform electric field distribution across the sample, a realistic mean hopping distance in the disordered regions would be one order less than that calculated above, i.e. closer to 7 nm rather than 70 nm at a temperature of 40 K.

Meanwhile, at temperature of 220 K, the mean hopping distance is calculated as follows:

$$r(T = 220; V_g = 0) = 2.7 \times 10^{-8} \text{ m} \quad (5.10)$$

and we obtain (to two significant figures) a mean hopping distance of 27 nm. Correcting for non-uniform electric field as per above, we take the realistic value of the mean hopping at a temperature of 220 K to be closer to 3 nm.

We observe that the mean hopping distance decreases as the temperature is increased, i.e. from ~ 7 nm at 40 K down to ~ 3 nm at 220 K. This is consistent with VRH theory which states the range in position space of typical hops decreases with the increase of temperature. This is because more near equivalent energy states exist at closer distances at higher temperatures, hence the average hop lengths decrease.

We also note that our calculated hopping distance of 27 nm at a temperature of 220 K somewhat disagrees with the value of 63 nm obtained in [Kaiser et al. 2009] for the same temperature. This is because the cited work introduced an additional constant G_0 to the low-field VRH expression (see [Kaiser et al. 2009, Eq. (3)]) to describe a temperature-independent residual metallic conductivity. We have omitted the unnecessary parameter G_0 in this work, as we suggest that any residual metallic conductivity is negligible compared to the dominant resistance contribution from VRH within the disordered regions. The present model and calculated values presented here in which the unnecessary residual metallic term is omitted, we believe to be more accurate than that previously presented in [Kaiser et al. 2009].

We now move on to focus on obtaining an analytical expression for the crossover field point that mediates the transition between the temperature-driven and field-driven VRH regimes. We notice that when such crossover occurs at the intermediate temperature of 40 K, see Fig. 5-4, the slopes of the fitting curves equate at the point of the crossover field (or voltage in this case). Thus we can obtain the analytical expression for a $E_{crossover}$ by equating both slopes of the intersecting lines at the crossover point.

First, we obtain the slope m_L of low-field VRH region in the figures,

$$\begin{aligned}
 G_{LOW\ FIELD}(T, E) &= G_L \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{d+1}} \right] \exp \left(\frac{aE}{T} \right) \\
 \Rightarrow \ln[G_{LOW\ FIELD}(T, E)] &= \ln(G_L) - \left(\frac{T_0}{T} \right)^{\frac{1}{d+1}} + \left(\frac{aE}{T} \right) \\
 m_L &= \frac{d \ln[G_{LOW\ FIELD}(T, E)]}{dE} = \frac{a}{T}.
 \end{aligned} \tag{5.11}$$

Meanwhile, the slope m_H of the high-field VRH region is,

$$\begin{aligned}
 G_{HIGH\ FIELD}(E) &= G_H \exp \left[- \left(\frac{E_0}{E} \right)^{\frac{1}{d+1}} \right] \\
 \Rightarrow \ln[G_{HIGH\ FIELD}(E)] &= \ln(G_H) - \left(\frac{E_0}{E} \right)^{\frac{1}{d+1}} \\
 m_H &= \frac{d \ln[G_{HIGH\ FIELD}(E)]}{dE} = \frac{E_0^{\frac{1}{d+1}}}{d+1} E^{-\frac{d+2}{d+1}}.
 \end{aligned} \tag{5.12}$$

By equating both slopes, $m_L = m_H$, we thus obtain the analytical expression for the crossover point for a sample of dimensionality d at a given temperature T ,

$$E_{crossover}(T) = \left(\frac{a(d+1)}{T E_0^{\frac{1}{d+1}}} \right)^{-\frac{d+1}{d+2}}. \tag{5.13}$$

We note that only two experimental fitting parameters i.e. a and E_0 are needed to calculate the value of the crossover field. As an example, for graphene conductance at a temperature of 40 K (i.e. $d = 2$, $T = 40$), and using the values of the fitting parameters a and E_0 from Table 5.1, we obtain a crossover voltage of:

$$E_{crossover}(40\text{ K})_{2D} = \left(\frac{3a}{TE_0^{\frac{1}{3}}} \right)^{-\frac{3}{4}} = 0.84\text{ V}.$$

We have written a MATLAB program to assist in the calculation to this effect, as described in Chapter 4.2.2. The analytical expression for the crossover field is written in alternative notation for a cleaner presentation in our paper [Cheah et al. 2013]. It is given in this form:

$$E_{crossover}(T) = (pE_aE_0^p)^{(p+1)^{-1}}, \quad (5.14)$$

where the notations $p = (d + 1)^{-1}$ and $E_a = \frac{k_B T}{0.18r(T)e} \equiv \frac{T}{a}$ are used. In the 2D case, the expression becomes:

$$E_{crossover}(T)_{2D} = \left(\frac{E_a E_0^{\frac{1}{3}}}{3} \right)^{\frac{3}{4}}. \quad (5.15)$$

5.1.2 3D carbon networks

We can now proceed to show that our VRH crossover model presented at length in the previous section to describe the experimentally measured conductance data of rGO, is also applicable to other carbon materials of different dimensionalities. For the 3D case, we use the data of Govor et al. [2000] as we note that the plot of their conductivity data versus applied field in their carbon networks, Fig. 5-12, shows very similar qualitative trends to the plot of conductance versus applied source-drain voltage in disordered graphene (cf. Fig. 5-3).

Fig. 5-12. Plot of natural logarithm of the conductivity σ versus applied field E in 3D carbon networks shows similar trends as for disordered graphene, cf. Fig. 5-3. Experimental data of [Govor et al. 2000] are shown as symbols while fits to our 2D VRH crossover model are shown as red and green curves, with the crossover points indicated by red arrows. Published in [Cheah et al. 2013]. Copyright 2013 IOP Publishing.

The similar conductance trends suggest the fits we presented earlier for graphene should also apply to these carbon networks, with a change of spatial dimensionality from the 2D graphene to 3D (i.e. $d = 3$) for the carbon networks under consideration. The three-dimensionality of the carbon network is justified by the reported sample thickness of ~ 100 nm [Govor et al. 2000] thereby qualifying it as a bulk conduction material. It is interesting that physically the bulk carbon network seems to resemble a micron-scale analogue to the hexagonal arrangements of carbon atoms in graphene, Fig. 5-1(c). The excellent fit of our model to their experimental data shows that our proposed model of crossovers occurring from temperature-driven (or low-field) to field-driven (or high-field) VRH at intermediate temperatures applies irrespective of the system dimensionality.

It must be noted that in their paper, Govor and colleagues have already suggested a crossover model for their conductivity data which is somewhat similar to our model proposed here. Specifically, they showed that $T^{-\frac{1}{4}}$ crossed over to E^n

behaviour where n is scaled from zero to one according to increasing electric field and temperature [Govor et al. 2000; 2002]. As opposed to their model, we present a more intuitive picture which preserves the system dimensionality, by crossing over from a low-field VRH, $T^{-\frac{1}{4}}$, into a high-field VRH, $E^{-\frac{1}{4}}$, without the need for a scaling index. We believe that the simplicity of our model, justified by the excellent fits to their data, presents a better description of the charge transport observed.

Fig. 5-13 shows a plot of conductivity versus the inverse one fourth applied electric field $E^{-\frac{1}{4}}$ to emphasize the linearity of conductivity at high fields, a characteristic of high-field VRH in three dimensional systems. It can be observed when plotted using these axes, that at a temperature of 4.2 K the conductivity appears to deviate from linearity, i.e. undergoes a minor crossover into low-field VRH at around $E^{-\frac{1}{4}} = 0.28 \text{ (V/cm)}^{-1/4}$, which corresponds to electric field of $E = \left(\frac{1}{0.28}\right)^4 = 0.16 \times 10^3 \text{ V/cm}$. The data at this field value, nearly zero, is barely visible in the plot of Fig. 5-12. This highlights the advantage of plotting against the inverse one fourth power, $E^{-\frac{1}{4}}$, as a complement to plotting against E in our data analysis.

Fig. 5-13. Plot of natural logarithm of the conductivity versus the inverse one fourth power of the applied field in 3D carbon networks. Experimental data of [Govor et al. 2000] are shown as symbols while fits to our 2D VRH crossover model are shown as red and green curves, with the crossover points indicated by red arrows. Published in [Cheah and Kaiser 2014]. Copyright 2014 Inderscience.

Values of fitting parameters are summarized in Table 5.2. As with the case for graphene, the graphical method of obtaining the Mott coefficient T_0 is illustrated in Fig. 5-14. The figure shows the values of the zero-intercept values of the x -axis (i.e. at zero applied field $E = 0$), $\ln \sigma_L$ versus temperature T , and fitted to 3D Mott VRH, $\ln \sigma_L = \ln \sigma_0 + \left(-\frac{T_0}{T}\right)^{\frac{1}{4}}$ to obtain the value of T_0 . In the inset of Fig. 5-14, we illustrate that plotting against $T^{\frac{1}{4}}$ would result in a linear fit.

We obtain $T_0 = (2.55178)^4 = 42.4 \text{ K}$. We note that the reported value of T_0 at a temperature range of 4.2 to 26 K is 80.0 K; this value is taken from [Govor et al. 2000, Table 2, sample 7]. The disagreement between our value and theirs is due to the different analysis method used. The main difference is that Govor and colleagues used a piecemeal approach in dividing the temperature range into several sections, while our analysis considers the complete temperature range as a whole.

Table 5.2. Fitting parameters for our model based on experimental conductivity of 3D carbon networks at various temperatures, with fitting expressions as stated in the text (see p. 58). Spatial dimensionality $d = 3$ for bulk carbon networks.

Parameters at $T \text{ (K)} =$	4.2	15	30	50	100
$[\ln \sigma_L \left(\frac{S}{cm}\right)]$	-	2.3	2.5	2.6	2.8
$a \text{ (K.cm/V)}$	-	6.9×10^{-4}	5.2×10^{-4}	3.7×10^{-4}	2.7×10^{-4}
$T_0 \text{ (K)}$	42.4				
$[\ln \sigma_H \left(\frac{S}{cm}\right)]$	3.3	3.3	3.1	-	-
$(E_0)^{\frac{1}{4}} \left(\frac{V}{cm}\right)^{\frac{1}{4}}$	1.9	1.9	1.5	-	-

Fig. 5-14. Obtaining the Mott coefficient T_0 by plotting low-field limit conductivity $\ln \sigma_L$ (symbols) versus temperature T , and fitted to 3D Mott VRH, $\ln \sigma_L = \ln \sigma_0 + \left(-\frac{T_0}{T}\right)^{\frac{1}{4}}$ shown as red lines. Inset shows plotting against $T^{\frac{1}{4}}$ gives a linear fit.

We use the analytical expression for our crossover point $E_{crossover}$ to calculate the crossover fields when low-field VRH crosses over to high-field VRH transport. With reference to the fitting parameter values from Table 5.3, we can obtain the crossover field at temperature 30 K:

$$E_{crossover}(30\text{ K})_{3D} = \left(\frac{4a}{TE_0^{\frac{1}{4}}} \right)^{-\frac{4}{5}} = 2.9 \times 10^3 \text{ V/cm},$$

as well as the crossover field at temperature 15 K,

$$E_{crossover}(15\text{ K})_{3D} = \left(\frac{4a}{TE_0^{\frac{1}{4}}} \right)^{-\frac{4}{5}} = 1.6 \times 10^3 \text{ V/cm},$$

which match the crossover points indicated by red arrows in Fig. 5-12.

We can also show mathematically the trivial cases wherein no crossover is seen to occur for the measured voltage or field range. We illustrate this using data for the 3D carbon networks but it must be noted that the results are equally valid for 2D systems. As an example, by observing the trend of a as temperature decreases in Table 5.2, we can infer that the slope parameter a would tend toward infinity at the limit of very low temperature.

Graphically, this can be interpreted that the low-field VRH fit would tend toward become almost parallel with the y-axis at the very-low temperature limit. Thus, setting the slope parameter a to tend toward infinity,

$$a \rightarrow \infty,$$

begets:

$$\lim_{a \rightarrow \infty} \left(\frac{4a}{TE_0^{\frac{1}{4}}} \right)^{-\frac{4}{5}} = 0. \quad (5.16)$$

This can be interpreted to mean that at the very-low temperature limit, the crossover point from low-field to high-field VRH is located at zero field $E_{crossover} \rightarrow 0$. In other words, the high-field VRH is valid for the whole field range at sufficiently low temperatures.

On the other hand, at the limit of very-high temperatures, the low-field VRH fit would tend to become almost parallel with the x-axis. Thus, setting the slope parameter to tend toward zero,

$$a \rightarrow 0,$$

begets:

$$\lim_{a \rightarrow 0} \left(\frac{4a}{TE_0^{\frac{1}{4}}} \right)^{-\frac{4}{5}} = \infty. \quad (5.17)$$

This can be interpreted to mean that at the very-high temperature limit, the crossover point from low-field to high-field VRH never occurs as $E_{crossover} \rightarrow \infty$. Thus the low-field VRH would be valid for the whole field range at sufficiently high temperatures.

Fig. 5-15. An alternative plot to Fig. 5-13 showing the conductivity until the limit of very high fields $E \rightarrow \infty$, an extrapolation far beyond the range of the experimentally measured data illustrating where our models might no longer apply. The saturation conductivities at this high-field limit, i.e. the zero-intercepts of the y-axis correspond to the values of σ_H in Table 5.2.

Fig. 5-15 presents an extrapolation from the experimental data into very high applied fields. It is interesting to observe from the figure that at the very high field limit, our model predicts a saturation conductivity (i.e. where the fit lines intersect the y-axis, given by σ_H in Table 5.3) that slightly decreases as temperature is increased from 4.2 K until 30 K, and then increases rapidly at temperature of 50 K and slightly decreases from this value as temperature increases to 100 K.

We note from Fig. 5-15 there is an anomalous jump in conductivity as temperature increases to around 50 K. Judging from the trend of the y-axis intercepts, we suggest that at very high fields, the conductivity does indeed crossover to a high-field VRH transport. It is more probable that at the limit of very high fields, the conductivities at temperatures of 50 and 100 K saturate consecutively below that of the saturation conductivities σ_H of that at a temperature of 30 K, as suggested by the trend

of the high-field limit conductivity σ_H in Table 5.3 (corresponding to y-axis intercepts in Fig. 5-15). However these very high field and temperature conditions are beyond the means of experimental measurement.

5.1.3 Quasi-1D highly-doped conducting polymers

We will now show that our crossover scenario, besides giving excellent descriptions for 3D and 2D disordered carbon materials, is also valid for quasi-1D disordered highly-doped conducting polymers. We use as an example, the experimentally measured conductivity data on HCl-doped emeraldine salt form of oriented polyaniline (PAN-ES) by Wang and colleagues [Wang et al. 1992], as shown in Fig. 5-16. In the figure, experimental data is shown as symbols while fits to our crossover scenario are shown in red for intermediate-field VRH, and green for high-field VRH, respectively.

Fig. 5-16. Plot of natural logarithmic conductivity versus the electric field at two temperatures for PAN-ES. Experimental data from [Wang et al. 1992] are shown as symbols. The behaviour of a purely Pollak-Riess regime in the absence of a crossover is indicated by magenta dotted lines, emphasizing the necessity of a crossover from the Pollak-Riess VRH regime (in red) to the Shklovskii VRH regime (in green). The crossover field positions are indicated with red arrows. Published in [Cheah and Kaiser 2014]. Copyright 2014 Inderscience.

It must be noted that in the paper of Wang et al. [1992], the conductivity data is claimed to follow solely the Pollak-Riess VRH, i.e. field-assisted, temperature-driven behaviour. However, this is evidently not the whole story, as the conductivity deviates from this linearity expected from the Pollak-Riess regime as the electric field reaches higher magnitudes, as seen in Fig. 5-16. At such high electric fields, the conductivity is consistent with a crossover to the Shklovskii VRH regime, i.e. field-driven VRH.

Thus, we illustrate that our crossover scenario gives a very good account of the conductivity of quasi-1D highly-doped conducting polymers, highlighting the need to consider the transport regime at high electric fields beyond the Pollak-Riess model interpretation used by Wang et al.

5.2 Investigation into the equivalence of temperature and field scaling parameters

In the theory paper of Shklovskii [1973] a relation between the electric field fitting coefficient E_0 and the Mott coefficient T_0 is suggested to be as follows:

$$\frac{E_0}{T_0} = \frac{ck_B}{er(T)}. \quad (5.18)$$

The dimensionless pre-factor c is suggested to be of “the order of unity” and Shklovskii was cautious to point out that the theory is insufficient to achieve further accuracy than to serve as an order-of-magnitude approximation. To the best of our knowledge, no effort has been made to verify the validity of the above relation as predicted by Shklovskii since the publication of his work.

In this thesis, with the support of experimental data and the fitting parameters in Tables 5.1 and 5.2, we are able to obtain estimates of the values of the dimensionless pre-factor c to determine the validity of the above theoretically predicted relationship. Rearranging Shklovskii’s relation to obtain c , we get:

$$c = \frac{eE_0r(T)}{k_B T_0} \equiv \frac{E_0 a}{0.18 T_0}, \quad (5.19)$$

where

$$a = \frac{0.18r(T)e}{k_B}. \quad (5.20)$$

The value of 0.18 is valid for 2D samples and is replaced by 0.17 for bulk samples [Pollak and Riess 1976], see Chapter 2.1.3. It is however intuitive that the difference between either value is negligible in obtaining the order of magnitude of the dimensionless pre-factor c .

We observe that parameter c is indeed dimensionless as both the numerator and denominator have units $[V/m][K]$ which cancel off each other. This is especially obvious if we rewrite the above relation in the alternative notation using:

$$E_a \equiv \frac{T}{a}$$

to obtain:

$$c = \frac{E_0 T}{0.18 E_a T_0}. \quad (5.21)$$

In order to proceed with the calculations we need to narrow our scope to only consider the conductance data at intermediate temperatures wherein crossovers from temperature-driven to field-driven VRH occur in order that we have both the temperature scaling parameter, i.e. the Mott coefficient T_0 from the former and the field scaling parameter E_0 from the latter regime. In the rGO data, this means we focus on the conductance data at a temperature of 40 K. The results are summarized in Table 5.3.

We see that for rGO, the dimensionless pre-factors c are indeed of the order unity when the majority charge carriers consist of electrons or holes, corresponding to positive and negative applied gate voltages respectively. This means that the energy difference over a mean hopping distance $r(T)$ of an electron in an electric field equal to the field scale parameter E_0 has a similar order of magnitude to the analogous thermal energy $k_B T_0$ where T_0 can be considered the temperature scale parameter, hence proving the validity of the theoretically predicted relation:

$$eE_0r(T) = ck_BT_0. \quad (5.22)$$

Table 5.3. Fitting parameters and the corresponding calculated dimensionless pre-factors c , based on experimental conductance of rGO at a temperature of 40 K. Published in [Cheah and Kaiser 2014]. Copyright 2014 Inderscience.

Gate voltage V_g (V)	T_0 (K)	E_0 $\left(\frac{V}{m}\right)$	a $\left(\frac{K \cdot m}{V}\right)$	c
0	40548	568.6	119.6	9.3
20	57811	380.7	103.4	3.8
-20	91232	205.1	102.4	1.3

However, near the charge neutrality point when the applied gate voltage is zero, the pre-factor c is found to be an order of magnitude larger than expected. We attribute this to the low density of charge carriers in the charge neutrality point existing in the form of sparse electron-hole puddles. The electric field distribution across the sample would subsequently be non-uniform and cause the non-unity relationship between the temperature and field scaling parameters.

From the definition of the pre-factor c (i.e. $c = eE_0r(T)/k_BT_0$), we can understand that an order-unity c means the electrical energy gained scales at the same rate as that of the thermal energy gained. Meanwhile, if c is one order of magnitude larger as obtained near the charge neutrality region, this means that the electrical energy is a larger contributing factor than the thermal energy. This supports our interpretation of the non-uniformity of the electric field distribution across the sample near charge neutrality.

In extending our calculation of the Shklovskii dimensionless pre-factor c to 3D carbon networks, we discover that the order unity prediction does not hold for the data of those samples. We obtain instead two orders of magnitude lower than expected values of c , indicating that for this material, the thermal energy is a larger contributing factor than the electrical energy. Specifically, the values of c are 2.3×10^{-2} at a temperature of 30 K and 4.9×10^{-2} at a temperature of 15 K.

The reason for the calculated result being significantly below the expected theoretical value for the case of the 3D carbon networks remains an open question. We propose that this is due to the electric field being concentrated at certain disordered

regions wherein the electric field in the defected region is roughly two orders-of-magnitude larger than the average field. As hinted at in Chapter 2.1.2 and investigated in depth in the text after Fig. 5-11, the theory of VRH assumes an average, uniform distribution of electric field across the sample and corrections have to be made to parameters obtained from analysis to correct for the non-uniformity of the electric field.

For the quasi-1D highly doped conducting polymers we find that we could not perform a meaningful quantitative analysis as the data of Wang and colleagues [Wang et al. 1992] are presented in a normalized form, wherein the temperature-dependent part is almost frozen out due to this normalization. As such, the temperature scaling parameter T_0 is in effect made zero, or close to zero, by this normalization. As such the electrical energy gain cannot be compared with the gain in thermal energy in a quantitative manner, although our qualitative fits to their data still allows us to demonstrate a good description of the conduction behaviour.

5.3 A proposal for a temperature-assisted, field-driven VRH expression

We again briefly recapitulate the work of Pollak and Riess which introduced a field-assistance exponential term (i.e. the $\exp\left(\frac{aE}{T}\right)$ term) to the temperature-driven VRH expression of Mott, thereby extending the validity of the Mott VRH expression up to intermediate applied voltages:

$$G(T, E) = G_L \exp\left[-\left(\frac{T_0}{T}\right)^p\right] \exp\left(\frac{aE}{T}\right), \quad (5.23)$$

where

$$p = \frac{1}{d+1}.$$

We remind the reader that at higher applied voltages, conduction behaviour switches over to exhibit solely field-driven VRH following Shklovskii as we have demonstrated in the main text.

Analogously, we propose introducing a temperature-assistance exponential term to the field-driven expression of Shklovskii, i.e.:

$$G(T, E) = G_H \exp \left[- \left(\frac{E_0}{E} \right)^p \right], \quad (5.24)$$

as follows:

$$G(T, E) = G_H \exp \left[- \left(\frac{E_0}{E} \right)^p \right] \exp \left(\frac{bT}{E} \right). \quad (5.25)$$

We demonstrate the applicability of our proposed model on the 3D carbon networks electrical conductivity data of Govor and team members. We first digitize and re-graph their data from a natural logarithmic conductivity versus applied field into one of natural logarithmic conductivity versus temperature.

Fig. 5-17 (a) shows with vertical lines of how each conductivity data point is read at specific given values of the applied field, and redrawn into the conductivity versus temperature in part (b). Based on Fig. 5-17 (b), we see that our proposed fitting function in the 3D case seems to work well at a limited temperature ($0 - 70 \text{ K}$) and field ($1000 - 7000 \text{ V/cm}$). This is in line with the validity of the Shklovskii VRH expression for relatively low temperatures and high fields.

Our proposed temperature-assisted, field-driven expression extends the validity of the solely field-driven expression of Shklovskii. Table 5.4 summarizes the fitting parameter values used in the fits. We used an estimate of $E_0 \sim 11 \text{ V/cm}$ by taking the average of its values at temperatures of 15 and 30 K as in [Cheah and Kaiser 2014, Table 2], i.e. 8.4 and 14.3 V/cm respectively.

Fig. 5-17. (a) The blue vertical lines illustrate how data is read from the natural logarithmic conductivity versus applied field graph to be re-drawn into (b) the natural logarithmic conductivity versus temperature graph. Experimental data in bulk carbon networks are taken from [Govor et al. 2000].

Table 5.4. Fitting parameters for our proposed model based on experimental conductance of bulk carbon networks as shown in Fig. 5-19.

Parameters at field $E \text{ (} \times 10^3 \frac{\text{V}}{\text{cm}} \text{)} =$	1	3	7
$[\ln \sigma_H \left(\frac{\text{S}}{\text{cm}} \right)]$	16.12	10.92	8.75
$E_0 \left(\frac{\text{V}}{\text{cm}} \right)$	11		
b	2.55	4.13	5.11

The model fits poorly for temperatures higher than ~ 70 K, and for fields lower than ~ 1000 V/cm, as shown in Fig. 5-18. Note that for the highest field in the dataset, i.e. at a field of 7000 V/cm, the fitting function fits quite well even up to a temperature of 100 K. Dashed lines in the figure show extrapolation where the proposed model is still valid (cf. Fig. 5-17).

Note also that the slope of the fitting line decreases as field increases, indicating a reduction in the average hopping length with the increase of applied electric field. This is analogous to the established VRH theory wherein the mean hopping length decreases as the temperature is increased.

Fig. 5-18. Plot of the natural logarithmic conductivity versus temperature. Experimental data in bulk carbon networks are taken from [Govor et al. 2000] while fits to our proposed model in the text is shown as coloured lines. Dashed lines show extrapolation where the proposed model is still valid, in comparison to Fig. 5-17.

The portion of the data that do not fit well to our proposed model – i.e. at higher temperatures or lower fields where our model is no longer valid – are suggested to fit to temperature-driven VRH following Mott. In Fig. 5-19 we plot our data with x -axis of the inverse one fourth temperature $T^{-\frac{1}{4}}$ to test for the characteristic of 3D Mott VRH,

$$G(T) = G_n \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{4}} \right]. \quad (5.26)$$

We note from Fig 5-19 that most of the data at the low field of 200 V/cm data shows the characteristic of 3D Mott VRH as the graph is linear. We also note that above a temperature of ~ 50 K (as $0.375^{-4} K^{-4} \sim 50$ K), the data from all the higher fields until 7000 V/cm seems to exhibit Mott-like, temperature-driven VRH behaviour. Taking into account our proposed model above ceases to be valid at temperatures above ~ 70 K, as we saw in Fig. 5-18, we propose that a crossover occurs to Mott VRH within the temperature range of 50 – 70 K.

Fig. 5-19. Plot of the natural logarithmic conductivity versus inverse one fourth power of the temperature. Straight lines indicate the characteristic 3D Mott VRH conduction.

CHAPTER 6. Exploratory work

Our crossover model presented so far in Chapter 5 has a main weakness, in that a crossover point has to exist to mediate the transition between the Pollak-Riess VRH and the Shklovskii VRH transport regimes. The physical explanation behind the crossover point which mediates a seemingly sudden transition from a field-assisted, temperature-driven regime to a solely field-driven regime is still an open question. As such, we are motivated to extend our analysis to find a singular, composite function that can fit to the whole range of electric fields, without the need for piecemeal fits divided by the presence of the crossover field point.

However we emphasize that the models we shall show in the following text do not intuitively lend themselves to physical interpretations and are phenomenological models. As such, our VRH crossover model remains the preferred model due to the abundance of physics one can glean from its simplicity.

6.1 A model consisting of the Pollak-Riess term, and its inverse

We derive inspiration from the way Pollak and Riess [1976] introduced the effect of electric field into the Mott VRH expression, i.e. by adding a field term in the numerator of Mott's temperature-driven VRH to obtain field-assisted, temperature-driven VRH. Our proposed composite function, valid across the range of low and high values of the

applied electric field, is thus a “double Pollak-Riess” function, with only 3 fitting parameters G_0 , a and b :

$$G = G_0 \exp\left(\frac{aE}{T}\right) \exp\left(\frac{bE}{T}\right)^{\frac{1}{d+1}}. \quad (6.1)$$

We can rewrite the above expression as:

$$G = G_0 \exp\left(\frac{aE}{T}\right) \exp\left(\frac{T}{bE}\right)^{d+1}, \quad (6.2)$$

to rid off the inverse power.

In writing it this way, we can see that the fitting parameter a functions to provide a negative contribution to conductivity at low temperatures, but becomes increasingly positive as temperature is increased. Fitting parameter b acts in the opposite manner, i.e. starting to become increasingly negative as temperature is increased. As such we expect this model to apply for a wide range of temperatures and applied electric fields, as we shall proceed to demonstrate. Figs. 6-1 and 6-2 show fits of this phenomenological model to the rGO and carbon network data respectively. We see that the fits are satisfactory except at very low values of the applied drain-source voltage and electric field in both figures.

Fig. 6-1. Fits (red curves) of the phenomenological expression consisting of the Pollak-Riess term and its inverse to the experimental conductance data (symbols) of reduced graphene oxide by Gómez-Navarro and colleagues.

Fig. 6-2. Fits (red curves) of the phenomenological expression consisting of the Pollak-Riess term and its inverse to the experimental conductivity data (symbols) of bulk carbon networks by Govor and colleagues.

6.2 A ‘field-dependent fluctuation assisted tunnelling’ model

If we consider the fact that the charge transport mechanism of fluctuation assisted tunnelling (FAT) is influenced by both thermal fluctuations and applied electric field, then it is justifiable to have a FAT model which instead of temperature, is driven by applied field. We expect such a model to apply e.g. at sufficiently low temperatures and sufficiently high applied electric fields, where the applied electric field drives the conduction significantly more than contributions from thermal fluctuations.

We modify Sheng’s FAT equation from a temperature-dependent one [Sheng 1980, Eq. 36(a)]:

$$G(T) = G_0 \exp\left(-\frac{T_b}{T + T_s}\right) \quad (6.3)$$

into a field-dependent one, that is:

$$G(E) = G_0 \exp\left(-\frac{E_b}{E + E_s}\right) \quad (6.4)$$

with $E_b, E_s > 0$ if the applied source-drain bias voltage (or field) is positive. If the source-drain bias voltage (field) is negative, the fitting parameters would in turn have negative values, i.e. $E_b, E_s < 0$.

We proceed to fit to all bias and temperature configurations with this single expression, Fig. 6-3. This is another phenomenological expression presented in passing as an alternative interpretation to our data. We emphasize again that although this model seems to present excellent fits comparable to that of our crossover VRH model in the main text (cf. Fig. 5-10), VRH is the more viable physical phenomenon, as STM analysis of our rGO samples showed disordered regions corresponding to localized charge carriers. On the other hand, fluctuation-assisted tunnelling (FAT) needs the charge carriers to be delocalized and tunnel through potential barriers with the help of thermal fluctuations and energy gained from an applied field. The FAT model would apply to metallic regions separated by grain boundaries; the opposite is the case for our rGO samples.

Fig. 6-3 (continued at next page). Fits (red curves) of the phenomenological expression consisting of our proposed field-dependent FAT model to the experimental conductance data (symbols) of rGO by Gómez-Navarro and team at temperatures of (a) 2; (b) 40; and (c) 220 K.

Fig. 6-3 (continued). Fits (red curves) of the phenomenological expression consisting of our proposed field-dependent FAT model to the experimental conductance data (symbols) of rGO by Gómez-Navarro and team at temperatures of (a) 2; (b) 40; and (c) 220 K.

CHAPTER 7. Results and discussion: electronic transport mechanisms in single-wall carbon nanotube networks

Synthesis methods of carbon nanotubes (CNTs) cannot yet ensure that each individual nanotube is of the same length and diameter or contains the same level of defects and byproducts. Hence, existing applications based on CNTs rely on the properties of CNT ensembles – so-called *networks* [e.g. Grobert 2007] or ultrathin films [e.g. Cao and Rogers 2009] of nanotubes – rather than the properties of each individual nanotubes.

Electronic transport data can serve as the main indicator for the quality of the CNT networks as these data can be correlated with their morphology [e.g. Andrade et al. 2007]. It is thus of interest to investigate in a systematic manner the electronic conduction mechanisms [e.g. Skákalová et al. 2006; Biercuk et al. 2008]. Electronic conduction in carbon-based materials, namely conducting polymers, CNTs and graphene has been reviewed in [Kaiser and Skákalová 2011].

We present in this chapter a detailed systematic analysis on the electronic transport of single-wall carbon nanotube (SWNT) networks grown by various different preparation methods. We motivate this work by emphasizing that the electrical transport data on SWNT networks grown via the chemical vapour deposition (CVD) method presented in this chapter are unpublished.

Various electronic transport mechanisms have been reported in the literature for SWNT networks. Some SWNT networks have been reported to exhibit variable-range hopping (VRH) [Ravi et al. 2010]; other networks exhibit a parallel combination of VRH and an activated (i.e. semiconductor) component at high temperatures [Ravi et al. 2013]. Meanwhile, some other SWNT networks exhibit a parallel combination of fluctuation assisted tunnelling (FAT) and quasi-1D metallic conduction at high applied electric fields [Seliuta et al. 2013].

Another possible transport mechanism for SWNT is the Luttinger liquid behaviour. The Luttinger liquid model approximates the nanotubes as ideal systems of interacting charge carriers in 1D. Such a Luttinger liquid in 1D would exhibit a conductance dependent on a power law of temperature following the expression $G(T) \propto T^n$ with the value of the power index n depending on fabrication details [Biercuk et al. 2008, pp. 474, 475].

Our work focuses on the electronic transport of SWNT, but it worth mentioning in passing reported transport mechanisms in multi-wall CNT (MWNT). In an *individual* MWNT, [Khan et al. 2008] reported experimental conductance following the Mott VRH model, with a crossover of dimensionality from 3D to 2D as the temperature is decreased. Other MWNT *networks* exhibit conductance behaviour following a parallel combination of VRH and FAT models [Kamalakannan et al. 2011].

7.1 Overview of the electrical data of the nanotube networks

We shall now proceed to discuss our experimentally measured conductance data in CVD-grown SWNT. For ease of discussion, we first present an overview of all SWNT networks under study, the type of data available for our analysis for each network, and the main findings in terms of the electrical transport mechanism of each network obtained from our analysis. We analyze here a total of 14 CVD-grown SWNT networks. Eight networks are prepared by Ansaldo and colleagues [Ansaldo et al. 2009; 2007]

while five networks prepared by Lima and colleagues [Lima et al. 2007]. Data for one post-grown SWNT network by Andrade and colleagues [Andrade et al. 2007] is added in our analysis for comparison. The synthesis methodology of these SWNT networks has been presented in Chapter 3.4.

Table 7.1 presents the codenames assigned to each SWNT network and their corresponding temperature-dependent and field-dependent electronic transport behaviour identified from our analysis and modelling of the experimentally measured conductance data. The codename is assigned to each network by our experimental colleagues and we retain these codenames to facilitate discussion throughout our analysis.

Fig. 7-1 summarizes the type of data available to us for analysis. Note that due to the nature of us combining data from several experimental groups, the amount of data furnished to us for analysis differ between samples. All SWNT networks are measured for temperature-dependent data but only selected networks undergo additional measurements for electric-field-dependent data.

Table 7.1. Codenames of each SWNT network prepared by (a) Ansaldo et al. or (b) by Lima et al. and Andrade et al., alongside their corresponding temperature- and field-dependent electronic transport mechanism resulting from our analysis.

(a)

SWNT networks prepared by Ansaldo et al.	Temperature-dependent electronic transport	Field-dependent electronic transport
One #Q-Co12-06	FAT (Sheng)	Field-driven FAT (Kaiser-Park)
Two #D-Co13-31	FAT (Sheng)	---- (no data)
Three #D-Co13-21	1D VRH (Mott) or Efros-Shklovskii (E-S) VRH	1D field-assisted temperature driven VRH (Pollak-Riess)
Four #D-Co13-11	1D VRH (Mott)	---- (no data)
Five #Q-Co13-22	1D VRH (Mott)	1D field-assisted temperature driven VRH (Pollak-Riess)
Six #Q-Co13-14	2D VRH (Mott) at lower drain current; Possibly 1D VRH (Mott) at higher drain current	2D VRH (Mott) Due to very low applied voltage (i.e. up to only ~0.01V), there is no field-assisted term observable

Seven #Q3	2D VRH (Mott)	2D field-assisted temperature driven VRH (Pollak-Riess)
Eight #Q4	FAT (Sheng)	Field-driven FAT (Kaiser-Park)

(b)

SWNT networks prepared by Lima et al. or Andrade et al.	Temperature-dependent electronic transport	Field-dependent electronic transport
One #8	1D VRH (Mott)	---- (no data)
Two #933-1	Interrupted metallic i.e. FAT + phonon backscattering	Field-driven FAT (Kaiser-Park) [†]
Three #933-2		---- (no data)
Four #936	FAT (Sheng)	Field-driven FAT (Kaiser-Park)
Five #940	3D VRH (Mott)	---- (no data)
Six #Andrade	2D VRH (Mott)	---- (no data)

[†]Additional note for network Two #933-1: We observe that a phonon backscattering contribution becomes significant in addition to FAT above a temperature of ~ 180 K in the temperature-dependent data. On the other hand, this phonon backscattering mechanism does not manifest in the field-dependent data as the field-dependent measurements were performed at temperatures of 4 and 12 K. In a strict sense, pure ‘backscattering’ happens only in 1D. For higher dimensions, it is more accurate to use the general term ‘scattering’, to include scattering e.g. into or out of plane of observation.

Fig. 7-1. SWNT networks grouped by their electronic transport mechanisms of either variable-range hopping (VRH) according to system dimensionality 1D (which is indistinguishable from Efros-Shklovskii (E-S) Coulombic-interaction dominated VRH), 2D or 3D; or fluctuation assisted tunnelling (FAT) as identified by our analysis on data measured by Ansaldo et al., Lima et al. and Andrade et al. A +E sign beside the network codename indicates that electric-field-dependent data are available in addition to temperature-dependent data.

In terms of experimental synthesis procedures, all eight SWNT networks prepared by Ansaldo et al. are grown by CVD from spin-coated catalyst. Meanwhile, two out of six SWNT networks prepared by Lima et al. (i.e. #933-1 and #933-2) are grown by CVD from patterned catalyst. Unfortunately, the preparation methods of the other four Lima networks are not identified to us and we could not deduce such information from published reports.

As such the latter samples may be excluded from further analysis. One SWNT network (i.e. #Andrade) is also analyzed in this study despite not being grown by CVD but fabricated via post-growth deposition via spin-coating. We note that Lima Five has a similar electrical conductance trend as the post-grown network and is possibly prepared in the same manner.

7.2 Electronic transport mechanisms of the nanotube networks

We shall first recap the transport theoretical models that we shall be using in this section. The temperature-driven VRH of Mott (as defined in Chapter 2.1.2) follows the conductivity behaviour,

$$\sigma(T) = \sigma_0 \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{d+1}} \right]. \quad (7.1)$$

With an applied electric field, the conductivity would follow the field-assisted, temperature-driven VRH model following the work of Pollak and Riess (as defined in Chapter 2.1.3) is,

$$\sigma(T, E) = \sigma_0 \exp \left[- \left(\frac{T_0}{T} \right)^{\frac{1}{d+1}} \right] \exp \left(\frac{aE}{T} \right). \quad (7.2)$$

We have demonstrated extensively in the previous chapter than in cases where the applied electric field is sufficiently high or the temperature sufficiently low, a crossover

occurs from the above regime to a purely field-driven VRH model following the work of Shklovskii (as defined in Chapter 2.1.4):

$$\sigma(E) = \sigma_0 \exp \left[- \left(\frac{E_0}{E} \right)^{\frac{1}{d+1}} \right]. \quad (7.3)$$

Meanwhile, for metallic electronic states separated by thin potential barriers, temperature-dependent conductivity follows the work of Sheng (as defined in Chapter 2.2.1):

$$\sigma^{-1}(T) = \sigma_0^{-1} \exp \left(\frac{T_b}{T + T_s} \right). \quad (7.4)$$

For thick SWNT networks, a significant resistance contribution comes from phonon scattering (see Chapter 2.2.1) which is reflected by an additional interrupted metallic term as follows:

$$\sigma^{-1}(T) = A \exp \left(-\frac{T_m}{T} \right) + B \exp \left(\frac{T_b}{T_s + T} \right); \quad T_m = 1830 \text{ K}. \quad (7.5)$$

With an applied electric field, a field-driven conductivity would result following the work of Kaiser and Park (see Chapter 2.2.2):

$$G = \frac{I}{V} = \frac{G_0 \exp \left(\frac{V}{V_0} \right)}{1 + h \left[\exp \left(\frac{V}{V_0} \right) - 1 \right]}. \quad (7.6)$$

To ascertain the conduction dimensionality in each network, we first ascertain whether the conduction mechanism is one of FAT (i.e. following the behaviour of Sheng, or Kaiser-Park model) or VRH (i.e. following Mott, Shklovskii or our proposed crossover model) by observing if the conductance limit as temperature tends to absolute zero is non-zero (FAT) or zero (VRH), as illustrated in Fig. 2-3. For VRH samples, we perform fitting to a non-preset power index (i.e. without user bias) that is decided by least square fitting procedure described in Chapter 4.2. We illustrate this representatively for the Mott VRH expression, wherein we use $p \equiv \frac{1}{d+1}$ to decide the conduction dimensionality, by fitting to this expression:

$$\sigma(T) = \sigma_0 \exp \left[- \left(\frac{T_0}{T} \right)^p \right], \quad (7.7)$$

and allowing the index p to freely vary in deciding the best fit to the experimental data. We then decide based on the best fit scenario, the dimensionality d of the sample. For example if the power index shows best fit with the value of $p \sim \frac{1}{4}$, then we perform a second more conclusive fitting using the index $p = \frac{1}{4}$ for 3D VRH conduction, i.e. $d = 3$. We note that for all the data analyzed in this chapter there is no ambiguous case wherein the dimensionality of the sample for instance lies between two integers of d .

This methodology gives the advantage of removing any preconceptions or bias we may have based on our knowledge of for instance the morphology and synthesis procedures of the SWNT network. The same fitting procedure is applied for all other VRH-conducting samples in this chapter.

7.2.1 Direct grown carbon nanotube networks via spray-coated catalysts prepared by Ansaldo et al.

We can now discuss the electronic transport mechanisms of the SWNT networks, starting with the Ansaldo samples. As seen in Table 7.1, the SWNT networks prepared by Ansaldo et al. exhibit several different electronic conduction mechanisms, namely VRH in 1D and 2D, and FAT. We note that 1D VRH can be alternatively interpreted in terms of the Efros-Shklovskii Coulombic-interaction dominated VRH model, as both models are indistinguishable by their analytical expressions, i.e. $\sigma \propto \exp T^{-\frac{1}{2}}$.

We focus on networks exhibiting 1D VRH behaviour. Three samples show this conduction mechanism in the temperature-dependent regime, Fig.7-2 (a)-(c). Notice that conductance tends to zero as the temperature tends to absolute zero; this is characteristic of the VRH model as the localized electronic states would freeze out at absolute zero. In terms of the electric field-dependent regime, we find that SWNT networks D-Co13-21

and Q-Co13-22 exhibit temperature-assisted, field-driven (Pollak-Riess) 1D VRH. Data for D-Co13-21 is representatively shown in Fig. 7-2(d).

Fig. 7-2 (continued at next page). (a)-(c) Three SWNT networks exhibiting 1D VRH model in the temperature-dependent regime, as shown by conductance versus temperature plots. Our fits are in red while the experimental data by Ansaldo et al. is shown in green. Notice that conductance tends to zero as the temperature tends to absolute zero; this is characteristic of the VRH model. (d) In the field-dependent regime, SWNT networks exhibiting 1D VRH model in the temperature-dependent regime is expected to follow the field-assisted behaviour of Pollak and Riess 1D VRH. Data for a representative network is shown here as conductance G versus source-drain voltage $V_{sd} = -V_{ds}$. Our fits are in red while the experimental data by Ansaldo et al. is shown as symbols. In (e) we show an alternate representation of the field-dependent regime (cf. part (d)) using the data of another SWNT showing 1D VRH plotted as current versus voltage instead of conductance over voltage.

Fig. 7-2 (continued). (a)-(c) Three SWNT networks exhibiting 1D VRH model in the temperature-dependent regime, as shown by conductance versus temperature plots. Our fits are in red while the experimental data by Ansaldo et al. is shown in green. Notice that conductance tends to zero as the temperature tends to absolute zero; this is characteristic of the VRH model. (d) In the field-dependent regime, SWNT networks exhibiting 1D VRH model in the temperature-dependent regime is expected to follow the field-assisted behaviour of Pollak and Riess 1D VRH. Data for a representative network is shown here as conductance G versus source-drain voltage $V_{sd} = -V_{ds}$. Our fits are in red while the experimental data by Ansaldo et al. is shown as symbols. In (e) we show an alternate representation of the field-dependent regime (cf. part (d)) using the data of another SWNT showing 1D VRH plotted as current versus voltage instead of conductance over voltage.

Fig. 7-2 (continued). (a)-(c) Three SWNT networks exhibiting 1D VRH conduction in the temperature-dependent regime, as shown by conductance versus temperature plots.

Our fits are in red while the experimental data by Ansaldo et al. is shown in green. Notice that conductance tends to zero as the temperature tends to absolute zero; this is characteristic of the VRH model. (d) In the field-dependent regime, SWNT networks exhibiting 1D VRH conduction in the temperature-dependent regime is expected to follow the field-assisted behaviour of Pollak and Riess 1D VRH. Data for a representative network is shown here as conductance G versus source-drain voltage $V_{sd} = -V_{ds}$. Our fits are in red while the experimental data by Ansaldo et al. is shown as symbols. In (e) we show an alternate representation of the field-dependent regime (cf. part (d)) using the data of another SWNT showing 1D VRH plotted as current versus voltage instead of conductance over voltage.

Table 7.2. Fitting parameters for the three SWNT networks exhibiting 1D VRH model in the temperature-dependent regime of Fig. 7-2 (a)-(e).

SWNT network	σ_0 (μS)	$T_0^{\frac{1}{2}} \left(K^{\frac{1}{2}} \right)$
#D-Co13-21; Fig. 7-2 (a), (d)	1.2×10^{-4}	26.6
#D-Co13-11; Fig. 7-2 (b)	7.6×10^{-5}	32.1
#Q-Co13-22; Fig. 7-2 (c), (e)	2.5×10^{-4}	9.6

It is interesting to see that while Fig. 7-2 (a)-(c) can be described by the same conduction mechanism, i.e. 1D VRH, their curve shapes differ slightly. Some insight can be gained by analyzing the fitting parameter values, as detailed in Table 7.2 above. We observe that the curves of (a) and (b) that exhibit quite a similar trend have quite

comparable values of σ_0 and T_0 , while for curve (c) the conductance at the absolute zero limit σ_0 is significantly higher than the others, and its Mott coefficient value T_0 which serves as the damping exponential term (i.e. $\exp\left[-\left(\frac{T_0}{T}\right)^{\frac{1}{2}}\right]$) is notably lower than the other two.

Two other SWNT networks exhibit 2D Mott VRH behaviour in the temperature-dependent regime, as presented in Fig. 7-3 (a). The outlier data near room temperature, 300 K, in part (b) is attributed to experimental error and is ignored in our modelling. Network #Q3 has electric field-dependent data, shown in Fig. 7-3 (c), which is most notable because it fits to our crossover model from 2D temperature-assisted, field-driven (Pollak-Riess) VRH to 2D field-driven (Shklovskii) VRH. In this case we find further evidence for our proposed VRH crossover model detailed in the previous chapter for disordered graphene and other carbon materials, now also shown to apply for SWNT data.

Fig. 7-3 (continued at next page). (a) and (b) Two SWNT networks exhibiting 2D Mott VRH behaviour in the temperature-dependent regime. Fits are in red to experimental data of Ansaldo et al. in green. (c) In the field-dependent regime, a selected network shows further evidence for our crossover model detailed in Chapter 5 for disordered carbon materials. Fits to our model are in red for 2D Pollak-Riess VRH and green for Shklovskii VRH regimes, with crossover points indicated by red arrows. Experimental data of Ansaldo et al. are shown as symbols. (d) Additional data for #Q-Co13-14 (cf. part (a)) measured at higher drain bias shows borderline 2D or 1D VRH behaviour.

Fig. 7-3 (continued at next page). (a) and (b) Two SWNT networks exhibiting 2D Mott VRH behaviour in the temperature-dependent regime. Fits are in red to experimental data of Ansaldo et al. in green. (c) In the field-dependent regime, a selected network shows further evidence for our crossover model detailed in Chapter 5 for disordered carbon materials. Fits to our model are in red for 2D Pollak-Riess VRH and green for Shklovskii VRH regimes, with crossover points indicated by red arrows. Experimental data of Ansaldo et al. are shown as symbols. (d) Additional data for #Q-Co13-14 (cf. part (a)) measured at higher drain bias shows borderline 2D or 1D VRH behaviour.

Fig. 7-3 (continued). (a) and (b) Two SWNT networks exhibiting 2D Mott VRH behaviour in the temperature-dependent regime. Fits are in red to experimental data of Ansaldo et al. in green. (c) In the field-dependent regime, a selected network shows further evidence for our crossover model detailed in Chapter 5 for disordered carbon materials. Fits to our model are in red for 2D Pollak-Riess VRH and green for Shklovskii VRH regimes, with crossover points indicated by red arrows. Experimental data of Ansaldo et al. are shown as symbols. (d) Additional data for #Q-Co13-14 (cf. part (a)) measured at higher drain bias shows borderline 2D or 1D VRH behaviour.

Table 7.3. Fitting parameters for the two SWNT networks exhibiting 2D VRH model in the temperature-dependent regime of Fig. 7-3 (a)-(d).

SWNT network	σ_0 (μS)	$T_0^{\frac{1}{3}} \left(K^{\frac{1}{3}} \right)$
#Q-Co13-14; 0.1 μA ; Fig. 7-3 (a)	3.7×10^{-4}	12.7
#Q-Co13-14; 1 μA ; Fig. 7-3 (d)	1.4×10^{-4}	17.2
#Q3; Fig. 7-3 (b), (c)	8.1×10^{-4}	17.0

To complement Fig. 7-3(a), we present data for the same network #Q-Co13-14 but at a higher applied drain current of 1 μA , Fig. 7-3(d), rather than 0.1 μA in part (a). We see in this case that at this higher drain bias, the conduction becomes 2D VRH possibly approaching 1D VRH. We are hampered by the lack of low-temperature data to achieve a conclusive interpretation of the conduction mechanism. We emphasize however that for temperature-dependent regime interpretations, the data at the lower drain bias gives the best analysis so as to minimize the contribution of the applied

voltage. As such the identification of the network #Q-Co13-14 as exhibiting 2D VRH at the lower drain bias remains valid.

So far we have presented SWNT networks following VRH behaviour in 1D and 2D. There are other SWNT networks, three in total, instead exhibiting FAT behaviour; these are presented in Fig. 7-4 (a)-(c) in the temperature-dependent measurement regime. Networks #Q-Co12-06 and #Q4 have electric field-dependent data which fit to field-driven (Kaiser-Park) FAT. Representative data for Q4 is shown in Fig. 7-4 (d). Fitting parameter values of graphs in Fig. 7-4 are listed in Table 7.6 (a).

Fig. 7-4 (continued at next page). (a)-(c) Three SWNT networks of Ansaldo et al. exhibit FAT behaviour, following the temperature-driven model of Sheng. Note the significantly higher conductance for (b) in $m\text{S}$ compared to μS for the other two networks. The data points coloured in blue near room temperature are eliminated from analysis due to anomalous scattering. (d) In the field-dependent measurement regime, the data fit very well to the field-driven Kaiser-Park FAT model as expected.

Fig. 7-4 (continued at next page). (a)-(c) Three SWNT networks of Ansaldo et al. exhibit FAT behaviour, following the temperature-driven model of Sheng. Note the significantly higher conductance for (b) in mS compared to μS for the other two networks. The data points coloured in blue near room temperature are eliminated from analysis due to anomalous scattering. (d) In the field-dependent measurement regime, the data fit very well to the field-driven Kaiser-Park FAT model as expected.

Fig. 7-4 (continued). (a)-(c) Three SWNT networks of Ansaldo et al. exhibit FAT behaviour, following the temperature-driven model of Sheng. Note the significantly higher conductance for (b) in mS compared to μS for the other two networks. The data points coloured in blue near room temperature are eliminated from analysis due to anomalous scattering. (d) In the field-dependent measurement regime, the data fit very well to the field-driven Kaiser-Park FAT model as expected.

7.2.1.1 Correlation between electronic transport and morphology

We now investigate the morphology of the SWNT networks of Ansaldo et al. to see if any correlation can be made between the morphology and electronic transport mechanism. Representative scanning electron microscopy (SEM) images of several SWNT networks grouped according to their electronic transport mechanism are shown in Fig. 7-5.

We observe that for the networks showing VRH conduction, Fig. 7-5(a)-(c), the networks appear to consist of relatively sparse arrangements of tubes wherein the individual tubes are visible. On the other hand, for the network showing FAT conduction, Fig. 7-5(d), the network appears to be so densely matted that it appears to be more accurately described as an ultrathin film consisting of carbon nanotubes.

(a) #D-Co13-21

(b) #D-Co13-11

Fig. 7-5 (continued at next page). Representative scanning electron microscopy (SEM) images by Ansaldo, Skákalová et al. show the surface morphology of SWNT networks exhibiting (a)-(c) variable-range hopping (VRH) and (d) fluctuation assisted tunnelling (FAT) behaviour in their electronic conduction. Scale bars at bottom-left indicate $1\text{ }\mu\text{m}$ at $5000\times$ magnification.

(c) #Q-Co13-22

(d) #Co13-31

Fig. 7-5 (continued). Representative scanning electron microscopy (SEM) images by Ansaldo, Skákalová et al. show the surface morphology of SWNT networks exhibiting (a)-(c) variable-range hopping (VRH) and (d) fluctuation assisted tunnelling (FAT) behaviour in their electronic conduction. Scale bars at bottom-left indicate 1 μm at 5000 $\times$ magnification.

It has been suggested by Skákalová and colleagues that thin SWNT networks show VRH while thick SWNT networks show FAT [Skákalová et al. 2006]. By comparing the SEM images in Fig. 7-5, we extend the observation of Skákalová and colleagues by further proposing that networks consisting of moderately dense tubes, (a)-(c), show VRH while very densely arranged tubes, as in (d), would show FAT.

We can understand this by considering that the very densely populated networks are able to retain a significant fraction of their metallic conductance down to very low temperatures, consistent with FAT theory. On the other hand, for less densely populated networks, the conductance would tend to be very small as the temperature tends to zero, consistent with VRH theory.

7.2.2 Direct grown carbon nanotube networks via patterned catalysts prepared by Lima et al.

We now discuss the electronic transport mechanisms of the Lima networks. SWNT network #933-1 and #933-2 are most probably the same sample but measured at different drain currents; the network shows FAT conduction with additional significant contribution to resistance coming from zone boundary phonon scattering, Figs. 7-6(a) and (b). Fitting parameter values are listed in Table 7.6 (b). The fits in the figures show the significant phonon scattering contribution to resistance at the temperature approaches room temperature. Electric field-dependent data measured at temperatures of 4 and 12 K for this network shows its conduction behaviour to be consistent with field-driven (Kaiser-Park) FAT, Fig. 7-6(c).

It is interesting that the data of the FAT-conducting network can be alternatively interpreted using the VRH mechanism, as we show the focus on the positive-bias data of Fig. 7-6(c) and present it in the form of Fig. 7-6(d). The conduction can be well explained by the solely field-driven Shklovskii VRH conduction (green curves) with a hint of an onset of a crossover into the field-assistance regime of Pollak-Riess VRH (red curves) as indicated by the red arrow.

How do we reconcile the delocalized electronic states consistent with FAT conduction in the temperature-dependent regime with the localized electronic states consistent with VRH in the electric field-dependent regime? We observe that the temperature-dependent data is measured for a wide range of temperatures from near absolute zero to near room temperature, as in Fig. 7-6(a). However, the field-dependent data is measured at low temperatures of 4 and 12 K, as in Fig. 7-6(c) and (d). Hence it makes sense that at low temperatures the electronic states are localized which become

delocalized as the thermal energy of the system is increased and thus rid off a majority of the potential barriers as temperature is increased. We thus show that it is possible for both VRH and FAT interpretations to co-exist and be valid for the same sample under different conditions.

Fig. 7-6 (continued at next page). (a) and (b) Temperature regime SWNT data prepared by Lima et al. show conduction consistent with fluctuation assisted tunnelling coupled with a significant resistance from phonon scattering near room temperature as illustrated by dotted lines. Experimental data of Lima et al. is shown in green while our fits are in red. (c) Field regime data is consistent with Kaiser-Park field-driven FAT conduction.

The effect of phonon scattering is not visible in these low-temperature data. Experimental data of Lima et al. is shown as symbols while our fits are in red. (d) An alternative interpretation of (c) in terms of the VRH model, see text.

Fig. 7-6 (continued). (a) and (b) Temperature regime SWNT data prepared by Lima et al. show conduction consistent with fluctuation assisted tunnelling coupled with a significant resistance from phonon scattering near room temperature as illustrated by dotted lines. Experimental data of Lima et al. is shown in green while our fits are in red. (c) Field regime data is consistent with Kaiser-Park field-driven FAT conduction. The effect of phonon scattering is not visible in these low-temperature data. Experimental data of Lima et al. is shown as symbols while our fits are in red. (d) An alternative interpretation of (c) in terms of the VRH model, see text.

7.2.3 Post-grown carbon nanotube networks prepared by Andrade et al.

The post-growth deposited SWNT network prepared by Andrade exhibits conduction behaviour consistent with 2D VRH, as shown in Fig. 7-7. A Lima network #940 is also shown in the figure as it is observed to have a similar temperature-dependent conductance trend but reaching a higher conductance at room temperature; it exhibits 3D VRH behaviour. Investigations are ongoing to determine the synthesis method of network #940. Due to the limited data, and restricted to temperature-dependent data due to the lack of field-dependent data, not much meaningful comparison can be made with the direct-growth group of SWNT networks.

Fig. 7-7 (continued at next page). (a) Post-grown SWNT network by Andrade et al. can be very well explained by a 2D VRH model. Meanwhile, in (b), one of the Lima SWNT network, #940, shows a similar conductance trend to (a) and is included in this group for comparison.

Fig. 7-7 (continued). (a) Post-grown SWNT network by Andrade et al. can be very well explained by a 2D VRH model. Meanwhile, in (b), one of the Lima SWNT network, #940, shows a similar conductance trend to (a) and is included in this group for comparison.

Table 7.4. Fitting parameters for the two SWNT networks exhibiting respectively 2D and 3D VRH models in the temperature-dependent regime of Fig. 7-7 (a) and (b).

SWNT network	σ_0 (μS)	T_0 (K)
Spray coated; Fig. 7-7 (a); 2D VRH	1.6×10^{-3}	1707
#940; Fig. 7-7 (b); 3D VRH	1.7×10^{-3}	1905

7.3 Further analysis

7.3.1 Mean hopping distances in VRH networks

From the fitting parameter:

$$a = \frac{0.18r(T)e}{k_B} \quad (7.8)$$

in the field-assisted temperature-driven VRH model of Pollak and Riess, we can calculate the mean hopping distance $r(T)$ in the SWNT networks at given temperatures

T . We multiply the hopping distance with the distance between the probe electrodes during electrical testing of $300\ \mu m$; this converts the electric field to its corresponding voltage, because our fits are performed over voltage on the x -axis rather than the field. These mean hopping lengths are summarized in Table 7.5.

Table 7.5. Calculated mean hopping lengths in VRH-conducting SWNT networks of Ansaldo et al.

SWNT networks by Ansaldo et al. showing VRH	Mean hopping lengths, $r(T)(nm)$ at given temperatures T (K)
#D-Co13-21	8 K: 73 nm 137 K: 735 nm
#Q-Co13-22	6 K: 491 nm
#Q3	7 K: 824 nm 48 K: 458 nm 94 K: 139 nm

From the SEM images of Fig. 7-5, we observe that the lengths of the nanotubes are of the order of $1 - 10\ \mu m$. From Table 7.5, we note that the typical mean hopping length is of the order of $10^{-7}\ m$, which agrees in order of magnitude to the typical nanotube length from morphology images.

We see for the network #Q3, that the average hopping distance decreases as the temperature increases. This is consistent with the VRH theory, as more nearby energy states become available with the increase in thermal energy thus reducing the need for longer-distance tunnelling. However, for the network #D-Co13-21, we observe that the trend seems to be the opposite of what is expected, although we have only data at two temperatures.

The average hopping distance in the case of #D-Co13-21 seems to be larger at the higher temperature and this is not consistent with the expectation of the VRH theory. This deviation from theory we suggest can be attributed to the effect of electron-electron Coulombic interaction becoming more dominant at increased temperature for this network, thus the electron-electron repulsion negates the existence of more available nearby energy states.

We also note here that we use a coefficient value of 0.18 which is actually for surface or 2D transport despite this network showing 1D conduction, because no value exists in the theory of Pollak and Riess for 1D transport; but only for surface and bulk. The use of a 2D coefficient for a 1D transport material might contribute to this deviation of the trend of the mean hopping distance from theoretical expectations. The correct coefficient for 1D transport is an interesting open question.

7.3.2 Barrier heights in FAT networks

From the Sheng model of temperature-driven FAT, we are able to estimate the barrier heights and the extent of quantum tunnelling occurring in SWNT networks exhibiting this conduction mechanism, Table 7.6.

Table 7.6. Calculated barrier energy and quantum tunnelling indicators in FAT-conducting SWNT networks of (a) Ansaldo et al. and (b) Lima et al.

(a)			
SWNT networks by Ansaldo et al. showing FAT	Sheng parameter, T_s (K)	Barrier energy indicator, T_b (K)	Quantum tunnelling indicator, T_s/T_b
#Q-Co12-06; Fig. 7-4 (a)	81	291	0.3
#D-Co13-31; Fig. 7-4 (b)	48	25	1.9
#Q4; Fig. 7-4 (c)	1515	20985	0.07

(b)			
SWNT networks by Lima et al. showing FAT	Sheng parameter, T_s (K)	Barrier energy indicator, T_b (K)	Quantum tunnelling indicator, T_s/T_b
#933-1; 10 μA ; Fig. 7-6 (a)	13	16	0.8
#933-2; 1 μA ; Fig. 7-6 (b)	50	39	1.3

The order of magnitude of potential barrier energy is indicated by the value of the fitting parameter T_b , while the extent of quantum tunnelling in the low-temperature limit is indicated by the dimensionless ratio T_s/T_b , where fitting parameter T_s is called the Sheng parameter. We note that the values of these indicators vary widely across

samples and are suggested to be dependent on the sample morphology. It could also be dependent on the applied bias voltage to the drain during electrical testing. As an applied voltage is increased, the perceived barrier height would be expected to decrease correspondingly.

It is interesting to observe the correlations (or lack thereof) of the shapes of the graphs of Figs. 7-4 (a)-(c) to Table 7.6 (a). We observe that Figs. 7-4 (a) and (b), corresponding to samples #Q-Co12-06 and D-Co13-31 respectively, have a similar trend while Fig. 7-4 (c), i.e. sample #Q4, is distinctly different in the way conductance increases with temperature. Looking at the quantum tunnelling ratio T_s/T_b , there does not seem to be a correlation for why the graph of Fig. 7-4 (c) differs so much from (a) and (b).

However the parameters T_s and T_b analyzed individually could hold the answer. We notice that the sample of Fig. 7.4 (c), #Q4, has both parameter values significantly orders of magnitude higher than the other two samples. What this could mean as we look at Sheng's FAT expression $\sigma^{-1}(T) = \sigma_0^{-1} \exp\left(\frac{T_b}{T+T_s}\right)$ is that for this former sample #Q4, as the values of constants T_s and T_b become significantly larger than the temperature T , the contribution of the temperature is made less significant in driving the electronic conduction.

In contrast, the other two samples have their values of T_s and T_b less than or comparable to room temperature. In this manner, the conduction mechanism is driven by a relatively balanced combined contributions of system temperature T , the Sheng parameter T_s and the barrier parameter T_b .

CHAPTER 8. Conclusions

The main novelty of this thesis is our model consisting of a crossover between two regimes of variable-range hopping (VRH) transport, namely one that is temperature-dependent to another that is field-dependent, with the transition effected by a crossover field described by our analytical expression. We have shown that our model is able to describe very well the experimentally measured electrical conductance data of partially disordered graphene, single-wall carbon nanotube (SWNT) networks and other carbon materials.

8.1 Crossover from temperature-dependent to field-dependent variable-range hopping conduction in partially disordered graphene

We have presented an analysis of low-temperature measurements of experimentally measured electrical conductance of reduced graphene oxide (rGO), finding that the data follow a VRH crossover model in 2D. The VRH crossover model incorporates two regimes of VRH, namely one that is field-assisted and temperature-driven, the so-called Pollak-Riess VRH, and another that is field-driven, the so-called Shklovskii VRH.

At room temperature T , electrical conductance G occurs via 2D Pollak-Riess VRH, $\ln G \propto T^{-\frac{1}{3}}$, which is dominated by the disordered regions in the material. The general form of the Pollak-Riess VRH model is:

$$G(T, E) = G_1 \exp \left[- \left(\frac{T_0}{T} \right)^p \right] \exp \left(\frac{E}{E_a} \right) \quad (8.1)$$

where the field scale factor,

$$E_a = \frac{k_B T}{0.18 r(T) e} \quad , \quad (8.2)$$

the Mott coefficient,

$$T_0 = \frac{13.8}{k_B N(\epsilon_F) L^2} \quad , \quad (8.3)$$

and $p = (d + 1)^{-1}$ with d the spatial dimensionality of the sample.

However, at lower temperatures, we find a smooth crossover to follow the 2D Shklovskii VRH conductance behaviour, $\ln G \propto E^{-\frac{1}{3}}$, when the applied electric field E exceeds a specific crossover value E_C . The general form of the Shklovskii VRH model is:

$$G(E) = G_2 \exp \left[- \left(\frac{E_0}{E} \right)^p \right], \quad (8.4)$$

where E_0 is the field scale factor in this regime.

8.1.1 Analytical expression for the crossover field

We find in our rGO samples that the crossover between the VRH regimes occurs at specific values of the crossover field E_C that can be described by an analytical expression. We obtained this expression by equating the slopes of the curves where both of the VRH regimes meet. This matching of slope corresponds to the smooth transitions observed between the two VRH regimes at the crossover field E_C :

$$E_C(T)_{2D} = \left(\frac{E_a E_0^{\frac{1}{3}}}{3} \right)^{\frac{3}{4}}. \quad (8.5)$$

We are thus able to calculate that the crossover voltage for our rGO sample at a temperature of 40 K and at zero applied gate voltage (i.e. charge neutrality point) to be 0.84 V. The conversion of gate voltage to electric field can be done knowing the distance between test electrodes of $1.1 \mu m$.

Generalized to arbitrary spatial dimensionality of the sample d , the expression for the crossover field E_C can be written [Cheah et al. 2013; Cheah and Kaiser 2014]:

$$E_C(T)_d = (pE_a E_0^p)^{(p+1)^{-1}}. \quad (8.6)$$

This expression consists of the field scale factors E_a for field-assisted, temperature-driven hopping and E_0 for purely field-driven hopping, in this manner unifying the theory of both distinct regimes of VRH. Our result highlights the need for further theoretical studies of this transition regime where the contributions of both the thermally-driven and field-driven hopping are simultaneously significant.

8.1.2 No evidence of Coulombic electron-electron interactions

We found no evidence for an effect of Coulomb interactions in our data, which would exhibit an electrical conduction mechanism following the Efros-Shklovskii model, $\ln G \propto T^{-\frac{1}{2}}$ at high temperatures or $\ln G \propto E^{-\frac{1}{3}}$ as temperature is decreased or the applied electric field is increased. This highlights the different nature of our material to that published in the literature. Specifically our rGO samples differ from the highly disordered graphene of Lo and colleagues [Lo et al. 2013] who report electrical conduction following the Efros-Shklovskii model. In contrast, our rGO samples are only partially disordered in that they contain alongside the disordered regions also highly crystalline regions.

8.1.3 Phenomenological models

In this thesis, we also included exploratory work detailing attempts at improving further our crossover model. One of which is the exploration of a single composite function that is able to describe the data over the whole voltage range. Another work is the trial of a phenomenological model that achieves a similar objective. However, for both of these exploratory fitting functions, no meaningful physical interpretation has been developed in contrast to the abundance of physics that results from our crossover model already described. Hence we emphasize the superiority of our crossover model over these other phenomenological expressions.

8.1.4 A proposal for a temperature-assisted, field-driven hopping expression

We further develop, in analogy to the work of Pollak and Riess, a temperature-assisted, field-driven VRH which aims to extend the field-driven expression of Shklovskii to cases wherein the temperatures are increased. The general form of our proposed model is as follows:

$$G(T, E) = G_m \exp \left[- \left(\frac{E_0}{E} \right)^p \right] \exp \left(\frac{bT}{E} \right), \quad (8.7)$$

where b is a constant. We discover that such an expression gives a good fit to the data until certain limits wherein the temperatures are too high or the applied field too low. In such cases the electronic transport mechanism crosses over to a temperature-driven (Mott) VRH, $\ln G \propto T^{-p}$, as expected.

8.1.5 Average hopping lengths reveal the non-uniformity of field distribution

The average hopping length obtained from our model is of the order of $60 - 80 \text{ nm}$ for the different gate voltages. This is found to be an order of magnitude larger than physically viable in the actual sample, as from STM data on the graphene samples we observe that the disordered regions are of the mean size $\sim 6 \text{ nm}$. We attribute this to the assumption of uniform electric field distribution across the whole sample which cannot hold due to our partially disordered nature of the sample. Thus we propose based on our calculated values that the electric field is highly non-uniform and largely concentrated in the disordered regions which act as potential barriers.

We found that the mean hopping distance in the disordered regions of the rGO decreases as the temperature increases. This is consistent with the theoretical expectation of the VRH model which states that more energy levels become available as thermal energy increases, thus decreasing the average length needed for transition between localized states.

8.1.6 Relation between temperature and field scale parameters

We also investigated the theoretically predicted equivalence of the temperature and field scaling parameters. The field scaling parameter E_0 was predicted by Shklovskii to be related to the Mott parameter T_0 by the relation:

$$eE_0 r(T) \sim ck_B T_0 \quad (8.8)$$

where the dimensionless pre-factor c is predicted to be of order unity. We understand this relation to mean that the energy difference over a mean hopping distance $r(T)$ of an electron in an electric field equal to the field scale parameter E_0 is expected to have a similar magnitude to its analogous thermal energy $k_B T_0$.

We find that the relationships between both scaling parameters are of the order unity as predicted when the majority charge carriers are either electrons or holes in our rGO samples. However, near the charge neutrality point, the relationship is different with the dimensionless pre-factor c of the order of 10, which we attribute to the nature of the low density of electronic states in the region.

8.1.7 Crossover model valid also for 3D and 1D disordered carbon materials

We further proceed to demonstrate the validity of our crossover model from the two-dimensional disordered conductor that is reduced graphene oxide to disordered carbon materials of other dimensionalities reported by other groups. These are the 3D self-assembled carbon networks of Govor et al. and quasi-1D highly-doped conducting polymers of Wang et al.

We propose our crossover model that is based on established theoretical framework as being a natural and simple explanation of the data of Govor et al. In the model proposed by the latter, the system dimensionality is not preserved in that they use a variable power law in the field-driven exponential term. In contrast, we discard the need to vary the power index and instead fix the index according to the system dimensionality. The main advantage of our model is that we are able to describe the full range of their data without splitting the dataset into arbitrary temperature ranges.

Based on the reported experimental conductivity data in quasi-1D highly doped conducting polymers of Wang et al., we show that with increase of the applied electric field at a fixed temperature, the data seems to suggest a deviation from the Pollak-Riess conduction regime approaching a crossover to the Shklovskii regime.

We have also investigated the theoretically predicted equivalence between temperature- and field-scaling parameters for the 3D carbon networks while the data for the quasi-1D conducting polymers could not be used for this analysis. We found that this equivalence does not hold for the carbon networks. We propose that this equivalence between the temperature and field scaling parameters is sample-dependent.

Possible contributing factors are the inhomogeneity of defects which in turn influence the uniformity of electric field distribution within the sample, which directly affects the electronic conduction across the sample.

8.2 Conduction in single-wall carbon nanotube networks: further evidence for our crossover model

We find further evidence of our crossover VRH model for a particular sample of single-wall carbon nanotube (SWNT) network prepared via chemical vapour deposition (CVD). This is part of a systematic study of CVD-grown SWNT networks with a spectrum of morphologies from dense networks to sparse networks.

8.2.1 Electronic transport mechanisms and correlation to morphology

We correlate the morphology of the SWNT networks based on scanning electron microscopy (SEM) images with their electronic transport mechanism. We find that SWNT networks which consist of relatively sparse tubes are observed to tend to zero conductance when temperature is lowered to near absolute zero temperature (0 K); this is consistent with the physical model of VRH conduction. On the other hand, SWNT networks which consist of relatively dense tubes are observed to be able to retain a significant fraction of the room-temperature conductance as the temperature tends to absolute zero; this is consistent with the physical model of fluctuation assisted tunnelling (FAT).

The general form of temperature-driven FAT conductivity σ model of Sheng is as follows:

$$\sigma^{-1}(T) = \sigma_0^{-1} \exp\left(\frac{T_b}{T + T_s}\right) \quad (8.9)$$

where T_s is the Sheng parameter and T_b an indicator of barrier energy. In certain samples showing FAT conduction, there is an additional contribution to resistance from phonon scattering that is most significant at near room temperature. On the other hand, most FAT samples can be described across the temperature range from absolute zero to room temperature by a sole FAT model.

We can understand the nature of the distinct physical phenomena by the following. VRH conduction involves quantum tunnelling between localized electronic states. As such, as temperature tends to zero, electronic states tend to insulating behaviour and thus exhibit zero conductance. Meanwhile, FAT conduction involves tunnelling of delocalized electronic states, i.e. metallic states, through thin potential barriers. Thus, as temperature tends to zero, a significant remnant conduction is still possible due to the metallic states.

8.2.2 Field-dependent data shows field analogue to temperature-dependent transport

Electric field-dependent measurements revealed the electrical analogous behaviour of the temperature-dependent data. Specifically, temperature-dependent VRH, i.e. the Mott law, corresponded with VRH that is field-assisted and temperature-driven, the so-called Pollak-Riess VRH. We emphasize again that notably, one SWNT network exhibits a crossover from Pollak-Riess VRH to the field-driven Shklovskii VRH as the temperature is decreased or the applied field increased, showing further evidence for our proposed VRH crossover model for disordered carbon materials. Similarly, temperature-driven FAT of Sheng corresponded with field-driven FAT proposed by Kaiser and Park.

8.2.3 Mean hopping distances

We calculated the mean hopping distances in the SWNT networks exhibiting VRH conduction with the assumption that the electric field distribution is uniform throughout each network. The mean hopping distances obtained from our calculations are generally of the order of 100 nm which we consider to be reasonable compared with the scale of the nanotube networks. While for one network, we found the mean hopping distance decreases as the temperature increases, consistent with the VRH theory, for another network an opposite trend is observed and we attribute this to probably electron-electron Coulombic interactions becoming dominant in the network.

8.2.4 Order estimate of barrier energies and quantum tunnelling

For SWNT networks exhibiting FAT conduction, we estimate an indication of the order of barrier energies and the extent of quantum tunnelling occurring within the sample. We find these indicators while helpful to be sample-dependent and also dependent on the applied voltage during electrical testing.

In this thesis, we also include the analysis of a SWNT network that is not grown by the in-situ method of CVD but instead by post-growth deposition method for comparison. The latter networks are prepared by Andrade et al. However, due to the limited amount of available data, no meaningful conclusion can be drawn from this comparison.

8.3 Outlook

Moving forward, as the production methods of graphene advance from the laboratory into large-scale production, it is certainly the long-term goal to produce as pristine graphene as possible. As demonstrated by industrial materials scientists [e.g. Lippert et al. 2014], the VRH theory can serve as a simple test for the presence of defects in the graphene. It must be emphasized that not all disorders might be undesirable, as these may contribute towards novel materials and device properties [e.g. Terrones et al. 2012].

The main topic of interest for further development in this thesis is the transition region between the temperature-dependent and field-dependent VRH effected by the crossover field described by our analytical expression. Experimental work is suggested to study disordered carbon materials, particularly at temperatures and field conditions where the crossovers have been shown to occur in this thesis, to further understand the nature of such transitions between two distinct VRH regimes. We also expect such transitions to occur in non-carbon disordered materials.

A related interesting development in electronic conduction studies is reported recently by the Brown group in the University of Canterbury [Sattar et al. 2013]. It has been found that quantum tunnelling transport consistent with VRH dominates the conduction between groups of non-connecting metallic particles carefully controlled to be just below the percolation threshold. This paper is the first instance, to the best of our knowledge, wherein VRH is explicitly modelled as the conduction mechanism before the onset of percolation conduction.

References

- Adam, S., Jung, S., Klimov, N. N., Zhitenev, N. B., Strosio, J. A., and Stiles, M. D., "Mechanism for puddle formation in graphene", *Physical Review B* **84**, 23 (2011), 235421.
- Anderson, P. W. "Absence of diffusion in certain random lattices", *Physical Review* **109**, 5 (1958), 1492-1505.
- Andrade, M. J., Lima, M. D., Skákalová, V., Bergmann, C. P., and Roth, S., "Electrical properties of transparent carbon nanotube networks prepared through different techniques", *physica status solidi – Rapid Research Letters* **1**, 5 (2007), 178-180.
- Ansaldo, A., Haluška, M., Čech, J., Meyer, J. C., Ricci, D., Gatti, F., Di Zitti, E., Cincotti, S., and Roth, S., "A study of the effect of different catalysts for the efficient CVD growth of carbon nanotubes on silicon substrates", *Physica E: Low-dimensional Systems and Nanostructures* **37**, 1–2 (2007), 6-10.
- Ansaldo, A., Jaybhaye, S., Chiarolini, M., Di Zitti, E., and Ricci, D., "Single-walled carbon nanotube networks growth optimization", *physica status solidi (b)* **246**, 11-12 (2009), 2473-2476.
- Ansaldo, A., Skákalová, V., Ricci, D., Di Zitti, E., and Roth, S., "Direct transfer of CVD-grown transparent SWCNT networks from growth substrate to polymer", *Physica E: Low-dimensional Systems and Nanostructures* **40**, 7 (2008), 2430-2433.
- Arkhipov, V. I., Emelianova, E. V., and Adriaenssens, G. J., "Field-dependent effective temperature and variable range hopping: Application to dark dc conductivity in doped a-Si:H", *Journal of Applied Physics* **93**, 10 (2003), 6150-6153.
- Avdoshenko, S. M., Koskinen, P., Sevinçli, H., Popov, A. A., and Rocha, C. G., "Topological signatures in the electronic structure of graphene spirals", *Scientific Reports* **3**, (2013), 1632.
- Bagri, A., Mattevi, C., Acik, M., Chabal, Y. J., Chhowalla, M., and Shenoy, V. B., "Structural evolution during the reduction of chemically derived graphene oxide", *Nature Chemistry* **2**, 7 (2010), 581-587.

- Ball, P., "Roll up for the revolution", *Nature* **414**, 6860 (2001), 142-144.
- Banhart, F. "The transformation of graphitic onions to diamond under electron irradiation", *Journal of Applied Physics* **81**, 8 (1997), 3440-3445.
- Baringhaus, J., Ruan, M., Edler, F., Tejeda, A., Sicot, M., Taleb-Ibrahimi, A., Li, A.-P., Jiang, Z., Conrad, E. H., Berger, C., Tegenkamp, C., and de Heer, W. A., "Exceptional ballistic transport in epitaxial graphene nanoribbons", *Nature* **506**, 7488 (2014), 349-354.
- Barnard, A. S., and Snook, I. K., "Ripple induced changes in the wavefunction of graphene: an example of a fundamental symmetry breaking", *Nanoscale* **4**, 4 (2012), 1167-1170.
- Biercuk, M. J., Ilani, S., Marcus, C. M., and McEuen, P. L., *Electrical Transport in Single-Wall Carbon Nanotubes (Carbon Nanotubes, Topics in Applied Physics vol. 111)*, Jorio, A., Dresselhaus, G., and Dresselhaus, M. S. (Eds.) (Springer, Berlin, 2008).
- Bonaccorso, F., Sun, Z., Hasan, T., and Ferrari, A. C., "Graphene photonics and optoelectronics", *Nature Photonics* **4**, 9 (2010), 611-622.
- Borisenko, S., Gibson, Q., Evtushinsky, D., Zabolotnyy, V., Büchner, B., and Cava, R. J., "Experimental realization of a three-dimensional Dirac semimetal", *Physical Review Letters* **113**, 2 (2014), 027603.
- Botas, C., Álvarez, P., Blanco, P., Granda, M., Blanco, C., Santamaría, R., Romasanta, L. J., Verdejo, R., López-Manchado, M. A., and Menéndez, R., "Graphene materials with different structures prepared from the same graphite by the Hummers and Brodie methods", *Carbon* **65**, (2013), 156-164.
- Bourzac, K. "Graphene's dark side", *Scientific American* **311**, 1 (2014). Available at <http://www.scientificamerican.com/article/graphene-s-dark-side/>, accessed June 2014. [viewpoint on Lanphere et al. 2014]
- Cao, Q., and Rogers, J. A., "Ultrathin films of single-walled carbon nanotubes for electronics and sensors: a review of fundamental and applied aspects", *Advanced Materials* **21**, 1 (2009), 29-53.
- Castro Neto, A. H., Guinea, F., Peres, N. M. R., Novoselov, K. S., and Geim, A. K., "The electronic properties of graphene", *Reviews of Modern Physics* **81**, 1 (2009), 109-162.
- Chakrabarti, S., Nagasaka, T., Yoshikawa, Y., Pan, L., and Nakayama, Y., "Growth of super long aligned brush-like carbon nanotubes", *Japanese Journal of Applied Physics* **45**, 28 (2006), L720-L722.
- Cheah, C. Y., and Kaiser, A. B., "Variable-range hopping transport: crossovers from temperature dependence to electric field dependence in disordered carbon materials", *International Journal of Nanotechnology* **11**, 5-8 (2014), 412-418.

- Cheah, C. Y., Gómez-Navarro, C., Jaurigue, L. C., and Kaiser, A. B., "Conductance of partially disordered graphene: crossover from temperature-dependent to field-dependent variable-range hopping", *Journal of Physics: Condensed Matter* **25**, 46 (2013), 465303.
- Cheah, C. Y., Kumar, R., and Yam, F. K., "Reduction of process-induced crystalline defects during silicon wafer processing", *Proceedings of the IEEE Regional Symposium on Micro and Nano Electronics* (IEEE Electron Devices Society, Kota Bharu, 2009), pp. 545-549.
- Chen, C.-C., Li, Z., Shi, L., and Cronin, S. B., "Thermal interface conductance across a graphene/hexagonal boron nitride heterojunction", *Applied Physics Letters* **104**, 8 (2014), 081908.
- Compton, O. C., and Nguyen, S. T., "Graphene oxide, highly reduced graphene oxide, and graphene: versatile building blocks for carbon-based materials", *Small* **6**, 6 (2010), 711-723.
- Compton, O. C., Dikin, D. A., Putz, K. W., Brinson, L. C., and Nguyen, S. T., "Electrically conductive "alkylated" graphene paper via chemical reduction of amine-functionalized graphene oxide paper", *Advanced Materials* **22**, 8 (2010), 892-896.
- Cruz-Silva, R., Morelos-Gomez, A., Kim, H.-i., Jang, H.-k., Tristan, F., Vega-Diaz, S., Rajukumar, L. P., Elías, A. L., Perea-Lopez, N., Suhr, J., Endo, M., and Terrones, M., "Super-stretchable graphene oxide macroscopic fibers with outstanding knotability fabricated by dry film scrolling", *ACS Nano* **8**, 6 (2014), 5959-5967.
- Das Sarma, S., Adam, S., Hwang, E. H., and Rossi, E., "Electronic transport in two-dimensional graphene", *Reviews of Modern Physics* **83**, 2 (2011), 407-470.
- De Volder, M. F. L., Tawfick, S. H., Baughman, R. H., and Hart, A. J., "Carbon nanotubes: present and future commercial applications", *Science* **339**, 6119 (2013), 535-539.
- Dresselhaus, M. S., Dresselhaus, G., and Fischer, J. E., "Graphite intercalation compounds: Electronic properties in the dilute limit", *Physical Review B* **15**, 6 (1977), 3180-3192.
- Eda, G., and Chhowalla, M., "Chemically derived graphene oxide: towards large-area thin-film electronics and optoelectronics", *Advanced Materials* **22**, 22 (2010), 2392-2415.
- Efros, A. L., and Shklovskii, B. I., "Coulomb gap and low temperature conductivity of disordered systems", *Journal of Physics C: Solid State Physics* **8**, 4 (1975), L49.
- Geim, A. K., and MacDonald, A. H., "Graphene: Exploring carbon flatland", *Physics Today* **60**, 8 (2007), 35-41.
- Geim, A. K., and Novoselov, K. S., "The rise of graphene", *Nature Materials* **6**, 3 (2007), 183-191.

- Giancoli, D. C., *Physics for Scientists and Engineers with Modern Physics*, 4th ed., (Pearson, New Jersey, 2009).
- Gómez-Navarro, C., Weitz, R. T., Bittner, A. M., Scolari, M., Mews, A., Burghard, M., and Kern, K., "Electronic transport properties of individual chemically reduced graphene oxide sheets", *Nano Letters* **7**, 11 (2007), 3499-3503.
- Govor, L. V., Bashmakov, I. A., Boehme, K., and Parisi, J., "Electrical field dependence of hopping conduction in self-organized carbon networks", *Journal of Applied Physics* **91**, 2 (2002), 739-747. [Note: quite similar results to Govor et al. 2000]
- Govor, L. V., Bashmakov, I. A., Kiebooms, R., Dyakonov, V., and Parisi, J., "Self-organized networks based on conjugated polymers", *Advanced Materials* **13**, 8 (2001), 588-591.
- Govor, L. V., Goldbach, M., Bashmakov, I. A., Butylina, I. B., and Parisi, J., "Electrical properties of self-assembled carbon networks", *Physical Review B* **62**, 3 (2000), 2201-2208.
- Grigorenko, A. N., Polini, M., and Novoselov, K. S., "Graphene plasmonics", *Nature Photonics* **6**, 11 (2012), 749-758.
- Grobert, N., "Carbon nanotubes – becoming clean", *Materials Today* **10**, 1–2 (2007), 28-35.
- Hauser, J. J., and Rodgers, J. W., "Variable range hopping in Al implanted sapphire", *Applied Physics Letters* **40**, 8 (1982), 707-708.
- Herrmann, M., and Schenk, A., "Field and high-temperature dependence of the long term charge loss in erasable programmable read only memories: Measurements and modeling", *Journal of Applied Physics* **77**, 9 (1995), 4522-4540.
- Hicks, J., Tejeda, A., Taleb-Ibrahimi, A., Nevius, M. S., Wang, F., Shepperd, K., Palmer, J., Bertran, F., Le Fevre, P., Kunc, J., de Heer, W. A., Berger, C., and Conrad, E. H., "A wide-bandgap metal-semiconductor-metal nanostructure made entirely from graphene", *Nature Physics* **9**, 1 (2013), 49-54.
- Hill, E. W., Geim, A. K., Novoselov, K., Schedin, F., and Blake, P., "Graphene spin valve devices", *IEEE Transactions on Magnetics* **42**, 10 (2006), 2694-2696.
- Huang, Y.-L., Chiu, S.-P., Zhu, Z.-X., Li, Z.-Q., and Lin, J.-J., "Variable-range-hopping conduction processes in oxygen deficient polycrystalline ZnO films", *Journal of Applied Physics* **107**, 6 (2010), 063715.
- Hummers, W. S., Jr., and Offeman, R. E., "Preparation of graphitic oxide", *Journal of the American Chemical Society* **80**, 6 (1958), 1339-1339.
- Iijima, S., "Helical microtubules of graphitic carbon", *Nature* **354**, 6348 (1991), 56-58.
- Iijima, S., and Ichihashi, T., "Single-shell carbon nanotubes of 1-nm diameter", *Nature* **363**, 6430 (1993), 603-605.

- Inagaki, M. "Applications of graphite intercalation compounds", *Journal of Materials Research* **4**, 06 (1989), 1560-1568.
- Jayasinghe, C., Chakrabarti, S., Schulz, M. J., and Shanov, V., "Spinning yarn from long carbon nanotube arrays", *Journal of Materials Research* **26**, 05 (2011), 645-651.
- Kaiser, A. B. "Electronic transport properties of conducting polymers and carbon nanotubes", *Reports on Progress in Physics* **64**, 1 (2001), 1-49.
- Kaiser, A. B., and Park, Y. W., "Current-voltage characteristics of conducting polymers and carbon nanotubes", *Synthetic Metals* **152**, 1-3 (2005), 181-184.
- Kaiser, A. B., and Skákalová, V. "Electronic conduction in polymers, carbon nanotubes and graphene", *Chemical Society Reviews* **40**, 7 (2011), 3786-3801.
- Kaiser, A. B., Gómez-Navarro, C., Sundaram, R. S., Burghard, M., and Kern, K., "Electrical conduction mechanism in chemically derived graphene monolayers", *Nano Letters* **9**, 5 (2009), 1787-1792.
- Kaiser, A. B., Rogers, S. A., and Park, Y. W., "Charge transport in conducting polymers: polyacetylene nanofibres", *Molecular Crystals and Liquid Crystals* **415**, 1 (2004), 115-124.
- Kaiser, A. B., Skákalová, V., and Roth, S., "Modelling conduction in carbon nanotube networks with different thickness, chemical treatment and irradiation", *Physica E: Low-dimensional Systems and Nanostructures* **40**, 7 (2008), 2311-2318.
- Kamalakannan, R., Ganesan, K., Ilango, S., Thirumurugan, N., Singh, V. N., Kamruddin, M., Mehta, B. R., and Tyagi, A. K., "The role of structural defects on the transport properties of a few-walled carbon nanotube networks", *Applied Physics Letters* **98**, 19 (2011), 192105.
- Katsnelson, M. I., and Geim, A. K., "Electron scattering on microscopic corrugations in graphene", *Philosophical Transactions of the Royal Society A: Mathematical, Physical and Engineering Sciences* **366**, 1863 (2008), 195-204.
- Kelly, M. J., "Application of the Johnson criteria to graphene transistors", *Semiconductor Science and Technology* **28**, 12 (2013), 122001.
- Kelly, M. J., "From nanoscience to nanotechnology: what can and what cannot be manufactured", *International Journal of Nanotechnology* **11**, 5-8 (2014), 441-444.
- Khan, Z. H., Husain, M., Perng, T. P., Salah, N., and Habib, S., "Electrical transport via variable range hopping in an individual multi-wall carbon nanotube", *Journal of Physics: Condensed Matter* **20**, 47 (2008), 475207.
- Kiveris, A., Kudžmauskas, Š., and Pipinys, P., "Release of electrons from traps by an electric field with phonon participation", *physica status solidi (a)* **37**, 1 (1976), 321-327.

- Kovtyukhova, N. I., Wang, Y., Berkdemir, A., Cruz-Silva, R., Terrones, M., Crespi, V. H., and Mallouk, T. E., "Non-oxidative intercalation and exfoliation of graphite by Brønsted acids", *Nature Chemistry* (2014), advance online publication, doi:10.1038/nchem.2054.
- Kroemer, H., "Nobel lecture: Quasielectric fields and band offsets: Teaching electrons new tricks", *Reviews of Modern Physics* **73**, (2001), 783-793.
- Kroemer, H., "Speculations about future directions", *Journal of Crystal Growth* **251**, (2003), 17-22.
- Lan, Y., Wang, Y., and Ren, Z. F., "Physics and applications of aligned carbon nanotubes", *Advances in Physics* **60**, 4 (2011), 553-678.
- Lanphere, J. D., Rogers, B., Luth, C., Bolster, C. H., and Walker, S. L., "Stability and transport of graphene oxide nanoparticles in groundwater and surface water", *Environmental Engineering Science* **31**, 7 (2014), 350-359.
- Lanza, M., Wang, Y., Bayerl, A., Gao, T., Porti, M., Nafria, M., Liang, H., Jing, G., Liu, Z., Zhang, Y., Tong, Y., and Duan, H., "Tuning graphene morphology by substrate towards wrinkle-free devices: Experiment and simulation", *Journal of Applied Physics* **113**, 10 (2013), 104301.
- Lee, C., Wei, X., Kysar, J. W., and Hone, J., "Measurement of the elastic properties and intrinsic strength of monolayer graphene", *Science* **321**, 5887 (2008), 385-388.
- Lee, G.-H., Cooper, R. C., An, S. J., Lee, S., van der Zande, A., Petrone, N., Hammerberg, A. G., Lee, C., Crawford, B., Oliver, W., Kysar, J. W., and Hone, J., "High-strength chemical-vapor-deposited graphene and grain boundaries", *Science* **340**, 6136 (2013), 1073-1076.
- Lehman, J. H., Terrones, M., Mansfield, E., Hurst, K. E., and Meunier, V., "Evaluating the characteristics of multiwall carbon nanotubes", *Carbon* **49**, 8 (2011), 2581-2602.
- Lima, M. D., Andrade, M. J., Skákalová, V., Nobre, F., Bergmann, C. P., and Roth, S., "In-situ synthesis of transparent and conductive carbon nanotube networks", *physica status solidi – Rapid Research Letters* **1**, 4 (2007), 165-167.
- Lippert, G., Dąbrowski, J., Schroeder, T., Schubert, M. A., Yamamoto, Y., Herziger, F., Maultzsch, J., Baringhaus, J., Tegenkamp, C., Asensio, M. C., Avila, J., and Lupina, G., "Graphene grown on Ge(001) from atomic source", *Carbon* **75**, (2014), 104-112.
- Liu, X., Bumby, C. W., Spencer, J. L., Arnold, W. M., and Kaiser, A. B., "Multi-walled carbon nanotubes synthesised from different catalysts: morphology, dielectrophoresis and conductance", *International Journal of Nanotechnology* **6**, 3-4 (2009), 329-343.
- Liu, Z. K., Jiang, J., Zhou, B., Wang, Z. J., Zhang, Y., Weng, H. M., Prabhakaran, D., Mo, S.-K., Peng, H., Dudin, P., Kim, T., Hoesch, M., Fang, Z., Dai, X., Shen, Z.

- X., Feng, D. L., Hussain, Z., and Chen, Y. L., "A stable three-dimensional topological Dirac semimetal Cd_3As_2 ", *Nature Materials* **13**, 7 (2014), 677-681.
- Lo, S.-T., Chuang, C., Puddy, R. K., Chen, T.-M., Smith, C. G., and Liang, C.-T., "Non-ohmic behavior of carrier transport in highly disordered graphene", *Nanotechnology* **24**, 16 (2013), 165201.
- Loh, K. P., Bao, Q., Eda, G., and Chhowalla, M., "Graphene oxide as a chemically tunable platform for optical applications", *Nature Chemistry* **2**, 12 (2010), 1015-1024.
- López, V., Sundaram, R. S., Gómez-Navarro, C., Olea, D., Burghard, M., Gómez-Herrero, J., Zamora, F., and Kern, K., "Chemical vapor deposition repair of graphene oxide: a route to highly-conductive graphene monolayers", *Advanced Materials* **21**, 46 (2009), 4683-4686.
- Mansfield, R. "Hopping conduction in III-V compounds", In: *Hopping Transport in Solids (Modern Problems in Condensed Matter Sciences vol. 28)*, Pollak, M., and Shklovskii, B. (Eds.), Agranovich, V. M., and Maradudin, A. A. (Series Eds.) (Elsevier, Amsterdam, 1991), pp. 349-375.
- Marcano, D. C., Kosynkin, D. V., Berlin, J. M., Sinitskii, A., Sun, Z., Slesarev, A., Alemany, L. B., Lu, W., and Tour, J. M., "Improved synthesis of graphene oxide", *ACS Nano* **4**, 8 (2010), 4806-4814.
- Martin, J., Akerman, N., Ulbricht, G., Lohmann, T., Smet, J. H., von Klitzing, K., and Yacoby, A., "Observation of electron-hole puddles in graphene using a scanning single-electron transistor", *Nature Physics* **4**, 2 (2008), 144-148.
- Mehr, W., Dabrowski, J., Lemme, M., Lippert, G., Lupina, G., and Scheytt, J. C., "P-type graphene base transistor", *U.S. Patent 2014/0027715* (2014), filed 20 Dec. 2012, and issued 30 Jan. 2014.
- Mehr, W., Dabrowski, J., Scheytt, J. C., Lippert, G., Xie, Y.-H., Lemme, M. C., Ostling, M., and Lupina, G., "Vertical graphene base transistor", *IEEE Electron Device Letters* **33**, 5 (2012), 691-693.
- Minett, D. R., O'Byrne, J. P., Jones, M. D., Ting, V. P., Mays, T. J., and Mattia, D., "One-step production of monolith-supported long carbon nanotube arrays", *Carbon* **51**, (2013), 327-334.
- Monthieux, M., and Kuznetsov, V. L., "Who should be given the credit for the discovery of carbon nanotubes?", *Carbon* **44**, 9 (2006), 1621-1623.
- Morozov, S. V., Novoselov, K. S., and Geim, A. K., "Electron transport in graphene", *Physics-Uspekhi* **51**, 7 (2008), 744.
- Mott, N. F., "Conduction in glasses containing transition metal ions", *Journal of Non-Crystalline Solids* **1**, 1 (1968), 1-17.
- Mott, N. F., "Electrons in glass", *Nobel Lecture* (1977), available at http://www.nobelprize.org/nobel_prizes/physics/laureates/1977/mott-lecture.pdf

- Mott, N. F., "Introductory talk: Conduction in non-crystalline materials", *Journal of Non-Crystalline Solids* **8–10**, (1972), 1-18.
- Mott, N. F., and Davis, E. A., *Electronic Processes in Non-Crystalline Materials*, 2nd ed., Marshall, W., and Wilkinson, D. H. (Series Eds.) (Oxford, New York, 1979), Chapter 2.
- Mott, N. F., *Conduction in Non-Crystalline Materials*, 2nd ed. (Oxford, New York, 1993), pp. 31-32.
- Mucciolo, E. R., and Lewenkopf, C. H., "Disorder and electronic transport in graphene", *Journal of Physics: Condensed Matter* **22**, 27 (2010), 273201.
- Muchharla, B., Narayanan, T. N., Balakrishnan, K., Ajayan, P. M., and Talapatra, S., "Temperature dependent electrical transport of disordered reduced graphene oxide", *2D Materials* **1**, 1 (2014), 011008.
- Neupane, M., Xu, S.-Y., Sankar, R., Alidoust, N., Bian, G., Liu, C., Belopolski, I., Chang, T.-R., Jeng, H.-T., Lin, H., Bansil, A., Chou, F., and Hasan, M. Z., "Observation of a three-dimensional topological Dirac semimetal phase in high-mobility Cd_3As_2 ", *Nature Communications* **5**, (2014), 3786.
- Nika, D. L., and Balandin, A. A., "Two-dimensional phonon transport in graphene", *Journal of Physics: Condensed Matter* **24**, 23 (2012), 233203.
- Novoselov, K. S., Fal'ko, V. I., Colombo, L., Gellert, P. R., Schwab, M. G., and Kim, K., "A roadmap for graphene", *Nature* **490**, 7419 (2012), 192-200.
- Novoselov, K. S., Geim, A. K., Morozov, S. V., Jiang, D., Katsnelson, M. I., Grigorieva, I. V., Dubonos, S. V., and Firsov, A. A., "Two-dimensional gas of massless Dirac fermions in graphene", *Nature* **438**, 7065 (2005b), 197-200.
- Novoselov, K. S., Geim, A. K., Morozov, S. V., Jiang, D., Zhang, Y., Dubonos, S. V., Grigorieva, I. V., and Firsov, A. A., "Electric field effect in atomically thin carbon films", *Science* **306**, 5696 (2004), 666-669.
- Novoselov, K. S., Jiang, D., Schedin, F., Booth, T. J., Khotkevich, V. V., Morozov, S. V., and Geim, A. K., "Two-dimensional atomic crystals", *Proceedings of the National Academy of Sciences* **102**, 30 (2005a), 10451-10453.
- Okada, K., and Taniguchi, K., "Electrical stress-induced variable range hopping conduction in ultrathin silicon dioxides", *Applied Physics Letters* **70**, 3 (1997), 351-353.
- Özmen-Monkul, B., *Graphite Intercalation with Fluoroanions by Chemical and Electrochemical Methods*, PhD Thesis (Materials Science), Oregon State University (2010).
- Paasch, G., Lindner, T., and Scheinert, S., "Variable range hopping as possible origin of a universal relation between conductivity and mobility in disordered organic semiconductors", *Synthetic Metals* **132**, 1 (2002), 97-104.

- Paufler, P., "Book Review – Graphene: Carbon in Two Dimensions by Mikhail I. Katsnelson. Cambridge University Press, 2012", *Journal of Applied Crystallography* **46**, 4 (2013), 1240-1241.
- Pei, S., and Cheng, H.-M., "The reduction of graphene oxide", *Carbon* **50**, 9 (2012), 3210-3228.
- Peres, N. M. R., "Colloquium: The transport properties of graphene: An introduction", *Reviews of Modern Physics* **82**, 3 (2010), 2673-2700.
- Petroski, H., *The Pencil: A History of Design and Circumstance* (Random House, New York, 1992).
- Pichon, L., and Rogel, R., "Experimental validation of the exponential localized states distribution in the variable range hopping mechanism in disordered silicon films", *Applied Physics Letters* **99**, 7 (2011), 072106.
- Pietronero, L., "Ideal conductivity of carbon π polymers and intercalation compounds", *Synthetic Metals* **8**, 3–4 (1983), 225-231.
- Pipinys, P., and Kiveris, A., "Comment on 'Electrical transport via variable range hopping in an individual multi-wall carbon nanotube'", *Journal of Physics: Condensed Matter* **22**, 2 (2010), 028001.
- Pipinys, P., and Kiveris, A., "Phonon-assisted tunnelling in electrical conductivity of individual carbon nanotubes and networks ones", *Physica B: Condensed Matter* **403**, 19–20 (2008), 3730-3733.
- Pipinys, P., and Kiveris, A., "Variable range hopping and/or phonon-assisted tunneling mechanism of electronic transport in polymers and carbon nanotubes", *Central European Journal of Physics* **10**, 2 (2012), 271-281.
- Pollak, M., and Riess, I., "A percolation treatment of high-field hopping transport", *Journal of Physics C: Solid State Physics* **9**, 12 (1976), 2339-2352.
- Pope, M., and Swenberg, C. E., *Electronic Processes in Organic Crystals and Polymers (Monographs on the Physics and Chemistry of Materials vol. 56)*, 2nd ed., Brook, R. J., Cheetham, A., Heuer, A., Hirsch, P., Marks, T. J., Pettifor, D. G., Silcox, J., Rühle, M., Tirrell, M. V., and Vitek, V. (Eds.), (Oxford, New York, 1999).
- Rafique, M. M. A., and Iqbal, J., "Production of carbon nanotubes by different routes—a review", *Journal of Encapsulation and Adsorption Sciences* **1**, (2011), 29-34.
- Rajput, S., Chen, M. X., Liu, Y., Li, Y. Y., Weinert, M., and Li, L., "Spatial fluctuations in barrier height at the graphene–silicon carbide Schottky junction", *Nature Communications* **4**, (2013), 2752.
- Ravi, S., Kaiser, A. B., and Bumby, C. W., "Charge transport in surfactant-free single walled carbon nanotube networks", *physica status solidi (b)* **250**, 8 (2013), 1463-1467.

- Ravi, S., Kaiser, A. B., and Bumby, C. W., "Improved conduction in transparent single walled carbon nanotube networks drop-cast from volatile amine dispersions", *Chemical Physics Letters* **496**, 1-3 (2010), 80-85.
- Ridley, B. K., *Quantum Processes in Semiconductors* (Oxford, New York, 1982), Chapter 5.
- Rutherglen, C., Jain, D., and Burke, P., "Nanotube electronics for radiofrequency applications", *Nature Nanotechnology* **4**, 12 (2009), 811-819.
- Sadeghi, M. M., Jo, I., and Shi, L., "Phonon-interface scattering in multilayer graphene on an amorphous support", *Proceedings of the National Academy of Sciences* **110**, 41 (2013), 16321-16326.
- Sarachik, M. P., and Dai, P., "Variable-range hopping in Si:B: A temperature-independent prefactor in three dimensions", *physica status solidi (b)* **230**, 1 (2002), 205-209.
- Sarkar, A., and Daniels-Race, T., "Electrophoretic deposition of carbon nanotubes on 3-amino-propyl-triethoxysilane (APTES) surface functionalized silicon substrates", *Nanomaterials* **3**, 2 (2013), 272-288.
- Sattar, A., Fostner, S., and Brown, S. A., "Quantized conductance and switching in percolating nanoparticle films", *Physical Review Letters* **111**, 13 (2013), 136808.
- Seliuta, D., Subačius, L., Kašalynas, I., Shuba, M., Paddubskaya, A., Ksenevich, V., Kuzhir, P., Maksimenko, S., and Valušis, G., "Electrical conductivity of single-wall carbon nanotube films in strong electric field", *Journal of Applied Physics* **113**, 18 (2013), 183719.
- Sharma, N., Granville, S., Kashyap, S. C., and Ansermet, J.-P., "Low-temperature hopping and absence of spin-dependent transport in single crystals of cobalt-doped ZnO", *Physical Review B* **82**, 12 (2010), 125211.
- Shegelski, M. R. A., *Hopping Conductivity in Lightly Doped Semiconductors*, PhD Thesis (Physics), University of British Columbia (1986).
- Sheng, P., "Fluctuation-induced tunneling conduction in disordered materials", *Physical Review B* **21**, 6 (1980), 2180-2195.
- Sheskin, D. J., *Handbook of Parametric and Nonparametric Statistical Procedures*, 3rd ed. (CRC, Boca Raton, 2004), pp. 945-955.
- Shklovskii, B. I., "Hopping conduction in semiconductors subjected to a strong electric field", *Soviet Physics – Semiconductors* **6**, 12 (1973), 1964-1967. [Translated from *Fizika i Tekhnika Poluprovodnikov* **6**, 12 (1972), 2335-2340]
- Shklovskii, B. I., and Efros, A. L., *Electronic Properties of Doped Semiconductors (Springer Series in Solid-State Sciences vol. 45)*, Cardona, M., Fulde, P., and Queisser, H.-J. (Series Eds.), (Springer, Berlin, 1984), Chapter 9. [Available at <http://www.tpi.umn.edu/shklovskii/>]

- Shulaker, M. M., Hills, G., Patil, N., Wei, H., Chen, H.-Y., Wong, H.-S. P., and Mitra, S., "Carbon nanotube computer", *Nature* **501**, 7468 (2013), 526-530.
- Skákalová, V., Kaiser, A. B., Woo, Y. S., and Roth, S., "Electronic transport in carbon nanotubes: From individual nanotubes to thin and thick networks", *Physical Review B* **74**, 8 (2006), 085403.
- Skákalová, V., Vretenár, V., Kopera, Ľ., Kotrusz, P., Mangler, C., Meško, M., Meyer, J. C., and Hulman, M., "Electronic transport in composites of graphite oxide with carbon nanotubes", *Carbon* **72**, (2014), 224-232.
- Sun, D.-M., Liu, C., Ren, W.-C., and Cheng, H.-M., "A review of carbon nanotube- and graphene-based flexible thin-film transistors", *Small* **9**, 8 (2013), 1188-1205.
- Sun, L., and Fugetsu, B., "Mass production of graphene oxide from expanded graphite", *Materials Letters* **109**, (2013), 207-210.
- Sundaram, R. S., Gómez-Navarro, C., Lee, E. J. H., Burghard, M., and Kern, K., "Noninvasive metal contacts in chemically derived graphene devices", *Applied Physics Letters* **95**, 22 (2009), 223507.
- Terrones, H., Lv, R., Terrones, M., and Dresselhaus, M. S., "The role of defects and doping in 2D graphene sheets and 1D nanoribbons", *Reports on Progress in Physics* **75**, 6 (2012), 062501.
- Tsen, A. W., Brown, L., Levendorf, M. P., Ghahari, F., Huang, P. Y., Havener, R. W., Ruiz-Vargas, C. S., Muller, D. A., Kim, P., and Park, J., "Tailoring electrical transport across grain boundaries in polycrystalline graphene", *Science* **336**, 6085 (2012), 1143-1146.
- van 't Erve, O. M. J., Friedman, A. L., Cobas, E., Li, C. H., Robinson, J. T., and Jonker, B. T., "Low-resistance spin injection into silicon using graphene tunnel barriers", *Nature Nanotechnology* **7**, 11 (2012), 737-742.
- Vandenberg, E. T., Bertilsson, L., Liedberg, B., Uvdal, K., Erlandsson, R., Elwing, H., and Lundström, I., "Structure of 3-aminopropyl triethoxy silane on silicon oxide", *Journal of Colloid and Interface Science* **147**, 1 (1991), 103-118.
- Vaziri, S., Lupina, G., Henkel, C., Smith, A. D., Östling, M., Dabrowski, J., Lippert, G., Mehr, W., and Lemme, M. C., "A graphene-based hot electron transistor", *Nano Letters* **13**, 4 (2013), 1435-1439.
- Vogel, F. L., Foley, G. M. T., Zeller, C., Falardeau, E. R., and Gan, J., "High electrical conductivity in graphite intercalated with acid fluorides", *Materials Science and Engineering* **31** (1977), 261-265.
- Wallace, P. R., "The band theory of graphite", *Physical Review* **71**, 9 (1947), 622-634.
- Wang, D. P., Feldman, D. E., Perkins, B. R., Yin, A. J., Wang, G. H., Xu, J. M., and Zaslavsky, A., "Hopping conduction in disordered carbon nanotubes", *Solid State Communications* **142**, 5 (2007), 287-291.

- Wang, X. X., Martoff, C. J., and Kaczanowicz, E., "Unified treatment of temperature, concentration, and electric-field dependences of variable-range-hopping conductivity", *Physical Review B* **51**, 8 (1995), 5402-5407.
- Wang, Z. H., Scherr, E. M., MacDiarmid, A. G., and Epstein, A. J., "Transport and EPR studies of polyaniline: A quasi-one-dimensional conductor with three-dimensional "metallic" states", *Physical Review B* **45**, 8 (1992), 4190-4202.
- Weng, L., Zhang, L., Chen, Y. P., and Rokhinson, L. P., "Atomic force microscope local oxidation nanolithography of graphene", *Applied Physics Letters* **93**, 9 (2008), 093107.
- Yosida, Y., and Oguro, I., "Variable range hopping conduction in LaC_2 , CeC_2 , or GdC_2 crystals encapsulated carbon nanocages", *Applied Physics Letters* **69**, 4 (1996), 586-588.
- Yu, D., Wang, C., Wehrenberg, B. L., and Guyot-Sionnest, P., "Variable range hopping conduction in semiconductor nanocrystal solids", *Physical Review Letters* **92**, 21 (2004), 216802.
- Zhang, Y., Tan, Y.-W., Stormer, H. L., and Kim, P., "Experimental observation of the quantum Hall effect and Berry's phase in graphene", *Nature* **438**, 7065 (2005), 201-204.

APPENDIX. Publications, presentations and publicity

A.1 Publications

1. C. Y. Cheah, C. Gómez-Navarro, L. C. Jaurigue and A. B. Kaiser, "Conductance of partially disordered graphene: crossover from temperature-dependent to field-dependent variable-range hopping", *Journal of Physics: Condensed Matter* **25**, 46 (2013), 465303.

[cited by Gunther Lippert et al., *Carbon* **75** (2014), 104-112.]
2. C. Y. Cheah and A. B. Kaiser, "Variable-range hopping transport: crossovers from temperature dependence to electric field dependence in disordered carbon materials", *International Journal of Nanotechnology* **11**, 5-8 (2014), 412-418.

Manuscripts in preparation:

- I. C. Y. Cheah, A. B. Kaiser, A. Ansaldo, M. D. Lima and V. Skákalová, "Electronic conduction in single-wall carbon nanotube networks grown via various CVD methods"
- II. C. Y. Cheah and A. B. Kaiser, "A temperature-assisted field-driven variable-range hopping model"

Our first paper [Cheah et al. 2013] presented a physical model in which temperature-dependent variable-range hopping crosses over to a field-dependent variable-range hopping via a smooth transition as the temperature is decreased and field is increased, based on experimental data of electrical conductance in disordered graphene. It is found that the transition happens at a specific crossover field that can be described by an analytical expression obtained by equating the slopes at the crossover point (see Chapter 5.1). This paper has been cited by materials scientists based in Germany and France [Lippert et al. 2014] to support their interpretation of temperature-dependent variable-range hopping data on experimentally measured conductivity data in disordered graphene.

The second paper [Cheah and Kaiser 2014] extended the model presented in [Cheah et al. 2013] to disordered carbon materials of different dimensionalities, viz. 3D self-assembled carbon networks and quasi-1D highly conducting carbon-based polymers. In this second paper, we also investigated more fully the validity of the theoretically predicted equivalence between the temperature- and field-scaling parameters. We find that the validity holds only for certain samples. The reason for this deviation is still an open question (see Chapter 5.2).

The third paper which is currently in preparation, finds further evidence for the crossover model proposed by the two papers above, based on experimental data on electrical conductance in carbon nanotube networks. In addition, we correlate the electronic conduction mechanism to the morphology of the carbon nanotube networks based on SEM images of selected samples. In general, we found that the denser networks exhibited a significant remnant of their room temperature conductivity at zero Kelvin, consistent with fluctuation-assisted tunnelling theory, while less dense networks showed a conductance tending to zero near zero Kelvin, consistent with variable-range hopping (see Chapter 6).

A fourth paper is being planned on our novel temperature-assisted, field-driven VRH model as detailed in Chapter 5.4.

A.2 Presentations

Our work has been presented in national symposia and meetings at Tatum Park, Kapiti Coast (in June 2012); University of Canterbury, Christchurch (Nov. 2012); Masterton, Wairarapa (June 2013 and June 2014); and Victoria University, Wellington (Aug. 2012, June 2013 and Nov. 2013).

An invited talk was presented by the author to visiting American doctoral scholars – hosted by the MacDiarmid Institute, US National Science Foundation and Royal Society NZ – at the MacDiarmid Institute, Wellington in June 2012.

The following list details international conferences in which the author either presented or contributed to work presented by Prof Kaiser. The list includes work done as a research assistant which is not part of this thesis:

1. C. Y. Cheah and A. B. Kaiser, oral presentation: "Variable-range hopping transport in disordered carbon materials", *Sixth International Conference on Advanced Materials and Nanotechnology (AMN-6)*, 11-15 Feb. 2013, University of Auckland, Auckland, New Zealand.
2. A. B. Kaiser, C. A. Hewitt, C. Y. Cheah and D. L. Carroll, poster: "Thermoelectric and related properties of carbon-based materials", *International Winter School on Electronic Properties of Novel Materials (IWEPNM) 2013*, 2-9 Mar. 2013, Tirol, Austria.
3. A. B. Kaiser and C. Y. Cheah, invited talk: "Carbon materials: Conduction and thermoelectric properties and applications", *International Symposium on Carbon Electronics (ISCE) 2013*, 6-7 May 2013, Seoul National University, Seoul, Korea.
4. A. B. Kaiser, C. A. Hewitt, C. Y. Cheah and D. L. Carroll, oral presentation: "Conduction and thermoelectric properties of disordered carbon materials", *12th International Conference on Frontiers of Polymers and Advanced Materials (ICFPAM)*, 8-13 Dec. 2013, University of Auckland, Auckland, New Zealand.

5. A. B. Kaiser, C. Y. Cheah, A. Ansaldo, M. D. Lima and V. Skákalová, poster: "Conduction in CVD-grown single-wall carbon nanotube networks", *International Winter School on Electronic Properties of Novel Materials (IWEPNM) 2014*, 8-15 Mar. 2014, Tirol, Austria.

A.3 Publicity

The MacDiarmid Institute for Advanced Materials and Nanotechnology organized a nationwide science communication competition in its 9th *Student and Post-Doc Symposium* in November 2013. The challenge was for scientists to describe their research using only words from a list of the ten hundred most common ones, according to rules of the so-called Up-Goer Five Challenge.

My entry titled “We make power bits run around in dark stuff” won first placing and the winning entry was publicized in the official media channels of the institute as well as by Victoria University of Wellington. I was then interviewed by science journalist Ruth Beran. The article – titled “A better understanding of graphene” – is available online at <http://macdiarmid.ac.nz/newsroom/our-stories/a-better-understanding-of-graphene>.

Selected media coverage of my work by the MacDiarmid Institute for Advanced Materials and Nanotechnology and Victoria University of Wellington. Reproduced from <http://twitter.com/MacDiarmidInsti/status/406258470355091456> and <http://facebook.com/VictoriaUniversityofWellington/posts/748821521798147>.

Heading of the article "A better understanding of graphene" by Ruth Beran. Reproduced from <http://macdiarmid.ac.nz/newsroom/our-stories/a-better-understanding-of-graphene>.